

SPs		MOS-P-FET-e	=BSS 84 (SMD-Marking)	35	SOT-23				•BSS 84
SPS 5384		Si-N	=BD 529	13m	TO-202		•BD 529		•BD 529
SPS 5418		Si-N-Darl	=MPS-A13	7e	TO-92		BC 879	7c	•MPS-A13
SPS 5431		Si-P-Darl	=MPS-A65	7e	TO-92		BC 880	7c	•MPS-A65
SPS 5491		Si-P	=BC 393	2a	TO-5		MPS-U606	13m	•BC 393
SPU 2220	Itt	NMOS-IC	CTV, SECAM Chroma Processor	40-DIP					
SPU 2243		MOS-IC	CTV, SECAM Processor						
SQ		Si-N	=2SC3082K-Q (SMD-Marking)	35	SOT-23				•2SC3082K
SQ		Si-N	=2SC4100-Q (SMD-Marking)	35(2mm)	SOT-323				•2SC4100
SR		Si-N	=2SC2405-R (SMD-Marking)	35	SOT-23				•2SC2405
SR		Si-N	=2SC3929-R (SMD-Marking)	35(2mm)	SOT-323				•2SC3929
SR		MOS-N-FET-e	=BSS 131 (SMD-Marking)	35	SOT-23				•BSS 131
SR 1(D...M)		Si-Di					1N4007	31a	
SR 105 D		Opto	LED						
SRD 212		Opto							
SRP 10 A...K	Sym	Si-Di	=SRP 100A...K	31a	DO-41		•SRP 100A...K		•SRP 100A...K
SRP 100 A...K	Gie	Si-Di	Frr, 50...800V, 1A, Uf<1.3V(1A), <100...200ns	31a	DO-41		BYD 33M	31a	BYT 11/... BYV 26/... BYV 96/...
SRP 300 A...K	Gie	Si-Di	Frr, 50...800V, 3A, Uf<1.3V(3A), <100...200ns	31a	DO-27A		BYW 95 C(600V)	31a	BYT56/... BYW95/... BYW96/... BYW16/...
SRP 600 A...K	Gie	Si-Di	Frr, 50...800V, 6A, Uf<1.3V(6A), <100...200ns	31a	(9x9mmØ)		BY 500/800	31a	BY 500/... EGP 50A... G, MR 820... 824, ++
SRs		MOS-N-FET-e	=BSS 131 (SMD-Marking)	35	SOT-23				•BSS 131

SS

SS		Si-N	=2SC2405-S (SMD-Marking)	35	SOT-23				•2SC2405
SS		Si-N	=2SC3929-S (SMD-Marking)	35(2mm)	SOT-323				•2SC3929
SS		MOS-N-FET-e	=BSS 138 (SMD-Marking)	35	SOT-23				•BSS 138
SS 01		Si-N	=BC 237				BC 546	7a	•BC 237
SS 02		Si-N	=BC 237				BC 546	7a	•BC 237
SS 100		Si-P	=BC 307	2a			BC 556	7a	•BC 307
SS 101	Hfo	Si-P	LFS, -/33V, 0,05A, 0,25W	2a	TO-39		(BC 556)	7a	(BC 212, BC 257, BC 307, BC 557, ++)
SS 102	Hfo	Si-P	=SS 101: -/66V	2a	TO-39		(BC 556)	7a	(BC 212, BC 256, BC 266, BC 556, ++)
SS 106	Hfo	Si-N	LFS, 25V, 0,2A, 0,3W, <40/75ns	2a	TO-18		(BC 546)	7a	BSS 11...12, 2N3011, 2N2368...69(A), ++
SS 108	Hfo	Si-N	=SS 106: 40V	2a	TO-18		(BC 546)	7a	BSS 11, BSX 19...20, 2N2368...69(A), ++
SS 109	Hfo	Si-N	=SS 106: 20V	2a	TO-18		(BC 546)	7a	BSS 10...11, 2N3011, 2N2368...69(A), ++
SS 120	Hfo	Si-N	LFS, 60V, 0,6A, 0,8W	2a	TO-5		BC 141	2a	BC 140...141, 2N2218...2219(A), ++
SS 125	Hfo	Si-N	LFS, 30V, 0,5A, 0,6W	2a	TO-5		BC 141	2a	BC 140...141, 2N2218...2219(A), ++
SS 126	Hfo	Si-N	=SS 125: 60V	2a	TO-5		BC 141	2a	BC 140...141, 2N2218...2219(A), ++
SS 200	Hfo	Si-N	Nixie, 70V, 0,03A, 0,15W	40a	=TO-92		BF 420 A	7c	BF 297...299, BF 422, BSS 38, BSX 21, ++
SS 201	Hfo	Si-N	=SS 200: 100V	40a	=TO-92		BF 420 A	7c	BF 297...299, BF 422, BSS 38, BSX 21, ++
SS 202	Hfo	Si-N	=SS 200: 120V	40a	=TO-92		BF 420 A	7c	BF 297...299, BF 422, BSS 38, BSX 21, ++
SS 216	Hfo	Si-N	LFS, 20V, 0,1A, 0,2W, <100/500ns	40a	=TO-92		(BC 546)	7a	BSV 89...92, BSX 92...93, 2N2368...69, ++
SS 218	Hfo	Si-N	=SS 216: <35/60ns	40a	=TO-92		(BC 546)	7a	BSV 89...92, BSX 92...93, 2N2368...69, ++
SS 219	Hfo	Si-N	=SS 216: 35/30ns	40a	=TO-92		(BC 546)	7a	BSV 89...92, BSX 92...93, 2N2368...69, ++
SS 2648	Tix	Si-N	=BF 258				BF 259	2a	•BF 258
SS 3277		Si-N	=BF 258				BF 259	2a	•BF 258
SS 8050(B...D)	Sam	Si-N	LF Out, 40V, 1,5A, 1W, 190MHz	ISS8550	7e	TO-92	2SD1207	7c	MPS 650...651, 2SD1207, 2SD1227, 2SD1331+
SS 8550(B...D)	Sam	Si-P	LF Out, 40V, 1,5A, 1W, 120MHz	ISS8050	7e	TO-92	2SB892	7c(9mm)	MPS 750...751, 2SB892, 2SB911, 2SB978, ++
SS 9011(D...I)	Sam	Si-N	LF, AM/FM IF, 50V, 0,03A, 0,4W, 370MHz	7e	TO-92		BC 547, BF 255	7a, 7d	BC 237, BC 547, BF 240...41, BF 254...55++
SS 9012(D...H)	Sam	Si-P	LF Out, 40V, 0,5A, 0,625W	7e	TO-92		BC 327	7a	BC 327, BC 636, BC 638, BC 640, ++
SS 9013(D...H)	Sam	Si-N	LF Out, 40V, 0,5A, 0,625W	7e	TO-92		BC 337	7a	BC 337, BC 635, BC 637, BC 639, ++
SS 9014(A...D)	Sam	Si-N	Uni, in, 50V, 0,1A, 0,45W, 270MHz	7e	TO-92		BC 550	7a	BC 414, BC 550, 2SC2240, 2SC2675, ++
SS 9015(A...C)	Sam	Si-P	Uni, in, 50V, 0,1A, 0,45W, 190MHz	7e	TO-92		BC 560	7a	BC 416, BC 560, 2SA970, 2SA1137, ++
SS 9016(D...I)	Sam	Si-N	AM/FM, 30V, 25mA, 0,4W, 620MHz	7e	TO-92		BF 255	7d	BF 240...241, BF 254...255, BF 594...595, ++
SS 9018(D...I)	Sam	Si-N	AM/FM, 30V, 0,05A, 0,4W, 1100MHz	7e	TO-92		BF 255, BF 959	7d	BF 225, BF 255, BF 314, BF 505, BF 507++
SSE 200	Hfo	Si-N	=SS 200: SMD	35a	SOT-23				BC 846, BCV 71...72, BSS 64, BSR 19(A)
SSE 201	Hfo	Si-N	=SS 201: SMD	35a	SOT-23				BSS 64, BSR 19(A), 2SC3340, 2SC4050
SSE 202	Hfo	Si-N	=SS 202: SMD	35a	SOT-23				BSS 64, BSR 19(A), 2SC3340, 2SD4050
SSE 216	Hfo	Si-N	=SS 216: SMD	35a	SOT-23				BSV 52, 2SC3578, 2SC3757
SSE 219	Hfo	Si-N	=SS 219: SMD	35a	SOT-23				BSV 52, 2SC3578, 2SC3757
SSE 350	Hfo	Si-N-Darl	Uni, 60V, 0,5A, hFE>2000	39b	SOT-89				BCV 49, BST 51...52, 2SD1625
SSE 351	Hfo	Si-N-Darl	=SSE 350: 80V	39b	SOT-89				BCV 49, BST 51...52, 2SD1625
SSE 352	Hfo	Si-N-Darl	=SSE 350: 90V	39b	SOT-89				BST 52
SSE 360	Hfo	Si-P-Darl	Uni, 60V, 0,5A, hFE>2000	39b	SOT-89				BCV 48, BST 61...62, 2SB1125
SSE 361	Hfo	Si-P-Darl	=SSE 360: 80V	39b	SOT-89				BCV 48, BST 61...62, 2SB1125
SSE 362	Hfo	Si-P-Darl	=SSE 360: 90V	39b	SOT-89				BST 62
(s)5F		MOS-P-FET-e	=SP 0610T (SMD-Marking)	35	SOT-23				•SP 0610T
SSG		MOS-N-FET-e	=SN 7002 (SMD-Marking)	35	SOT-23				•SN 7002
(s)SH		MOS-N-FET-e	=BSS 119 (SMD-Marking)	35	SOT-23				•BSS 119
SSH 3 N70	Sam	MOS-N-FET-e	VFET, 700/20V, 3/12A, 75W, on<5Ω(1,5A), <135/210ns	18p	TO-3P				BUZ 307, 2SK726, 2SK954, 2SK1339, ++
SSH 4 N45	Sam	MOS-N-FET-e	VFET, 450/20V, 4/10A, 75W, on<1,5Ω(2A), <150/300ns	18p	TO-3P				2SK1213, 2SK1403
SSH 4 N50	Sam	MOS-N-FET-e	=SSH 4N45: 500/20V	18p	TO-3P				2SK1213, 2SK1403
SSH 4 N55	Sam	MOS-N-FET-e	VFET, 550/20V, 4/16A, 75W, on<2,5Ω(2A), <190/160ns	18p	TO-3P				2SK1213, 2SK1403
SSH 4 N60	Sam	MOS-N-FET-e	=SSH 4N55: 600/20V	18p	TO-3P				2SK1213, 2SK1403
SSH 4 N70	Sam	MOS-N-FET-e	VFET, 700/20V, 4/25A, 125W, <2,5Ω(2A), <210/430ns	18p	TO-3P				2SK695, 2SK727, 2SK793, 2SK1760, ++
SSH 5 N35	Sam	MOS-N-FET-e	VFET, 350/20V, 5/12A, 75W, on<1Ω(2,5A), <150/300ns	18p	TO-3P				2SK2264
SSH 5 N40	Sam	MOS-N-FET-e	=SSH 5N35: 400/20V	18p	TO-3P				2SK2264
SSH 6 N55	Sam	MOS-N-FET-e	VFET, 550/20V, 6/24A, 125W, <1,2Ω(3A), <210/320ns	18p	TO-3P				BUZ 332A, BUZ 305, 2SK684, 2SK1032
SSH 6 N60	Sam	MOS-N-FET-e	=SSH 6N55: 600/20V	18p	TO-3P				BUZ 332A, BUZ 305, 2SK684, 2SK1032
SSH 6 N70	Sam	MOS-N-FET-e	VFET, 700/20V, 6/24A, 150W, <1,4Ω(3A), <290/600ns	18p	TO-3P				BUZ 305, 2SK684, 2SK1032
SSH 7 N12	Sam	MOS-N-FET-e	VFET, 120/20V, 7/18A, 75W, <0,7Ω(3,5A), <170/100ns	18p	TO-3P				2SK405, 2SK631, 2SK633, 2SK1529
SSH 7 N15	Sam	MOS-N-FET-e	=SSH 7N12: 150/20V	18p	TO-3P				2SK405, 2SK631, 2SK633, 2SK1529
SSH 7 N18	Sam	MOS-N-FET-e	VFET, 180/20V, 7/18A, 75W, <0,7Ω(3,5A), <200/150ns	18p	TO-3P				2SK400, 2SK633, 2SK1529
SSH 7 N20	Sam	MOS-N-FET-e	=SSH 7N18: 200/20V	18p	TO-3P				2SK400, 2SK633
SSH 8 N12	Sam	MOS-N-FET-e	VFET, 120/20V, 8/25A, 75W, on<0,5Ω(4A), <200/150ns	18p	TO-3P				2SK405, 2SK631, 2SK633, 2SK1529
SSH 8 N15	Sam	MOS-N-FET-e	=SSH 8N12: 150/20V	18p	TO-3P				2SK405, 2SK631, 2SK633, 2SK1529
SSH 8 N18	Sam	MOS-N-FET-e	VFET, 180/20V, 8/25A, 75W, on<0,4Ω(4A), <190/300ns	18p	TO-3P				2SK400, 2SK633, 2SK1529
SSH 8 N20	Sam	MOS-N-FET-e	=SSH 8N18: 200/20V	18p	TO-3P				2SK400, 2SK633
SSH 8 N55	Sam	MOS-N-FET-e	VFET, 550/20V, 8/32A, 150W, <0,5Ω(4A), <290/600ns	18p	TO-3P				BUZ 332A, BUZ 334, 2SK1968
SSH 8 N60	Sam	MOS-N-FET-e	=SSH 8N55: 600/20V	18p	TO-3P				BUZ 332A, BUZ 334, 2SK1968
SSH 10 N05	Sam	MOS-N-FET-e	VFET, 50/20V, 10/28A, 75W, <0,28Ω(5A), <170/110ns	18p	TO-3P				2SK399, 2SK500, 2SK631
SSH 10 N06	Sam	MOS-N-FET-e	=SSH 10N05: 60/20V	18p	TO-3P				2SK399, 2SK500, 2SK631
SSH 10 N08	Sam	MOS-N-FET-e	VFET, 80/20V, 10/30A, 75W, <0,33Ω(5A), <200/150ns	18p	TO-3P				2SK399, 2SK631
SSH 10 N10	Sam	MOS-N-FET-e	=SSH 10N08: 100/20V	18p	TO-3P				2SK399, 2SK631