

| TYPE NO | CONSTRUCTION | PACKAGE & PINOUT | V _{DS} | | I _D | T _J | P _{TOT} | V _{GS(OFF)} or V _{GS(TH)} | I _{LOSS} or I _{D(OFF)} | G _{FS} | R _{DS(ON)} | C _{ISS} | C _{RSS} | USE | MNF | SUBSTITUTE | | |
|-----------|--------------|------------------|-----------------|-----|----------------|----------------|------------------|---|--|-----------------|---------------------|------------------|------------------|-----|-----|------------|---------|--------|
| | | | MAX | MAX | | | | | | | | | | | | | MAX | MAX |
| 1G2 | NJD | T072 | Ek | 50V | 16mA | 200C | 300mWF | 6.5Vmx | 16mAmx | 4mSnn | - | 7P5 | - | ALG | OBS | BFW61 | 2N3822 | |
| 2G2 | NJD | T072 | Ek | 50V | 8mA | 200C | 300mWF | 4Vmx | 8mAmx | 2mSnn | - | 7P5 | - | ALG | OBS | BFW12 | 2N3822 | |
| 2N2386 | PJD | T039 | F | 20V | 20mA | 200C | 500mWF | 8Vmx | 0.9/9mA | 1mSnn | - | 50P | - | ALG | TEL | BF320 | 2N2386A | |
| 2N2386A | PJD | T039 | F | 20V | 15mA | 200C | 500mWF | 8Vmx | 1/1.5mA | 2.2/5mS | - | 18P | - | ALG | TEL | BF320 | 2N2386A | |
| 2N2497 | PJD | T039 | F | 20V | 3mA | 200C | 500mWF | 5Vmx | 1/3mA | 1/2mS | - | 32P | - | ALG | TEL | BF320A | 2N3329 | |
| 2N2497JAN | PJD | T039 | F | 20V | 10mA | 200C | 500mWF | 5Vmx | 3mAmx | 1/2mS | - | 32P | - | RLS | TEL | - | 2N2497 | |
| 2N2498 | PJD | T039 | F | 20V | 8mA | 200C | 500mWF | 6Vmx | 2/6mA | 1.5/3mS | - | 32P | - | ALG | TEL | BF320B | 2N3330 | |
| 2N2498JAN | PJD | T039 | F | 20V | 10mA | 200C | 500mWF | 6Vmx | 6mAmx | 1.5/3mS | - | 32P | - | ALG | TEL | - | 2N2498 | |
| 2N2499 | PJD | T039 | F | 20V | 15mA | 200C | 500mWF | 8Vmx | 5/15mA | 2/4mS | - | 32P | - | ALG | TEL | BF320 | 2N2386A | |
| 2N2499A | PJD | T039 | F | 20V | 15mA | 200C | 500mWF | 10Vmx | 5/15mA | 1.7mStp | - | 32P | - | ALG | TEL | BF320 | 2N3909 | |
| 2N2499JAN | PJD | T039 | F | 20V | 25mA | 200C | 500mWF | 8Vmx | 15mA | 2/4mS | - | 600R | - | RLS | TEL | - | 2N2498 | |
| 2N2500 | PJD | T039 | F | 20V | 6mA | 200C | 500mWF | 8Vmx | 1/6mA | 1/2.2mS | - | 32P | - | ALG | TEL | BF320B | 2N3332 | |
| 2N2500JAN | PJD | T039 | F | 20V | 10mA | 200C | 500mWF | 6Vmx | 6mAmx | 1/2.2mS | - | 32P | - | RLS | TEL | - | 2N2499 | |
| 2N2606 | PJD | T018 | F | 30V | 500µA | 175C | 300mWF | 1/4V | 100/500µA | 100µSnn | - | 6P0 | - | ALG | INS | BF320A | 2N2843 | |
| 2N2606JAN | PJD | T018 | F | 30V | - | 200C | 300mWF | 4Vmx | 500µAmx | 110/600µS | - | 6P0 | - | ALG | INS | BF320A | 2N2606 | |
| 2N2607 | PJD | T018 | F | 30V | 1500µA | 175C | 300mWF | 1/4V | - | - | - | 10P | - | ALG | INS | BF320A | 2N2844 | |
| 2N2607JAN | PJD | T018 | F | 30V | - | 200C | 300mWF | 4Vmx | - | - | - | 10P | - | ALG | INS | BF320A | 2N2607 | |
| 2N2608 | PJD | T018 | F | 30V | 4500µA | 175C | 300mWF | 1/4V | 0.9/4.5mA | 1mSnn | - | 17P | - | ALG | SLX | BF320A | 2N5460 | |
| 2N2608CHP | PJD | CHIP | - | 30V | 10mA | 200C | 300mWF | 1/4V | 0.9/4.5mA | 1mSnn | - | 17P | - | ALG | SLX | - | 2N2608 | |
| 2N2608JAN | PJD | T018 | F | 30V | - | 200C | 300mWF | 4Vmx | 4.5mAmx | 1/2.5mS | - | 17P | - | ALG | SLX | BF320B | 2N2608 | |
| 2N2609 | PJD | T018 | F | 30V | 10mA | 175C | 300mWF | 1/4V | 2/10mA | 2.5mSnn | - | 30P | - | ALG | INS | BF320 | 2N5464 | |
| 2N2609CHP | PJD | CHIP | - | 30V | 10mA | 200C | 300mWF | 1/4V | - | - | - | 30P | - | ALG | SLX | - | 2N2609 | |
| 2N2609JAN | PJD | T018 | F | 30V | - | 200C | 300mWF | 4Vmx | 10mAmx | 2.5/6.2mS | - | 30P | - | ALG | SLX | BF320B | 2N2609 | |
| 2N2620 | NJD | T018 | B | 50V | 200mA | 175C | 300mWF | 4Vmx | 1.5/5mA | 100µSnn | - | 30P | - | ALG | OBS | BFW12 | 2N3822 | |
| 2N2794 | PJD | T05 | B | 20V | 5mA | 175C | 400mWF | 1.5Vmx | 1.5/5mA | 100µSnn | - | 30P | - | ALG | OBS | BF320A | 2N3820 | |
| 2N2841 | PJD | T018 | F | 30V | 2200µA | 200C | 300mWF | 1.7Vmx | 125µAmx | 80µSnn | - | 6P0 | - | RLS | SLX | J177 | 2N3573 | |
| 2N2842 | PJD | T018 | F | 30V | 2200µA | 200C | 300mWF | 1.7Vmx | 325µAmx | 180µSnn | - | 10P | - | RLS | SLX | J177 | 2N3574 | |
| 2N2843 | PJD | T018 | F | 30V | 2200µA | 200C | 300mWF | 1.7Vmx | 0.2/1mA | 540µSnn | - | 10P | - | RLS | SLX | J177 | 2N3574 | |
| 2N2844 | PJD | T018 | F | 30V | 2200µA | 200C | 300mWF | 1.7Vmx | 0.4/2.2mA | 1.4mSnn | - | 30P | - | RLS | SLX | BF320A | 2N2606 | |
| 2N3066 | NJD | T018 | E | 50V | 4mA | 200C | 300mWF | 9.5Vmx | 0.8/4mA | 0.4/1mS | - | 10P | 1P5 | RLS | ALX | BF800 | 2N4302 | |
| 2N3066A | NJD | T018 | E | 50V | 4mA | 200C | 300mWF | 9.5Vmx | 0.8/4mA | 0.4/1mS | - | 10P | 1P5 | ALN | SLX | BF800 | 2N4302 | |
| 2N3067 | NJD | T018 | E | 50V | 4mA | 200C | 300mWF | 4.5Vmx | 0.2/1mA | 0.3/1mS | - | 10P | 1P5 | ALG | SLX | BF800 | 2N3686A | |
| 2N3067A | NJD | T018 | E | 50V | 4mA | 200C | 300mWF | 4.5Vmx | 0.2/1mA | 0.3/1mS | - | 10P | 1P5 | ALG | SLX | BF800 | 2N3686A | |
| 2N3068 | NJD | T018 | E | 50V | 4mA | 200C | 300mWF | 2.2Vmx | 250µAmx | 0.2/1mS | - | 10P | 1P5 | ALG | SLX | BF800 | 2N3687A | |
| 2N3068A | NJD | T018 | E | 50V | 4mA | 200C | 300mWF | 2.2Vmx | 250µAmx | 0.2/1mS | - | 10P | 1P5 | ALG | SLX | BF800 | 2N3687A | |
| 2N3069 | NJD | T018 | E | 50V | 10mA | 200C | 350mWF | 9.5Vmx | 2/10mA | 1/2.5mS | - | 15P | 1P5 | ALG | SLX | BFW12 | 2N3822 | |
| 2N3069A | NJD | T018 | E | 50V | 10mA | 200C | 350mWF | 9.5Vmx | 2/10mA | 1/2.5mS | - | 15P | 1P5 | ALN | SLX | BFW56 | 2N3685A | |
| 2N3070 | NJD | T018 | E | 50V | 10mA | 200C | 350mWF | 4.5Vmx | 0.5/2.5mA | 0.75/2.5mS | - | 15P | 1P5 | ALG | SLX | BF808 | 2N3685A | |
| 2N3070A | NJD | T018 | E | 50V | 10mA | 200C | 350mWF | 4.5Vmx | 0.5/2.5mA | 0.75/2.5mS | - | 15P | 1P5 | ALN | SLX | BF808 | 2N3685A | |
| 2N3071 | NJD | T018 | E | 50V | 10mA | 200C | 350mWF | 2.2Vmx | 100/600µA | 0.5/2.5mS | - | 15P | 1P5 | ALG | SLX | BF347 | 2N3687A | |
| 2N3084 | NJD | T05 | B | 30V | 3mA | 200C | 400mWF | 10Vmx | 3mAmx | 0.4/2mS | - | 14P | - | ALG | OBS | BF808 | 2N3685 | |
| 2N3085 | NJD | T018 | B | 30V | 3mA | 200C | 400mWF | 10Vmx | 3mAmx | 0.4/2mS | - | 14P | - | ALG | TEL | BF808 | 2N3621 | |
| 2N3086 | NJD | T05 | B | 40V | 3mA | 200C | 400mWF | 10Vmx | 3mAmx | 0.4/2mS | - | 14P | - | ALG | OBS | BF808 | 2N3685 | |
| 2N3087 | NJD | T018 | B | 40V | 3mA | 200C | 400mWF | 10Vmx | 3mAmx | 0.4/2mS | - | 14P | - | ALG | TEL | BF808 | 2N3621 | |
| 2N3088 | NJD | T05 | B | 15V | 3mA | 200C | 400mWF | 5Vmx | 2mAmx | 0.4/4mS | - | 14P | - | ALG | OBS | BF808 | 2N4339 | |
| 2N3088A | NJD | T05 | B | 15V | 3mA | 200C | 400mWF | 5Vmx | 2mAmx | 0.4/2mS | - | 14P | - | ALG | OBS | BF808A | 2N3821 | |
| 2N3089 | NJD | T018 | B | 30V | 2mA | 200C | 400mWF | 1/5V | 0.5/2mA | 0.3/2mS | - | 6P0 | 2P0 | ALG | SLX | BF800 | 2N3687A | |
| 2N3089A | NJD | T018 | B | 30V | 2mA | 200C | 400mWF | 1/5V | 0.5/2mA | 0.3/2mS | - | 6P0 | 2P0 | ALN | SLX | BF200 | 2N3687A | |
| 2N3112 | PJD | T018 | F | 20V | 10mA | 200C | 300mWF | 4Vmx | 180µAmx | 50/120µS | - | 3P5 | - | ALG | SLX | - | 2N2606 | |
| 2N3113 | PJD | T018 | F | 20V | 1mA | 200C | 300mWF | 4Vmx | 180µAmx | 50µSnn | - | 2P0 | - | ALG | SLX | - | 2N3573 | |
| 2N3277 | PJD | T012 | Fk | 25V | 10mA | 200C | 400mWF | 5Vmx | 150/500µA | 100µSnn | - | 4P5 | - | ALG | INS | - | 2N2606 | |
| 2N3278 | PJD | T012 | Fk | 25V | 10mA | 200C | 400mWF | 5Vmx | 500/900µA | 150µSnn | - | 4P5 | - | ALG | INS | - | 2N2606 | |
| 2N3328 | PJD | T072 | Fk | 20V | 1mA | 200C | 300mWF | 6Vmx | 1mA | 100µSnn | - | 4P0 | - | ALG | SLX | BF320A | 2N5265 | |
| 2N3329 | PJD | T072 | Fk | 20V | 15mA | 200C | 300mWF | 5Vmx | 1/3mA | 1/2mS | - | 20P | - | ALN | SLX | BF320A | 2N5266 | |
| 2N3329CHP | PJD | CHIP | - | 20V | 3mA | 200C | 300mWF | 5Vmx | 1/3mA | 1/2mS | - | 20P | - | ALG | SLX | - | 2N5266 | |
| 2N3329JAN | PJD | T072 | Fk | 20V | 10mA | 200C | 300mWF | 5Vmx | 3mA | 1/2mS | - | 1K0 | 20P | - | ALG | SLX | BF320A | 2N3329 |
| 2N3330 | PJD | T072 | Fk | 20V | 15mA | 200C | 300mWF | 6Vmx | 2/6mA | 1.5/3mS | - | 800R | 20P | - | ALN | SLX | BF320B | 2N3378 |
| 2N3330CHP | PJD | CHIP | - | 20V | 6mA | 200C | 300mWF | 6Vmx | 2/6mA | 1.5/3mS | - | 800R | 20P | - | ALG | SLX | - | 2N3378 |
| 2N3330JAN | PJD | T072 | Fk | 20V | 10mA | 200C | 300mWF | 6Vmx | 6mA | 1.5/3mS | - | 800R | 20P | - | ALG | SLX | BF320B | 2N3330 |
| 2N3331 | PJD | T072 | Fk | 20V | 15mA | 200C | 300mWF | 8Vmx | 5/15mA | 2/4mS | - | 600R | 20P | - | ALN | SLX | BF320C | 2N5482 |
| 2N3331CHP | PJD | CHIP | - | 20V | 15mA | 200C | 300mWF | 8Vmx | 5/15mA | 2/4mS | - | 600R | 20P | - | ALG | SLX | - | 2N3331 |
| 2N3331JAN | PJD | T072 | Fk | 20V | 10mA | 200C | 300mWF | 8Vmx | 15mA | 2/4mS | - | 600R | 20P | - | ALG | SLX | BF320 | 2N3331 |
| 2N3332 | PJD | T072 | Fk | 20V | 15mA | 200C | 300mWF | 6Vmx | 1/6mA | 1/2.2mS | - | 20P | - | ALN | SLX | BF320B | 2N2500 | |
| 2N3332JAN | PJD | T072 | Fk | 20V | 10mA | 200C | 300mWF | 6Vmx | 6mA | 1/2.2mS | - | 800R | 20P | - | ALG | SLX | BF320B | 2N3332 |
| 2N3333 | PJD | T089 | - | 20V | 10mA | 200C | 400mWF | 1.6Vmx | 1mA | 0.8/1.8mS | - | 30P | - | DUA | TIS | - | 2N3332 | |
| 2N3334 | PJD | T089 | - | 20V | 10mA | 200C | 400mWF | 1.6Vmx | 1mA | 0.6/1.8mS | - | 30P | - | DUA | TIS | - | 2N3334 | |
| 2N3335 | PJD | T089 | - | 20V | 10mA | 200C | 400mWF | 1.8Vmx | 1mA | 0.8/1.8mS | - | 30P | - | DUA | TIS | - | 2N3335 | |
| 2N3336 | PJD | T089 | - | 20V | 10mA | 200C | 400mWF | 1.6Vmx | 1mA | 0.6/1.8mS | - | 30P | - | DUA | TIS | - | 2N3336 | |
| 2N3365 | NJD | T018 | E | 40V | 4mA | 150C | 300mWF | 11.5Vmx | 0.8/4mA | 0.4/2mS | - | 15P | 2P5 | ALG | SLX | BF808 | 2N3685A | |
| 2N3366 | NJD | T018 | E | 40V | 4mA | 150C | 300mWF | 6.5Vmx | 0.2/1mA | 0.25/1mS | - | 15P | 2P5 | ALG | SLX | BF800 | 2N3687A | |
| 2N3367 | NJD | T018 | E | 40V | 4mA | 150C | 300mWF | 2.2Vmx | 250µAmx | 0.1/1mS | - | 15P | 2P5 | ALG | SLX | BF800 | 2N3687A | |
| 2N3368 | NJD | T018 | E | 40V | 12mA | 150C | 300mWF | 11.5Vmx | 2/12mA | 1/4mS | - | 20P | 3P0 | ALG | SLX | BFW61 | 2N5458 | |
| 2N3369 | NJD | T018 | E | 40V | 12mA | 150C | 300mWF | 6.5Vmx | 2.5mA | 0.6/2.5mS | - | 20P | 3P0 | ALG | SLX | BF347 | 2N3821 | |
| 2N3370 | NJD | T018 | E | 40V | 12mA | 150C | 300mWF | 3.2Vmx | 100/600µA | 0.3/2.5mS | - | 20P | 3P0 | ALG | SLX | BF800 | 2N3687A | |
| 2N3376 | PJD | T072 | Fk | 30V | 50mA | 175C | 300mWF | 1/5V | 0.6/6mA | 0.8/2.3mS | - | 1K5 | 10P | - | RLS | SLX | BF320B | 2N3376 |