16. DIRECT REPLACEMENT TRANSISTORS

LINE No.	[1] TYPE NO. TO BE REPLACED	The Following Type Numbers Are Claimed By The Manufacturer To Replace The Type Number In The Left Column											
		TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.	TYPE NO.	MFR.
1▼	100T2	2N4347	RCA										
2▼	104T2	2N6253	RCA										
3▼	108T2	2N5039	RCA										
4▼	109T2	2N6354	RCA										
5▼	182T2A	BUX16	RCA										
6▼	182T2B	BUX16	RCA										
7▼	182T2C	BUX16	RCA										
8▼	183T2A	BUX16	RCA										
9▼	183T2B	BUX16	RCA										
10▼	183T2C	BUX16	RCA										
11▼	184T2A	BUX16	RCA										
12▼	184T2B	BUX16	RCA										
13▼	184T2C	BUX16	RCA										
14▼	185T2A	BUX16A	RCA										
15▼	185T2B	BUX16A	RCA										
16▼	185T2C	BUX16A	RCA										
17▼	40250	2N3054	RCA	PTC112	MAL								
18▼	40251	2N3055	RCA										
19▼	40369	2N5877	MOTA										
20▼	40372	2N3054	MOTA										
21▼	40373	2N3441	MOTA										
22▼	40374	2N3583	MOTA										
23▼	40375	2N5428	MOTA										
24▼	40411	MJ802	MOTA										
25▼	40513	MJE3055T	MOTA										
26▼	40514	MJE3055T	MOTA										
27▼	40542	2N5978	MOTA										
28▼	40543	2N5978	MOTA										
29▼	40632	TIP41A	MOTA										
30▼	40636	2N5878	MOTA										
31▼	40829	2N6316	MOTA										
32▼	40830	2N6315	MOTA										
33▼	40831	2N6315	MOTA										
34▼	40850	2N4240	MOTA										
35▼	40852	2N6543	MOTA										
36▼	40853	2N6546	MOTA										
37▼	40854	2N6546	MOTA										
38▼	40871	TIP41C	MOTA										
39▼	40872	TIP42C	MOTA										
40▼	40873	TIP41B	MOTA										
41▼	40874	TIP41B	MOTA										
42▼	40875	TIP41C	MOTA										
43▼	40876	TIP41A	MOTA										
44▼	40885	MPSU10	MOTA										
45▼	40886	MPSU10	MOTA										
46▼	40887	2N6559	MOTA										
47▼	40910	2N4231A	MOTA										
48▼	40912	2N4233A	MOTA										
49▼	40913	2N5050	MOTA										
50▼	41012	2N5038	MOTA										
51▼	41013	2N5039	MOTA										
52▼	41500	TIP29	MOTA										
53▼	41501	TIP30	MOTA										
54▼	41504	TIP31	MOTA										
55▼	41506	2N6543	MOTA										
56▼	43104	2N5631	MOTA										
57▼	BC119	2N697	RCA	PTC125	MAL								
58▼	BC120	2N697	RCA	PTC125	MAL								
59▼	BC139	40406	RCA	PTC127	MAL	2N2904	PHIN						
60▼	BC140	2N5321	RCA										
61▼	BC141	2N5320	RCA	PTC125	MAL								
62▼	BC142	40360	RCA	2N2218A	PHIN								
63▼	BC143	40595	RCA	PT127	MAL	2N2905A	PHIN						
64▼	BC144	40594	RCA	PT125	MAL	2N2218A	PHIN						
65▼	BC160	2N5323	RCA										
66▼	BC161	2N5322	RCA										
67▼	BC300	2N1893	RCA	BD139	PHIN								
68▼	BC301	2N699	RCA	BD139	PHIN								
69▼	BC302	2N2270	RCA	BSX59	PHIN								
70▼	BC303	2N4314	RCA	BD140	PHIN								
71▼	BC304	2N4037	RCA	BC640	PHIN								
72▼	BC310	2N1893	RCA										
73▼	BC311	2N4314	RCA										
74▼	BC323	2N5320	RCA										
75▼	BC324	2N5320	RCA										
76▼	BC429	2N2270	RCA										
77▼	BC430	2N2270	RCA										
78▼	BC440	2N5321	RCA	BC635	PHIN								
79▼	BC441	2N5320	RCA	BC637	PHIN								
80▼	BC460	2N5323	RCA										
81▼	BC461	2N5322	RCA										
82▼	BCW44	40360	RCA										
83▼	BCW45	40362	RCA										
84▼	BCW77-16	2N1711	RCA										
85▼	BCW78-16	2N1711	RCA										
86▼	BCW79-16	2N4037	RCA										
87▼	BCW80-16	2N4037	RCA										
88▼	BCY40	2N4037	RCA										
89▼	BCY54	2N4036	RCA										
90▼	BD115	BF258	RCA										
91▼	BD116	2N3055	RCA	PTC906	MAL								
92▼	BD141	2N4347	RCA	PTC118	MAL								
93▼	BD144	BUX18C	RCA	PTC129A	MAL								
94▼	BD148	BDY71	RCA										
95▼	BD149	BDY71	RCA										
96▼	BD160	2N6510	RCA										
97▼	BD162	40250	RCA										
98▼	BD163	2N6260	RCA										
99▼	BD215	2N3584	RCA										
100▼	BD216	2N3585	RCA										
101▼	BD301	BD243	RCA	PTC169	MAL	BD201	PHIN						
102▼	BD302	BD244	RCA	PTC168	MAL	BD202	PHIN						
103▼	BD303	BD243A	RCA	PTC169	MAL	BD203	PHIN						
104▼	BD304	BD244A	RCA	PTC168	MAL	BD204	PHIN						
105▼	BD311	2N6471	RCA	PTC173	MAL								
106▼	BD312	2N6246	RCA	PTC149	MAL								
107▼	BD313	2N6472	RCA	PTC173	MAL								
108▼	BD314	2N6247	RCA	PTC172	MAL								
109▼	BD315	2N6472	RCA										
110▼	BD316	2N6247	RCA	PTC172	MAL								

Datasheet.Directory