

CS 3,5-05FZ2	50Hz-Thy		13e	TAG 626-600	17e	4
CS 0014	Si-Di	≈BA 100	31a	1N4148	31a	
CS 0080	Si-Di	≈BA 100	31a	1N4148	31a	
CS 1245(F....T)	Si-N	≈BC 337		BC 337	7a	
CS 1250(E,F)	Si-N	≈BC 639		BC 639	7c	
CS 1251(E,F)	Si-P	≈BC 640		BC 640	7c	
CS 1303	Si-P	≈BC 640		BC 640	7c	
CS 1312 F,G	Si-P	≈BF 450	2a	BF 324	7a	
CS 1312 H	Si-P	≈BC 309	2a	BC 560	7a	
CS 1312 I	Si-P	≈BC 307	2a	BC 560	7a	
CS 1506 F,G	Si-P	≈BC 307	2a	BC 556	7a	
CS 1508 E,G	Si-N	≈BF 255	2a	BF 255	7d	
CS 1509 E,F	Si-N	≈BF 254	2a	BF 255	7d	
CS 1655	Si-N	≈BF 494	7c	BF 255	7d	
CS 1659	Si-N	≈BC 338	7c	BC 337	7a	
CS 1660	Si-P	≈BC 328	7c	BC 327	7a	
CS 1702	Si-N	≈BC 337		BC 337	7a	
CS 1774	Si-N	≈BC 548	7c	BC 546	7a	
CS 1909	Si-N	≈BC 337	2a	BC 337	7a	
CS 1910	Si-P	≈BC 327	2a	BC 327	7a	
CS 1914(H)	Si-P	≈BC 307	2a	BC 556	7a	
CS 1978(A)	Si-N	≈BC 337	7e	BC 337	7a	
CS 5609	Si-N	≈BC 337		BC 337	7a	
CS 5610	Si-P	≈BC 327		BC 327	7a	
CS 6203 H,I	Si-P	≈BC 309	7e	BC 560	7a	
CS 6208	Si-N	≈BC 337	2a	BC 337	7a	
CS 6209	Si-P	≈BC 327	2a	BC 327	7a	
CS 6305(A)	Si-P	≈BC 307	2a	BC 556	7a	
CS 9003	Si-N	≈BC 547	7	BC 546	7a	
CS 9010	Si-N	≈BC 547	7e	BC 546	7a	
CS 9011(D....I)	Si-N	=SS 9011	7e	↳SS 9011		
CS 9012(D....I)	Si-P	=SS 9012	7e	↳SS 9012		
CS 9013(D....I)	Si-N	=SS 9013	7e	↳SS 9013		
CS 9014(A....C)	Si-N	=SS 9014	7e	↳SS 9014		
CS 9015(A....C)	Si-P	=SS 9015	7e	↳SS 9015		
CS 9016(D....H)	Si-N	=SS 9016	7e	↳SS 9016		
CS 9017	Si-N	AM/FM, -/18V	7e	BF 255	7d	
CS 9018(D....H)	Si-N	=SS 9018	7e	↳SS 9018		
CS 9020(G,H)	Si-P	≈BF 450	7e	BF 324	7a	
CS 9021	Si-N	≈BF 495	7	BF 255	7d	
CS 9022	Si-N	≈BC 547	7	BC 546	7a	
CS 9102(B)	Si-P	≈BC 640		BC 640	7c	
CS 9103(B,C)	Si-N	≈BC 639		BC 639	7c	
CS 9126	Si-N	≈BC 548	7e	BC 546	7a	
CS 9127	Si-P	≈BC 558	7e	BC 556	7a	
CSF 02 AM 1	F-Thy	50V, 0,26A(Ta=45°C), Igt/Ih<0,25/<2,3mA	7b	BRX 49	7a	
CSF 02 AM 2	F-Thy	=CSF02AM1: 100V	7b	BRX 49	7a	
CSF 02 AM 4	F-Thy	=CSF02AM1: 200V	7b	BRX 49	7a	
CSF 02 AM 8	F-Thy	=CSF02AM1: 400V	7b	BRX 49	7a	
CSF 02 AM 10	F-Thy	=CSF02AM1: 500V	7b	(TAG 626-600)	17e	6
CSM 2B2	50Hz-Thy	200V, 2A(Tc=71°), Igt/Ih=1/1,5mA	13b	(TIC 106M)	17e	4
CSM 2B4	50Hz-Thy	=CSM2B2: 400V	13b	(TIC 106M)	17e	4
CSM 3B2	50Hz-Thy	200V, 3A(Tc=63°), Igt/Ih=1/1,5mA	13b	(TIC 106M)	17e	4
CSM 3B4	50Hz-Thy	=CSM3B2: 400V	13b	(TIC 106M)	17e	4
CT 005...06	Si-Br	50...600V, 2A	33(+maxim-)	B380C5000	33(+maxim-)	