

BF 222 [Riz]	Si-N	HF/ZF, 135MHz	2a	BF 255	7d
BF 222 [SGS]	Si-N	FM-V-re, 400MHz	5g	BF 255	7d
BF 223 [AEG]	Si-N	TV-ZF, 750MHz	11d	BF 199	7d
BF 223 [Riz]	Si-N	HF/ZF, 135MHz	2a	BF 255	7d
BF 224	Si-N	TV-ZF, VHF-M/O, 45V, 700MHz	7d	BF 199	7d
BF 225	Si-N	TV-ZF-re, VHF-V, 700MHz	7d	BF 199	7d
BF 226	Si-N	FM-M/O, 250MHz	5k	BF 255	7d
BF 231 [Riz]	Si-N	AM/FM/VHF, 800MHz	2a	BF 199	7d
BF 232 [Riz]	Si-N	AM/FM/VHF, 300MHz	2a	BF 199	7d
BF 232 [Siemens]	Si-N	TV-ZF, 600MHz	5k	BF 199	7d
BF 233 [CSF,SGS]	Si-N	AM/FM-ZF, 500MHz	8d	BF 255	7d
BF 233 [Riz]	Si-N	AM/FM/VHF, 800MHz	2a	BF 199	7d
BF 234 [CSF,SGS]	Si-N	AM-V/M/O/ZF, 500MHz	8d	BF 255	7d
BF 234 [Riz]	Si-N	AM/FM/VHF, 300MHz	2a	BF 199	7d
BF 235 [CSF,SGS]	Si-N	FM-V/M, 500MHz	8d	BF 255	7d
BF 235 [Riz]	Si-N	AM/FM/VHF, 400MHz	2a	BF 199	7d
BF 236	Si-N	FM/VHF-O, 250MHz	8d	BF 255	7d
BF 237	Si-N	FM-V/M/O/ZF	7d	BF 255	7d
BF 238	Si-N	AM-V/M/O/ZF	7d	BF 255	7d
BF 240(B)	Si-N	AM/FM-ZF-re, 400MHz	7d	BF 255	7d
BF 240 B	Si-N	=BF 240:	10d	>BF 240	
BF 240 [Riz]	Si-N	Uni, 15V, 0,1A, 0,3W, >90MHz	2a	BC 546	7a
BF 241(C,D)	Si-N	AM/FM-ZF, 400MHz	7d	BF 255	7d
BF 241 [Riz]	Si-N	Uni, 30V, 0,1A, 0,3W, 125MHz	2a	BC 546	7a
BF 241 A [Riz]	Si-N	=BF 241 [Riz]: 60V	2a	BC 546	7a
BF 241 C,D [Piher]	Si-N	=BF 241:	10d	>BF 241	
BF 242 [Riz]	Si-N	Uni, 30V, 0,1A, 0,3W, 140MHz	2a	BC 546	7a
BF 242 A [Riz]	Si-N	=BF 242 [Riz]: 60V	2a	BC 546	7a
BF 243 [Riz]	Si-N	Uni, 30V, 0,1A, 0,3W, 170MHz	2a	BC 546	7a
BF 243 [Texas]	Si-P	AM-V/M/O/ZF, >80MHz	7d	BF 324	7a
BF 244 [Riz]	Si-N	Uni, 30V, 0,1A, 0,3W, 170MHz	2a	BC 546	7a
BF 244	N-FET	NF/HF...VHF, 30V, Idss>2mA, Up<8V	7e	BF 245	7f
BF 245	N-FET	=BF 244:	7f	>BF 244	
BF 246	N-FET	FM/VHF, 25V, Idss>10mA, Up<14,5V	7e	-	
BF 247	N-FET	=BF 246:	7f	-	
BF 248	Si-N	NF-Tr, 30V, 0,6A, 0,4W, 250MHz	2a	BC 337	7a
BF 249	Si-P	NF-Tr, 30V, 0,6A, 0,4W, 250MHz	2a	BC 327	7a
BF 250	Si-N	NF-Tr, 15V, 0,6A, 0,4W, 20MHz	2a	BC 337	7a
BF 251	Si-N	TV-ZF-re, 600MHz	5k	BF 198	7d
BF 252	Si-N	TV-ZF, 400MHz	5k	BF 198	7d
BF 253	Si-N	AM-V/M/O, >150MHz	7d	BF 255	7d
BF 254	Si-N	AM-V/M/O/ZF, 260MHz	7d	BF 255	7d
BF 255	Si-N	FM-V/M/O, 200MHz	7d	BF 255	7d
BF 255 [Riz]	Si-N	HF/ZF, 600MHz	5k	BF 199	7d
BF 256	N-FET	VHF/UHF, 30V, Idss>3mA, Up<7,5V, 1GHz	7f	(BF 245)	7f
BF 256 L	N-FET	=BF 256:	7e	>BF 256	
BF 257	Si-N	Vid, 160V, 0,1A, 0,8W, 90MHz	2a	BF 259	2a
BF 258	Si-N	=BF 257: 250V	2a	BF 259	2a
BF 259(A,G)	Si-N	=BF 257: 300V	2a	BF 259	2a
BF 260	Si-N	VHF-V, re, 800MHz	5k	BF 198	7d
BF 261 [ATES,CSF]	Si-N	TV-ZF-re, 730MHz	5k	BF 198	7d
BF 261 [Riz]	Si-N	AM/FM/VHF	5g	BF 199	7d
BF 262	Si-N	UHF-V, 650MHz	24a	-	
BF 263	Si-N	UHF-M, >525MHz	24a	-	
BF 264	Si-N	UHF-M, >400MHz	24a	-	
BF 265	Si-N	UHF-V/M/O, 600MHz	5k	2SC2570A	7f