

BDX 33 A	Si-N-Darl+Di	=BDX 33: 60V	17j	BDW 93 C	17j
BDX 33 B	Si-N-Darl+Di	=BDX 33: 80V	17j	BDW 93 C	17j
BDX 33 C	Si-N-Darl+Di	=BDX 33: 100V	17j	BDW 93 C	17j
BDX 33 D	Si-N-Darl+Di	=BDX 33: 120V	17j	-	-
BDX 33 E	Si-N-Darl+Di	=BDX 33: 140V	17j	-	-
BDX 34	Si-P-Darl+Di	NF-L, 45V, 10A, 70W, >20MHz, B>750	17j	BDW 94 C	17j
BDX 34 A	Si-P-Darl+Di	=BDX 34: 60V	17j	BDW 94 C	17j
BDX 34 B	Si-P-Darl+Di	=BDX 34: 80V	17j	BDW 94 C	17j
BDX 34 C	Si-P-Darl+Di	=BDX 34: 100V	17j	BDW 94 C	17j
BDX 34 D	Si-P-Darl+Di	=BDX 34: 120V	17j	-	-
BDX 35	Si-N	NF/S-L, 100V, 5A, 15W(Tc=75°), 100MHz	14h	-	-
BDX 36	Si-N	=BDX 35: 120/60V	14h	-	-
BDX 37	Si-N	=BDX 35: 120/80V	14h	-	-
BDX 40	Si-N	NF/S-L, 100V, 20A, 150W, >0.8MHz	23a	-	-
BDX 41	Si-N	NF/S-L, 50V, 30A, 150W, >0.8MHz	23a	-	-
BDX 42	Si-N-Darl+Di	NF-L, 60V, 1A, 5W(Tc=100°), 350MHz	14h	(BD 679)	14h
BDX 43	Si-N-Darl+Di	=BDX 42: 80V	14h	(BD 679)	14h
BDX 44	Si-N-Darl+Di	=BDX 42: 100V	14h	(BD 679)	14h
BDX 45	Si-P-Darl+Di	NF-L, 60V, 1A, 5W(Tc=100°), 350MHz	14h	(BD 680)	14h
BDX 46	Si-P-Darl+Di	=BDX 45: 80V	14h	(BD 680)	14h
BDX 47	Si-P-Darl+Di	=BDX 45: 100V	14h	(BD 680)	14h
BDX 50	Si-N	NF/S-L, 160V, 16A, 150W, >0.8MHz	23a	MJ 15015	23a
BDX 51	Si-N	NF/S-L, 140V, 10A, 120W, >0.8MHz	23a	MJ 15015	23a
BDX 53	Si-N-Darl+Di	NF-L, 45V, 8A, 60W, 20MHz, B>750	17j	BD 901	17j
BDX 53 A	Si-N-Darl+Di	=BDX 53: 60V	17j	BD 901	17j
BDX 53 B	Si-N-Darl+Di	=BDX 53: 80V	17j	BD 901	17j
BDX 53 BFI	Si-N-Darl+Di	=BDX 53B: Iso, 30W	17c	2SD1415	17c
BDX 53 C	Si-N-Darl+Di	=BDX 53: 100V	17j	BD 901	17j
BDX 53 E	Si-N-Darl+Di	=BDX 53: 140V	17j	-	-
BDX 53 F	Si-N-Darl+Di	=BDX 53: 160V	17j	-	-
BDX 53 H	Si-N-Darl+Di	=BDX 53: 60V	17j	BD 901	17j
BDX 53 S	Si-N-Darl+Di	NF/S, 150V, 6A, 15W(Tc=25°), 20MHz	2a	-	-
BDX 54	Si-P-Darl+Di	NF-L, 45V, 8A, 60W, 20MHz, B>750	17j	BD 902	17j
BDX 54 A	Si-P-Darl+Di	=BDX 54: 60V	17j	BD 902	17j
BDX 54 B	Si-P-Darl+Di	=BDX 54: 80V	17j	BD 902	17j
BDX 54 BFI	Si-P-Darl+Di	=BDX 54B: Iso, 30W	17c	2SB1020	17c
BDX 54 C	Si-P-Darl+Di	=BDX 54: 100V	17j	BD 902	17j
BDX 54 E	Si-P-Darl+Di	=BDX 54: 140V	17j	-	-
BDX 54 F	Si-P-Darl+Di	=BDX 54: 160V	17j	-	-
BDX 54 H	Si-P-Darl+Di	=BDX 54: 60V	17j	BD 902	17j
BDX 54 S	Si-P-Darl+Di	NF/S, 150V, 6A, 15W(Tc=25°), 20MHz	2a	-	-
BDX 60	Si-N	NF/S-L, 100V, 15A, 150W, >0.8MHz	23a	2N3055	23a
BDX 61	Si-N	=BDX 60: 80V	23a	2N3055	23a
BDX 62	Si-P-Darl+Di	NF/S-L, 60/60V, 8A, 90W, 7MHz, B>1000	23a	BDW 84 C	18j
BDX 62 A	Si-P-Darl+Di	=BDX 62: 80/80V	23a	BDW 84 C	18j
BDX 62 B	Si-P-Darl+Di	=BDX 62: 100/100V	23a	BDW 84 C	18j
BDX 62 C	Si-P-Darl+Di	=BDX 62: 120/120V	23a	-	-
BDX 62 L	Si-P-Darl+Di	=BDX 62: 45/45V	23a	BDW 84 C	18j
BDX 63	Si-N-Darl+Di	NF/S-L, 80/60V, 8A, 90W, 7MHz, B>1000	23a	BDW 83 C	18j
BDX 63 A	Si-N-Darl+Di	=BDX 63: 100/80V	23a	BDW 83 C	18j
BDX 63 B	Si-N-Darl+Di	=BDX 63: 120/100V	23a	-	-
BDX 63 C	Si-N-Darl+Di	=BDX 63: 140/120V	23a	-	-
BDX 63 L	Si-N-Darl+Di	=BDX 63: 60/45V	23a	BDW 83 C	18j
BDX 64	Si-P-Darl+Di	NF/S-L, 60/60V, 12A, 117W, 7MHz, B>1000	23a	BDW 84 C	18j
BDX 64 A	Si-P-Darl+Di	=BDX 64: 80/80V	23a	BDW 84 C	18j
BDX 64 B	Si-P-Darl+Di	=BDX 64: 100/100V	23a	BDW 84 C	18j