

BC 312	Si-N	NF, 100V, 0,15A, 0,8W	2a	BC 141	2a
BC 313	Si-P	NF-Tr/E, 60V, 1A, 0,8W, 200MHz	2a	BC 161	2a
BC 313 A	Si-P	=BC 313: 80V	2a	(BC 161)	2a
BC 314	Si-N	Uni, 120V, 0,05A, 0,18W, >50MHz	8a	2SC2632	7c
BC 315	Si-P	NF-V, ra, 45V, 0,1A, 0,3W, >200MHz	7a	BC 560	7a
BC 317	Si-N	=BC 318: 50V	7e	BC 546	7a
BC 318	Si-N	Uni, 40V, 0,15A, 0,35W, 280MHz	7e	BC 546	7a
BC 319	Si-N	=BC 318: 30V, ra	7e	BC 550	7a
BC 320	Si-P	=BC 321: 50V	7e	BC 556	7a
BC 321	Si-P	Uni, 45V, 0,15A, 0,31W, 250MHz	7e	BC 556	7a
BC 322	Si-P	=BC 321: 30V, ra	7e	BC 560	7a
BC 323	Si-N	TV-VA, 100V, 5A, 0,8W, 100MHz	2a	(BD 189)	14h
BC 324	Si-N	TV-VA, 85V, 1A, 0,8W, 100MHz	2a	BC 141	2a
BC 325	Si-P	NF, ra 60V, 50mA, 0,36W, B=40...120	2a	BC 560	7a
BC 326	Si-P	=BC 325: B=100...500	2a	BC 560	7a
BC 327	Si-P	NF-Tr, 50V, 0,8A, 0,625W, 100MHz	7a	BC 327	7a
BC 327 A	Si-P	=BC 327: 60V	7a	BC 640	7c
BC 327 L	Si-P	=BC 327:	7c	->BC 327	
BC 327 P	Si-P	=BC 327:	40e	->BC 327	
BC 328	Si-P	=BC 327: 30V	7a	BC 327	7a
BC 328 L	Si-P	=BC 328:	7c	->BC 328	
BC 328 P	Si-P	=BC 328:	40e	->BC 328	
BC 329	Si-N	NF-V, ra, 60V, 30mA, 0,25W	7a	BC 550	7a
BC 330	Si-N	=BC 329: 45V	7a	BC 550	7a
BC 331	Si-N	NF-V, ra, 60V, 30mA, 0,25W	7a	BC 550	7a
BC 332	Si-N	=BC 321: 45V	7a	BC 550	7a
BC 333	Si-N	Uni, 25V, 50mA, 0,31W, 50MHz	7e	BC 546	7a
BC 334	Si-P	Uni, 25V, 50mA, 0,31W, 50MHz	7e	BC 556	7a
BC 335	Si-N	=BC 333: ra	7e	BC 550	7a
BC 336	Si-P	=BC 334: ra	7e	BC 560	7a
BC 337	Si-N	NF-Tr, 50V, 0,8A, 0,625W, 100MHz	7a	BC 337	7a
BC 337 A	Si-N	=BC 337: 60V	7a	BC 639	7c
BC 337 L	Si-N	=BC 337:	7c	->BC 337	
BC 337 P	Si-N	=BC 337:	40e	->BC 337	
BC 338	Si-N	=BC 337: 30V	7a	BC 337	7a
BC 338 L	Si-N	=BC 338:	7c	->BC 338	
BC 338 P	Si-N	=BC 338:	40e	->BC 338	
BC 340	Si-N	NF-Tr/E, 40V, 0,5A, 0,8W, 100MHz	2a	BC 141	2a
BC 341	Si-N	=BC 340: 60V	2a	BC 141	2a
BC 342	Si-N	NF-Tr/E, 70V, 1A, 0,8W, 100MHz	2a	BC 141	2a
BC 343	Si-P	NF-Tr/E, 70V, 1A, 0,8W, 100MHz	2a	BC 161	2a
BC 344	Si-N	=BC 342: 90V	2a	BC 141	2a
BC 345	Si-P	=BC 343: 90V	2a	BC 161	2a
BC 347	Si-N	Uni, 50V, 0,1A, 0,3W, >125MHz	7e	BC 546	7a
BC 348	Si-N	=BC 347: 40V	7e	BC 546	7a
BC 349	Si-N	=BC 347: 30V	7e	BC 546	7a
BC 350	Si-P	Uni, 50V, 0,1A, 0,3W, >125MHz	7e	BC 556	7a
BC 351	Si-P	=BC 350: 40V	7e	BC 556	7a
BC 352	Si-P	=BC 350: 30V	7e	BC 556	7a
BC 354	Si-P	Uni, 30V, 0,2A, 0,31W, >200MHz	7e	BC 556	7a
BC 355	Si-P	Uni, 30V, 0,2A, 0,31W, >200MHz	7e	BC 556	7a
BC 357	Si-P	Uni, 25V, 0,1A, 0,31W, >125MHz	7e	BC 556	7a
BC 358	Si-N	Uni, 25V, 0,1A, 0,31W, >125MHz	7e	BC 546	7a
BC 360	Si-P	NF-Tr/E, 40V, 0,5A, 0,8W, 250MHz	2a	BC 161	2a
BC 361	Si-P	=BC 360: 60V	2a	BC 161	2a
BC 362	Si-P	NF-L, 50V, 2A, 8W, 100MHz	13m	(2SA1593)	30j