

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
2N5226	PS	T092	L14	25V	25V	4V	500MA	135C	310MWF	50M	20P	30/600	50MA	AMG	MOB	BC388	2N4403	0
2N5227	PS	T092	L14	30V	30V	3V	50MA	135C	310MWF	100M	5P	50/700	2MA	ALG	MOB	BC350A	2N3905	0
2N5228	PS	T092	L14	5V	5V	3V	50MA	135C	310MWF	300M	5P	30MN	10MA	VLS	MOB	BSW25	2N3546	0
2N5229	PS	T046	L01	15V	10V	15V	50MA	200C	500MWF	8M	5P	50MN	100UA	ALC	MOB			0
2N5230	PS	T046	L01	15V	20V	30V	50MA	200C	500MWF	8M	5P	50MN	100UA	ALC	MOB			0
2N5231	PS	T046	L01	50V	30V	50V	50MA	200C	500MWF	8M	5P	50MN	100UA	ALC	MOB			0
2N5232	NS	T098	L21	70V	50V	5V	100MA	125C	360MWF	4P	4P	250MN	2MA	ALG	GEU	BC184L	2N5210	1
2N5232A	NS	T098	L21	70V	50V	5V	100MA	125C	360MWF	4P	4P	250MN	2MA	ALN	GEU	BC184L	2N5210	1
2N5233	NS	T098	L21	80V	60V		100MA	140C	330MWF	4P	4P	100MN	10MA	FLG	OBS	BC182L	2N5832	2
2N5234	NS	T098	L21	80V	60V		100MA	140C	330MWF	4P	4P	250MN	10MA	FLG	OBS	BC390	2N2484	2
2N5235	NS	T098	L21	80V	60V		100MA	140C	330MWF	4P	4P	400MN	10MA	RLG	OBS	BC107C	2N2484	2
2N5236	NS	T039	L04	40V	20V		150MA	200C	600MWF	500M	3P	30/120	50MA	VLA	FCU	BCF510	2N3137	2
2N5237	NS	T05	L04	150V	120V	5V	5A	200C	5WC	50M		40/120	5A	RHH	NAT	BUY48	2N5238	2
2N5238	NS	T05	L04	200V	170V	5V	5A	200C	5WC	50M		40/120	5A	RHE	NAT	BUY48	2N5238	2
2N5239	NS	T03	L05	300V	225V	6V	5A	200C	100WC	5M	150P	20/80	2A	RHE	RCB	BUX16C	2N5157	1
2N5240	NS	T03	L05	375V	300V	6V	5A	200C	100WC	5M	150P	20/80	2A	RHE	RCB	BUX16C	2N5157	1
2N5241	NS	T03	L05	400V	325V	5V	5A	150C	125WC	2500K		15/35	2500MA	RHE	MOB	BU105	2N5157	0
2N5242	PS	T0105	L17	20V	20V	5V	1A	150C	500MWF	170M	35P	25/100	500MA	RMG	OBS	BFR23	2N3245	2
2N5243	PS	T0105	L17	30V	30V	5V	1A	150C	500MWF	170M	35P	25/100	500MA	RMG	OBS	BFR23	2N3244	2
2N5244	PS	T018	L01	40V	40V	5V	100MA	175C	360MWF	450M	4P	150MN	10MA	VLS	SGI	BSW25	2N3546	0
2N5249	NS	T098	L21	70V	50V	5V	100MA	125C	360MWF	4P	4P	400MN	2MA	ALG	GEU	BC184L	2N5210	1
2N5249A	NS	T098	L21	70V	50V	5V	100MA	125C	360MWF	4P	4P	400MN	2MA	ALN	GEU	BC184L	2N5210	1
2N5250	NS	X50	X50	125V	100V	10V	90A	200C	350WC	10M		10/40	70A	AHE	KER	BLX34	2N4866	2
2N5251	NS	X50	X50	180V	150V	10V	90A	200C	350WC	10M		10/40	70A	AHE	KER			2
2N5252	NS	T039	L04	300V	300V		1A	200C	1WF	30M		40/120	100MA	RME	SOD	BUX53	2N3439	2
2N5253	NS	T039	L04	300V	300V		1A	200C	1WF	30M		80/250	100MA	RME	SOD	BUX53	2N3439	2
2N5262	NS	T05	L04	75V	50V	5V	2A	200C	800MWF	250M		25MN	1A	VMH	RGU	BSS14	2N5262	0
2N5263	NS	X35	L81	20V	15V	3V	25MA	125C	360MWF	1000M		20MN	2MA	ULA	OBS			2
2N5264	NS	T03	L05	400V	180V		10A	200C	87WC	50M	80P	30/300	1A	RHE	SIT	BOY27	2N6308	2
2N5271	NS	T039	L04	200V		7V	5A		600MWF	6P				SMS	MOB	BSS45	2N5154	1
2N5272	NS	T018	L01	40V	20V		200MA	200C	360MWF	500M	4P	100MN	10MA	ULS	OBS	BSX20	2N2369	2
2N5279	NS	T05	L04	400V		7V	1A	200C	5WC	15M	10P	40/160	20MA	RME	SIT	BUX53	2N3439	2
2N5280	NS	T05F	L44	400V		7V	1A	200C	15WC	15M	10P	40/160	20MA	RME	SIT			2
2N5281	PS	T05	L04	175V	150V		1A	175C	2WC	20M	20P	20/200	1MA	AME	SIT	BFT19	2N5415	2
2N5282	PS	T05	L04	325V	300V		1A	175C	2WC	20M	20P	20/200	1MA	AME	SIT	BFT19B	2N5416	2
2N5284	NS	T059	L63	120V	80V	6V	5A	200C	50WC	60M	250P	30/90	2A5	RHH	KER		2N5288	2
2N5285	NS	T059	L63	120V	80V	6V	5A	200C	50WC	70M	250P	70/200	2A5	RHH	KER		2N5289	2
2N5286	PS	T059	L63	100V	100V	5V5	5A	200C	50WC	60M	250P	30/90	2A5	RHH	KER		2N5290	2
2N5287	PS	T059	L63	100V	100V	5V5	5A	200C	50WC	70M	250P	70/200	2A5	RHH	KER		2N5291	2
2N5288	NS	T061	L46	120V	100V	6V	10A	200C	100WC	30M	275P	30/90	5A	RHH	KER		2N5957	2
2N5289	NS	T061	L46	120V	100V	6V	10A	200C	100WC	40M	275P	70/200	5A	RHH	KER		2N5957	2
2N5290	PS	T061	L46	100V	100V	6V	10A	200C	100WC	30M	500P	30/90	5A	RHH	KER		2N5009	2
2N5291	PS	T061	L46	100V	100V	6V	10A	200C	100WC	40M	500P	70/200	5A	RHH	KER		2N5009	2
2N5292	PS	T018	L01	12V	12V	4V5	100MA	200C	360MWF	800M	4P5	40/100	30MA	ULS	OBS	BSW25	2N3546	2
2N5293	NS	T0066	L33	80V	75V	7V	4A	150C	36WC	800K		30/120	500MA	AHH	RCB	BDX72	2N6293	0
2N5294	NS	T0P66	L32	80V	75V	7V	4A	150C	36WC	800K		30/120	500MA	AHH	RCB	BD589	2N6123	0
2N5295	NS	T0066	L32	60V	50V	5V	4A	150C	36WC	800K		30/120	1A	AHG	RGU	BDX72	2N6293	0
2N5296	NS	T0P66	L32	60V	50V	5V	4A	150C	36WC	800K		30/120	1A	AHG	RCB	BD589	2N6123	0
2N5297	NS	T0Q66	L33	80V	70V	5V	4A	150C	36WC	800K		20/80	1500MA	AHG	RCU	BDX72	2N6293	0
2N5298	NS	T0P66	L32	80V	70V	5V	4A	150C	36WC	800K		20/80	1500MA	AHG	RCU	BD589	2N6123	0
2N5301	NS	T03	L05	40V	40V	5V	30A	200C	200WC	2M		15/60	15A	AHG	MOB	BDX40	2N3772	0
2N5302	NS	T03	L05	60V	60V	5V	30A	200C	200WC	2M		15/60	15A	AHH	MOB	BDX40	2N3772	0
2N5303	NS	T03	L05	80V	80V	5V	20A	200C	200WC	2M		15/60	10A	AHH	MOB	BDX40	2N3772	0
2N5304	NS	T061	L46	50V	40V	6V	10A	200C	25WC	100M	300P	30/120	2A	RHP	MOB	BOY63	2	
2N5305	NS	T098	L21	25V	25V	12V	300MA	125C	400MWF	60M	10P	2KMN	2MA	ALD	GEU			1
2N5306	NS	T098	L21	25V	25V	12V	300MA	125C	400MWF	60M	10P	7KMN	2MA	ALD	GEU			1
2N5306A	NS	T098	L21	25V	25V	12V	300MA	125C	400MWF	60M	10P	7KMN	2MA	ALD	GEU			1
2N5307	NS	T098	L21	40V	40V	12V	300MA	125C	400MWF	60M	10P	2KMN	2MA	ALD	GEU			1
2N5308	NS	T098	L21	40V	40V	12V	300MA	125C	400MWF	60M	10P	7KMN	2MA	ALD	GEU			1
2N5308A	NS	T098	L21	40V	40V	12V	300MA	125C	400MWF	60M	10P	7KMN	2MA	ALN	GEU			1
2N5309	NS	T098	L21	70V	50V	5V	100MA	125C	360MWF	100M	6P	100MN	2MA	ALG	GFU	PBC107	2N53090	0
2N5310	NS	T098	L21	70V	20V	5V	100MA	125C	360MWF	4P	4P	100MN	2MA	ALN	GEU	BC184L	2N5210	1
2N5311	NS	T098	L21	70V	20V	5V	100MA	125C	360MWF	4P	4P	250MN	2MA	ALN	GEU	BC184L	2N5210	1
2N5320	NS	T039	L04	100V	75V	7V	2A	200C	1WF	50M		30/130	500MA	AMH	RCU	BSS42	2N5320	0
2N5321	NS	T039	L04	75V	50V	5V	2A	200C	1WF	50M		40/250	500MA	AMG	ATB	BSS16	2N5320	1
2N5322	PS	T039	L04	100V	75V	7V	2A	200C	1WF	50M		30/130	500MA	AMH	ATB	BSS17	2N5322	1
2N5323	PS	T039	L04	75V	50V	5V	2A	200C	1WF	50M		40/250	500MA	AMG	ATB	BSS18	2N5322	1
2N5324	PG	T03	L05	250V	150V	4V	10A	110C	56WC	2M		20/60	5A	AHE	MOB	AU106	2N5325	0
2N5325	PG	T03	L05	325V	200V	4V	10A	110C	57WH	2M		20MN	5A	RHH	MOU	AU106	2N5325	0
2N5326	NS	T059	L63	100V	80V		5A	200C	20WC	80M		50/150	1A	RHH	TRW		2N3850	2
2N5327	NS	T05	L04	100V	80V	5V	10A	200C	5WC	100M		100MN	1A	RHH	TRW			2
2N5328	NS	T059	L63	100V	80V	5V	10A	200C	30WC	100M		100MN	1A	RHH	TRW			2
2N5329	NS	T061	L46	150V	90V	5V	20A	200C	65WC	80M		40/120	10A	RHH	TRW			2
2N5330	NS	T061	L46	150V	90V	5V	30A	200C	80WC	80M		40/120	10A	RHH	TRW			2
2N5331	NS	T063	L60	150V	90V	5V	30A	200C	100WC	80M		40/120	10A	RHH	TRW			2