

2 N 2661	USA,Tix	Ge-P	=2N2659: 90V	2a	TO-5	2N1041
2 N 2662	USA,Tix	Ge-P	LFS P, 50V, 3A, 15W(Tc=25°)	2a°		2N2553, 2N2561
2 N 2663	USA,Tix	Ge-P	=2N2662: 70V	2a°		2N2554, 2N2562
2 N 2664	USA,Tix	Ge-P	=2N2662: 90V	2a°		2N2555, 2N2563
2 N 2665	USA,Tix	Ge-P	LFS P, 50V, 3A, 15W(Tc=25°)	2a	TO-39	2N1039
2 N 2666	USA,Tix	Ge-P	=2N2665: 70V	2a	TO-39	2N1040
2 N 2667	USA,Tix	Ge-P	=2N2665: 90V	2a	TO-39	2N1041
2 N 2668	USA,Tix	Ge-P	LFS P, 50V, 3A, 15W(Tc=25°)	2a°		2N2553, 2N2561
2 N 2669	USA,Tix	Ge-P	=2N2668: 70V	2a°		2N2554, 2N2562
2 N 2670	USA,Tix	Ge-P	=2N2668: 90V	2a°		2N2555, 2N2563
2 N 2671	Amp	Ge-P	VHF, 25V, 10mA, 0,1W, >200MHz	5g	TO-12	AF 106, AF 109R, AF 306
2 N 2672(A)	Amp	Ge-P	HF, 25V(A=32V), 10mA, 0,1W, >18MHz	2a	TO-39	AF 124...127, AF 200
2 N 2673	Gen	Si-N	Uni, 60V, 0,025A, 0,25W, 40MHz, hFE=8...22	2a	TO-46	BC 174, BC 182, BC 190, BC 546, ++
2 N 2674	Gen	Si-N	=2N2673: hFE=12...40	2a	TO-46	BC 174, BC 182, BC 190, BC 546, ++
2 N 2675	Gen	Si-N	=2N2673: hFE=22...76	2a	TO-46	BC 174, BC 182, BC 190, BC 546, ++
2 N 2676	Gen	Si-N	=2N2673: hFE=45...290	2a	TO-46	BC 174, BC 182, BC 190, BC 546, ++
2 N 2677	Gen	Si-N	=2N2673: 45V, hFE=20...55	2a	TO-46	BC 167, BC 182, BC 237, BC 547, ++
2 N 2678	Gen	Si-N	=2N2673: 45V, hFE=45...150	2a	TO-46	BC 167, BC 182, BC 237, BC 547, ++
2 N 2679	USA,Mot,Tag	50Hz-Thy	30V, 0,35A(Tc=55°), Igt/Ih<0,02<0,5mA	2a	TO-18	(2N2323A) ⁶
2 N 2680	USA,Mot,Tag	50Hz-Thy	=2N2679: 60V	2a	TO-18	(2N2324A) ⁶
2 N 2681	USA,Mot,Tag	50Hz-Thy	=2N2679: 100V	2a	TO-18	(2N2324A) ⁶
2 N 2682	USA,Mot,Tag	50Hz-Thy	=2N2679: 200V	2a	TO-18	(2N2326A) ⁶
2 N 2683	USA,Mot,Tag	50Hz-Thy	30V, 0,28A(Tc=55°), Igt/Ih<0,02<1mA	2a	TO-18	(2N2323A) ⁶
2 N 2684	USA,Mot,Tag	50Hz-Thy	=2N2683: 60V	2a	TO-18	(2N2324A) ⁶
2 N 2685	USA,Mot,Tag	50Hz-Thy	=2N2683: 100V	2a	TO-18	(2N2324A) ⁶
2 N 2686	USA,Mot,Tag	50Hz-Thy	=2N2683: 200V	2a	TO-18	(2N2326A) ⁶
2 N 2679 A...2686A	USA,Mot,Tag	F-Thy	=2N2679...2686: tq<10µs	2a	TO-18	-
2 N 2687	USA,Mot,Tag	50Hz-Thy	30V, 0,28A(Tc=55°), Igt/Ih<0,2<2mA	2a	TO-18	(TAG 103 X) 2a
2 N 2688	USA,Mot,Tag	50Hz-Thy	=2N2687: 60V	2a	TO-18	(BRX 49) 7a
2 N 2689	USA,Mot,Tag	50Hz-Thy	=2N2687: 100V	2a	TO-18	(BRX 49) 7a
2 N 2690	USA,Mot,Tag	50Hz-Thy	=2N2687: 200V	2a	TO-18	(BRX 49) 7a
2 N 2691	USA	Ge-P	LFS P, 100V, 20A, 100W	23a	TO-3	2N1652...53, 2N2286...87
2 N 2691 A	USA	Ge-P	=2N2691: 120V	23a	TO-3	2N1653, 2N2287
2 N 2692	USA,Tix	Si-N	Uni, 45V, 0,05, 0,3W, >42MHz, hFE=90...360	2a	TO-18	BC 167, BC 182, BC 237, BC 547, ++
2 N 2693	USA,Tix	Si-N	=2N2692: hFE=60	2a	TO-18	BC 167, BC 182, BC 237, BC 547, ++
2 N 2694	USA,Tix	Si-N	=2N2692: hFE>30	2a	TO-18	BC 167, BC 182, BC 237, BC 547, ++
2 N 2695	USA,Sgs,Tix	Si-P	LFS, 25V, 0,5A, 0,36W, >100MHz	2a	TO-46	BC 327...328, BC 636, 2N2906...07(A), ++
2 N 2696	USA,Sgs,Tix	Si-P	LFS, 25V, 0,5A, 0,36W, >100MHz	2a	TO-18	BC 327...328, BC 636, 2N2906...07(A), ++
2 N 2697	Csr,Sem	Si-N	LFS P, 80V, 5A, 10W(Tc=100°), >20MHz			(BDV 10...12, 2SC3253) ⁴
2 N 2698	Csr,Sem	Si-N	=2N2697: 100V			(BDV 10...12) ⁴
2 N 2699	Phc	Ge-P	S, 15V, 0,1A, 0,15W, >300MHz	2a	TO-18	2N705A, 2N964(A), 2N2635, 2N2955...57
2 N 2706(MP)	Amp,Phc	Ge-P	LF Drv, 32V, 0,2A, 0,28W	2a	TO-1	AC 128, AC 152...153, 2SB324, 2SB415
2 N 2707	Amp,Phc	Ge-N/P	=2N2430+2N2706 Matched Pair	2a		AC 127+AC 128, AC 127+AC 152
2 N 2708	USA,Mot,Rca	Si-N	VHF/UHF Mx,Os, 35V, 0,05A, >700MHz	5g	TO-72	BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 2709	Ray,Sty	Si-P	LFS, 50V, 0,05A, 0,24W	2a	TO-5	BC 212, BC 257, BC 307, BC 557, ++
2 N 2710	USA,Mot	Si-N	S, 40V, 0,5A, 0,36W, <20/35ns	2a	TO-18	BSS 10, BSX 26, BSX 39, 2N3261
2 N 2711	USA,Mic	Si-N	Uni, 18V, 0,1A, 0,12W, hFE=30...90	7c	TO-98	BC 168, BC 183, BC 238, BC 548, ++
2 N 2712	USA,Mic	Si-N	=2N2711: hFE=75...225	7c	TO-98	BC 168, BC 183, BC 238, BC 548, ++
2 N 2713	USA,Mic,Tho	Si-N	Uni, 18V, 0,2A, 0,36W, 200MHz, hFE=30...90	7c	TO-98	BC 168, BC 183, BC 238, BC 548, ++
2 N 2714	USA,Mic,Tho	Si-N	=2N2713: hFE=75...225	7c	TO-98	BC 168, BC 183, BC 238, BC 548, ++
2 N 2715	Gen,Sem	Si-N	Uni, 18V, 0,05A, 0,2W, hFE=30...90	7c	TO-98	BC 168, BC 183, BC 238, BC 548, ++
2 N 2716	Gen,Sem	Si-N	=2N2715: hFE=75...225	7c	TO-98	BC 168, BC 183, BC 238, BC 548, ++
2 N 2717	Idi,Ssi	Ge-P	S, 25V, 15mA, 0,1W, >300MHz	2a	TO-18	(ASZ 21, 2N2635, 2N2955...57)
2 N 2718	USA	Ge-P	S, 20V, 0,4A, 0,24W, >150MHz, <100/250ns	2a	TO-5	-
2 N 2719	Cen,Syl	Si-N	S, 25V, 0,2A, 0,3W, 200MHz	2a	TO-18	BC 238, BC 548, BSY 62, 2N706A, ++
2 N 2720	USA,Mot	Si-N	Dual, 80V, 0,04A, 0,6W, >80MHz, ΔUbe<5mV	TO-77	(CBE-EBC-)	BFX 70...72, 2N2060, 2N2223
2 N 2721	USA,Mot	Si-N	=2N2720: ΔUbe<10mV	TO-77	(CBE-EBC-)	BFX 70...72, 2N2060, 2N2223
2 N 2722	USA,Mot,Nsc	Si-N	Dual, In, 45V, 0,04A, 0,6W, >100MHz, ΔUbe<5mV	TO-77	(CBE-EBC-)	BFY 81, 2N2639...44, 2N2913...20
2 N 2723	USA,Mot	Si-N-Darl	Uni, 80V, 0,04A, 0,5W, hFE>2000	5	TO-72	-
2 N 2724	USA,Mot	Si-N-Darl	=2723: hFE>7000	5	TO-72	-
2 N 2725	USA,Mot	Si-N-Darl	=2723: 45V	5	TO-72	-
2 N 2726	USA	Si-N	Vid,S, 200V, 0,5A, 1W, >15MHz, hFE=30...90	2a	TO-5	BSS 48, 2N2440, 2SD413, 2SD576, 2SD624
2 N 2727	USA	Si-N	=2N2726: hFE=75...150	2a	TO-5	BSS 48, 2N2440, 2SD413, 2SD576, 2SD624
2 N 2728	USA,Mot	Ge-P	S P, 15V, 50A, 170W	38a	TO-36	2N4048...4053
2 N 2729	USA	Si-N	HF,IF, 30V, 0,05A, 0,3W, >600MHz	2a	TO-46	BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 2730	Gpd,Sem	Ge-P	S P, 80V, 65A, 170W	38a	TO-36	2N4050, 2N4053
2 N 2731	Gpd,Sem	Ge-P	=2N2730: 60V	38a	TO-36	2N4049...4050, 2N4052...4053
2 N 2732	Gpd,Sem	Ge-P	=2N2730: 40V	38a	TO-36	2N4048...4050, 2N4051...4053
2 N 2733	Gpd,Sem	Ge-P	S P, 80V, 65A, 170W	38a		2N4050, 2N4053
2 N 2734	Gpd,Sem	Ge-P	=2N2733: 60V	38a		2N4049...4050, 2N4052...4053
2 N 2735	Gpd,Sem	Ge-P	=2N2733: 40V	38a		2N4048...4050, 2N4051...4053
2 N 2736	Gpd,Sem	Ge-P	S P, 80V, 65A, 170W	38a		2N4050, 2N4053
2 N 2737	Gpd,Sem	Ge-P	=2N2736: 60V	38a		2N4049...4050, 2N4052...4053
2 N 2738	Gpd,Sem	Ge-P	=2N2736: 40V	38a		2N4048...4050, 2N4051...4053
2 N 2739	Sem,Ssi,Stc	Si-N	S P, 50V, 20A, 200W		TO-82	-
2 N 2740	Sem,Ssi,Stc	Si-N	=2N2739: 100V		TO-82	-
2 N 2741	Sem,Ssi,Stc	Si-N	=2N2739: 150V		TO-82	-
2 N 2742	Sem,Ssi,Stc	Si-N	=2N2739: 200V		TO-82	-
2 N 2743	Sem,Ssi,Stc	Si-N	=2N2739: 250V		TO-82	-
2 N 2744	Sem,Ssi,Stc	Si-N	=2N2739: 300V		TO-82	-
2 N 2745	Sem,Ssi,Stc	Si-N	S P, 50V, 20A, 200W		TO-82	-
2 N 2746	Sem,Ssi,Stc	Si-N	=2N2745: 100V		TO-82	-
2 N 2747	Sem,Ssi,Stc	Si-N	=2N2745: 150V		TO-82	-
2 N 2748	Sem,Ssi,Stc	Si-N	=2N2745: 200V		TO-82	-
2 N 2749	Sem,Ssi,Stc	Si-N	=2N2745: 250V		TO-82	-
2 N 2750	Sem,Ssi,Stc	Si-N	=2N2745: 300V		TO-82	-
2 N 2751	Sem,Ssi,Stc	Si-N	S P, 50V, 20A, 200W		TO-82	-
2 N 2752	Sem,Ssi,Stc	Si-N	=2N2751: 100V		TO-82	-
2 N 2753	Sem,Ssi,Stc	Si-N	=2N2751: 150V		TO-82	-
2 N 2754	Sem,Ssi,Stc	Si-N	=2N2751: 200V		TO-82	-
2 N 2755	Sem,Ssi,Stc	Si-N	=2N2751: 250V		TO-82	-
2 N 2756	Sem,Ssi,Stc	Si-N	=2N2751: 300V		TO-82	-
2 N 2757	USA,Whs	Si-N	S P, 50V, 30A, 200W	49m	TO-63	2N6324...25