

2 N 2937	Ray,Sem,Sty	Si-N	=2N2936: ΔUbe--	TO-77	(CBE-EBC-)	BFY 81, 2N2639...44, 2N2919...20
2 N 2938	Etc,Fer	Si-N	S, 25V, 0.5A, 0.3W, >500MHz, <30/30ns	2a	TO-18	BSS 10, BSX 26, BSX 28, BSX 39, 2N3261
2 N 2939	Etc,Ssi,Tra	Si-N	LFS, 75V, 1A, 0.8W, >150MHz	2a	TO-5	BC 140...141, BSX 45...47, 2N1990, ++
2 N 2940	Etc,Ssi,Tra	Si-N	=2N2939: 120V	2a	TO-5	BSS, 42, BSW 67, BSX 47, 2N2405, ++
2 N 2941	Etc,Ssi,Tra	Si-N	=2N2939: 150V	2a	TO-5	BSS 43, BSW 68
2 N 2942	Spr	Ge-P	S, 50V, 0.1A, 0.15W, >150MHz	2a	TO-9	-
2 N 2943	Spr	Ge-P	=2N2942: 30V, >120MHz	2a	TO-9	2N2635, 2N2955...57
2 N 2944(A)	Mot,Tix,++	Si-P	Chopper, 15V, 0.1A, 0.4W, 15MHz	2a	TO-46	2N5229
2 N 2945(A)	Mot,Tix,++	Si-P	Chopper, 25V, 0.1A, 0.4W, 13MHz	2a	TO-46	2N5230
2 N 2946(A)	Mot,Tix,++	Si-P	Chopper, 25V, 0.1A, 0.4W, 12MHz	2a	TO-46	2N5231
2 N 2947	Mot,Sca,Ssi	Si-N	HF P, 60V, 1.5A, PQ=15W(50MHz)	23a	TO-3	-
2 N 2948	Mot,Sca,Ssi	Si-N	HF P, 40V, 1.5A, PQ=15W(30MHz)	23a	TO-3	-
2 N 2949	Mot,Sca,Ssi	Si-N	HF Drv,Out, 60V, 0.7A, PQ=3.5W(50MHz)	2a	TO-107	-
2 N 2950	Mot,Sca,Ssi	Si-N	HF Drv,Out, 60V, 0.7A, PQ=3.5W(50MHz)	49a	TO-102	-
2 N 2951(S)	Mot,Tix,++	Si-N	HF A,Drv, 60V, 0.25A, PQ=0.6W(50MHz)	2a	TO-5	BFX 55, MRF 229...230
2 N 2952	Mot,Tix,++	Si-N	HF A,Drv, 60V, 0.25A, PQ=0.6W(50MHz)	2a		(BFX 55, MRF 229...230) ⁶
2 N 2953	Can,Spe,Sty	Ge-P	LFS, 30V, 0.15A, 0.12W, 10MHz	2a	TO-1	AC 125...126, AC 151, ASY 26, ASY 76...77
2 N 2954	Phc	Si-N	HF Os,Drv, 30V, 0.5A, 0.2W, >300MHz			BFS 51, BFQ 42, BFR 98, BFX 55, ++
2 N 2955	Idi,Mot,Ssi	Ge-P	S, 40V, 0.1A, 0.15W, 32/53ns	2a	TO-18	-
2 N 2956	Idi,Mot,Ssi	Ge-P	S, 40V, 0.1A, 0.15W, 25/55ns	2a	TO-18	-
2 N 2957	Idi,Mot,Ssi	Ge-P	S, 40V, 0.1A, 0.15W, 22/50ns	2a	TO-18	-
2 N 2958(S)	Mot,Sgs,++	Si-N	S, 60V, 0.6A, 0.6W, <95/500ns, hFE>40	2a	TO-5	BSW 27...28, BSW 51...54, 2N2218...19(A), ++
2 N 2959(S)	Mot,Sgs,++	Si-N	=2N2958: hFE>100	2a	TO-5	BSW 27...28, BSW 51...54, 2N2218...19(A), ++
2 N 2960	Ray,Sem,Tra	Si-N	S, 60V, 0.6A, 0.6W, <95/500ns	2a	TO-5	BSW 27...28, BSW 51...54, 2N2218...19(A), ++
2 N 2961	Ray,Sem,Tra	Si-N	S, 60V, 0.6A, 0.6W, <95/500ns	2a	TO-5	BSW 27...28, BSW 51...54, 2N2218...19(A), ++
2 N 2962	Sca,Spr	Ge-P	VHF A,Drv, 40V, 0.3A, 0.35W, >560MHz	≈49m		-
2 N 2963	Sca,Spr	Ge-P	VHF A,Drv, 40V, 0.3A, 0.35W, >560MHz	≈49m		-
2 N 2964	Sca,Spr	Ge-P	VHF A,Drv, 30V, 0.3A, 0.35W, >560MHz	≈49m		-
2 N 2965	Sca,Spr	Ge-P	VHF A,Drv, 30V, 0.3A, 0.35W, >560MHz	≈49m		-
2 N 2966	Phc	Ge-P	VHF, 20V, 0.1A, 0.06W, >500MHz			2N3283...86, (AF 139, AF 239(S)) ⁷
2 N 2967	Phc	Si-N	SS, 12V, 0.3W, <15/15ns	2a	TO-18	BSS 11...12, BSY 17...18, 2N3268...69(A), ++
2 N 2968	USA	Si-P	Chopper, 30V, 0.05A, 0.15W, >10MHz	2a	TO-5	2N2946
2 N 2969	USA	Si-P	=2N2969:	2a	TO-18	2N2946
2 N 2970	USA	Si-P	Chopper, 20V, 0.05A, 0.15W, >8MHz	2a	TO-5	2N2946
2 N 2971	USA	Si-P	=2N2970:	2a	TO-18	2N2946
2 N 2972	USA,Mot,Sgs	Si-N	=2N2913: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2973	USA,Mot,Sgs	Si-N	=2N2914: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2974	USA,Mot,Sgs	Si-N	=2N2915: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2975	USA,Mot,Sgs	Si-N	=2N2916: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2976	USA,Mot,Sgs	Si-N	=2N2917: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2977	USA,Mot,Sgs	Si-N	=2N2918: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2978	USA,Mot,Sgs	Si-N	=2N2919: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2979	USA,Mot,Sgs	Si-N	=2N2920: 0.3W	TO-71	(EBC-EBC-)	BFW 51...52
2 N 2980	USA,Mic,Sgs	Si-N	Dual, 100V, 0.5A, 0.25W, >60MHz, ΔUbe<3mV	TO-71	(EBC-EBC-)	(BFX 70...72, 2N2060, 2N2223) ⁶
2 N 2981	USA,Mic,Sgs	Si-N	Dual, 100V, 0.5A, 0.25W, >50MHz, ΔUbe<15mV	TO-71	(EBC-EBC-)	(BFX 70...72, 2N2060, 2N2223) ⁶
2 N 2982	USA,Mic,Sgs	Si-N	Dual, 100V, 0.5A, 0.25W, >50MHz, ΔUbe<5mV	TO-71	(EBC-EBC-)	(BFX 70...72, 2N2060, 2N2223) ⁶
2 N 2983	USA	Si-N	LFS, 155V, 3A, 1W, 60MHz, hFE>20	2a	TO-5	BUX 49...53, BUY 41, 2SD625
2 N 2984	USA	Si-N	=2N2983: 185V	2a	TO-5	BUX 50...53, 2SD625
2 N 2985	USA	Si-N	=2N2983: hFE>40	2a	TO-5	BUX 49...53, BUY 41, 2SD625
2 N 2986	USA	Si-N	=2N2983: 185V, hFE>40	2a	TO-5	BUX 50...53, 2SD625
2 N 2987	USA,Tix	Si-N	LFS, 95V, 1A, 15W(Tc=100°), hFE>25	2a	TO-5	BUX 49...53, BUY 41, 2SD625
2 N 2988	USA,Tix	Si-N	=2N2987: 155V	2a	TO-5	BUX 49...53, 2SD625
2 N 2989	USA,Tix	Si-N	=2N2987: hFE>60	2a	TO-5	BUX 49...53, BUY 41, 2SD625
2 N 2990	USA,Tix	Si-N	=2N2987: 155V, hFE>60	2a	TO-5	BUX 49...53, 2SD625
2 N 2991	USA,Tix	Si-N	=2N2987:	49m		(2SC2275(A), 2SC2528...29, 2SD608, ++) ⁴
2 N 2992	USA,Tix	Si-N	=2N2988:	49m		(2SC2275A, 2SC2529, 2SD608, 2SD759, ++) ⁴
2 N 2993	USA,Tix	Si-N	=2N2989:	49m		(2SC2275(A), 2SC2528...29, 2SD608, ++) ⁴
2 N 2994	USA,Tix	Si-N	=2N2990:	49m		(2SC2275A, 2SC2529, 2SD608, 2SD759, ++) ⁴
2 N 2995	USA	Si-N	LFS, 120V, 1A, >10MHz	49m		(2SC2275(A), 2SC2528...29, 2SD608, ++) ⁴
2 N 2996	Ssi,Sty,Tix	Ge-P	UHF, 15V, 0.05A, 0.075W, >400MHz	5g	TO-72	AF 139, AF 239(S), 2N3283...86
2 N 2997	Ssi,Sty,Tix	Ge-P	UHF, 30V, 0.05A, 0.075W, >400MHz	5g	TO-72	AF 139, AF 239(S), 2N3283...86
2 N 2998	Sty,Tix	Ge-P	UHF, 15V, 0.05A, 0.075W, >600MHz	5g	TO-72	AF 139, AF 239(S), 2N3283...86
2 N 2999	Sty,Tix	Ge-P	UHF, 15V, 0.05A, 0.075W, >1400MHz	5g	TO-72	AF 139, AF 239(S), 2N3283...86
2 N 3000	Stc,Sty	Ge-P	LF, 45V, 0.4A, 0.15W	2a	TO-5	ASY 76...77
2 N 3001	USA,Mot,Tag	50Hz-Thy	30V, 0.25A(Tc=55°), 0.35A=, Igt/Ih<0.02/<3mA	2a	TO-18	(2N2323A) ⁶
2 N 3002		50Hz-Thy	=2N3001: 60V	2a	TO-18	(2N2324A) ⁶
2 N 3003		50Hz-Thy	=2N3001: 100V	2a	TO-18	(2N2324A) ⁶
2 N 3004		50Hz-Thy	=2N3001: 200V	2a	TO-18	(2N2326A) ⁶
2 N 3005		50Hz-Thy	=2N3001: Igt/Ih<0.2/<5mA	2a	TO-18	(2N6605, TAG 06Y, (2N2323, TAG 615-100) ⁶
2 N 3006		50Hz-Thy	=2N3002: Igt/Ih<0.2/<5mA	2a	TO-18	(2N6606, TAG 06Y, (2N2324, TAG 615-100) ⁶
2 N 3007		50Hz-Thy	=2N3003: Igt/Ih<0.2/<5mA	2a	TO-18	(2N6607, TAG 06A, (2N2324, TAG 615-100) ⁶
2 N 3008		50Hz-Thy	=2N3004: Igt/Ih<0.2/<5mA	2a	TO-18	(2N6608, TAG 06B, (2N2326, TAG 615-200) ⁶
2 N 3009	USA,Mot,Sgs	Si-N	S, 40V, 0.2A, 0.36W, <15/25ns	2a	TO-52	BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 3010	USA,Mot,Sgs	Si-N	S, 15V, 0.05A, 0.3W, <12/12ns	2a	TO-18	BSS 11...12, BSY 17...18, 2N2368...69(A), ++
2 N 3011	USA,Mot,Mic	Si-N	SS, 30/12V, 0.2/0.5A, 0.36W, >400MHz, <15/20ns	2a	TO-18	BSS 11...12, BSX 19...20, 2N2368...69(A), ++
	Sgs,Tix,++			{2N3012		
2 N 3012	USA,Mot,Mic	Si-P	S, 12/12V, 0.2A, 0.36W, >400MHz, <60/75ns	2a	TO-18	BSX 36
	Sgs,Tix,++			{2N3011		
2 N 3013(R)	USA,Mot,Mic	Si-N	SS, 40/15V, 0.2/0.5A, 0.36W, >350MHz, <15/25ns	2a	TO-52	BSS 10...11, BSX 19...20, 2N2368...69(A), ++
	Sgs,Tix,++			{2N3013R(Tho):		
	=2N1313	Si-N	SS, 40/20V, 0.2/0.5A, 0.36W, >350MHz, <16/25ns	2a	TO-52	BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 3015	USA,Mot,Tix	Si-N	S, 60V, 1A, 0.8W, <40/60ns	2a	TO-5	BSS 27, BSV 77, BSV 95, 2N5189, ++
2 N 3016	USA	Si-N	LFS, 100V, 2.5A, 3.3W(Tc=25°)	2a	TO-5	BSX 64, 2N4239, 2SC696(A), 2SC2214
2 N 3017	USA	Si-N	=2N3016: 5A	49m		(BD 243C, BD 539C, BD 953, 2SD613, ++) ⁴
2 N 3018	USA	Si-N	=2N3016: 10A, 25W(Tc=25°)	49m	TO-61	2N5288...89, 2N5542
2 N 3019(S)	USA,EUR,Mic	Si-N	Uni, 140/80V, 1A, 0.8W, >100MHz, hFE=100...300, F<4dB	2a	TO-5	BSS 43, BSW 68, 2SC1860
2 N 3020(S)	USA,EUR,Mic	Si-N	=2N3019: hFE=40...120, >80MHz, F=-	IS: TO-39	TO-5	BSS 43, BSW 68, 2SC1860
2 N 3021	USA,Mot,Tix	Si-P	LFS P, 30V, 3A, 25W, >60MHz, hFE=20...60	23a	TO-3	2SA1141, 2SA1146, 2SA1186, 2SA1292, ++
2 N 3022		Si-P	=2N3021: 45V	23a	TO-3	2SA1141, 2SA1146, 2SA1186, 2SA1292, ++
2 N 3023		Si-P	=2N3021: 60V	23a	TO-3	2SA1141, 2SA1146, 2SA1186, 2SA1292, ++
2 N 3024		Si-P	=2N3021: hFE=50...180	23a	TO-3	2SA1141, 2SA1146, 2SA1186, 2SA1292, ++
2 N 3025		Si-P	=2N3021: 45V, hFE=50...180	23a	TO-3	2SA1141, 2SA1146, 2SA1186, 2SA1292, ++
2 N 3026		Si-P	=2N3021: 60V, hFE=50...180	23a	TO-3	2SA1141, 2SA1146, 2SA1186, 2SA1292, ++