

2 N 3801		Si-P	=2N3800: hFE=300...900, F<1,5dB(1kHz)	TO-71	(EBC-EBC-)	-		
2 N 3802		Si-P	=2N3800: ΔhFE=0.8...1, ΔUbe<5mV	TO-71	(EBC-EBC-)	-		
2 N 3803		Si-P	=2N3801: ΔhFE=0.8...1, ΔUbe<5mV	TO-71	(EBC-EBC-)	-		
2 N 3804(A)		Si-P	=2N3800: ΔhFE=0.9(A: 0.95)...1, ΔUbe<5(A: <1.5)mV	TO-71	(EBC-EBC-)	-		
2 N 3805(A)		Si-P	=2N3801: ΔhFE=0.9(A: 0.95)...1, ΔUbe<3(A: <1.5)mV	TO-71	(EBC-EBC-)	-		
2 N 3806		Si-P	=2N3800:	TO-77	(CBE-EBC-)	-	2N4015...16	
2 N 3807		Si-P	=2N3801:	TO-77	(CBE-EBC-)	-	2N4015...16	
2 N 3808		Si-P	=2N3802:	TO-77	(CBE-EBC-)	-	2N4015...16	
2 N 3809		Si-P	=2N3803:	TO-77	(CBE-EBC-)	-	2N4015...16	
2 N 3810(A)		Si-P	=2N3804(A):	TO-77	(CBE-EBC-)	-	2N4015...16	
2 N 3811(A)		Si-P	=2N3805(A):	TO-77	(CBE-EBC-)	-	2N4015...16	
2 N 3812		Si-P	=2N3800:	10-FLP	TO-89	-	-	
2 N 3813		Si-P	=2N3801:	10-FLP	TO-89	-	-	
2 N 3814		Si-P	=2N3802:	10-FLP	TO-89	-	-	
2 N 3815		Si-P	=2N3803:	10-FLP	TO-89	-	-	
2 N 3816(A)		Si-P	=2N3804(A):	10-FLP	TO-89	-	-	
2 N 3817(A)		Si-P	=2N3805(A):	10-FLP	TO-89	-	-	
2 N 3818	Mot,Sca,Ssi	Si-N	VHF P, 60V, 2A, PQ=15W(100MHz)	49a	TO-60	-	BLY 35, 2N3632	
2 N 3819	USA, EUR	N-FET	Uni/VHF, sym, 25V, Idss>2mA, Up<8V	7e	TO-72	BF 245	7f	BF 244...245, BFS 72, 2N3823
2 N 3820	USA, Phi, Tix	P-FET	Uni, sym, 20V, Idss>0.3mA, Up<8V	7e	TO-92	-	-	BF 320A, 2N3909
2 N 3821	USA, EUR	N-FET	Uni/VHF, 50V, Idss>0.5mA, Up<4V	5k	TO-72	-	-	BFS 70, 2N4220, 2SK104, 2SK301
2 N 3822	USA, EUR	N-FET	Uni/VHF, 50V, Idss>2mA, Up<6V	5k	TO-92	-	-	BFS 71, BFS 80, BFW 11, 2N4416
2 N 3823	USA, EUR	N-FET	VHF, In, 30V, Idss>4mA, Up<8V	5k	TO-92	BF 245	7f	BF 244...245, BFS 72
2 N 3824	USA, EUR	N-FET	Chopper, sym, Idss>12mA	5k	TO-92	-	-	BFS 73
2 N 3825	Mic, Nsc, Tix	Si-N	Uni, 30V, 0.1A, 0.25W, >200MHz	7c	TO-92	-	-	BC 168, BC 183, BC 238, BC 548, ++
2 N 3826	Tix	Si-N	AM/FM Mx, O, IF, 300MHz, hFE=40...160	7c	TO-92	-	-	BF 240...241, BF 254...255, BF 594...595, ++
2 N 3827	Tix	Si-N	=2N3826: hFE=100...300	7c	TO-92	-	-	BF 240...241, BF 254...255, BF 594...595, ++
2 N 3828	Sem, Tix	Si-N	TV IF, 40V, 0.1A, 0.3W, >360MHz	7c	TO-92	-	-	BF 198...199, BF 224...225, BF 596...597, ++
2 N 3829	Sca, Ssi, Tix	Si-P	S, 35V, 0.2A, 0.36W, <25/65ns	2a	TO-52	-	-	BSS 10...11, BSX 19...20, 2N2368...69(A), ++
2 N 3830	USA, Tix	Si-N	S, 80V, 1.2A, 1W, <60/70ns	2a	TO-5	-	-	BSS 14, BSV 95, 2N3735, 2N5262
2 N 3831	USA, Tix	Si-N	=2N3830: 70V	2a	TO-5	-	-	BSS 14, BSV 95, 2N3735, 2N5262
2 N 3832	Etc, Tix	Si-N	S, 15V, 0.035A, 0.2W, <35/30ns	5g	TO-72	-	-	BSS 10...12, BSY 17...18, 2N3011, ++
2 N 3833	Tix	Si-N	UHF, 25V, 0.1A, >1GHz	24f	-	-	-	BFT 12, 2SC3288, 2SC3368...69
2 N 3834	Tix	Si-N	UHF, 25V, 0.1A, >1GHz	24f	-	-	-	BFT 12, 2SC3288, 2SC3368...69
2 N 3835	Tix	Si-N	UHF, 25V, 0.1A, >1GHz	24f	-	-	-	BFT 12, 2SC3288, 2SC3368...69
2 N 3836	Tix	Si-N-Darl	LFS P, 80V, 7A, 25W, hFE>1000	-	-	-	-	-
2 N 3837	Tix	Si-N-Darl	=2N3836: 100V	-	-	-	-	-
2 N 3838	Mot, Ray, Tix	Si-N/P	NPN+PNP, 60V, 0.6A, 0.35W, >200MHz	10-FLP	TO-89	-	-	-
2 N 3839	USA, Mot, Sgs	Si-N	UHF Inp, Mx, Os, 30V, 0.04A, 0.2W, >1GHz	5g	TO-72	-	-	BF 357, BF 377...378, 2SC2498, 2SC3037, ++
2 N 3840	Sem, Spr, Tdy	Si-P	Chopper, 50/50/50V, 0.1A, 0.4W	2a	TO-46	-	-	2N2946
2 N 3841	Sem, Sty	Si-P	Chopper, 100/100/80V, 0.1A, 0.3W	2a	TO-18	-	-	-
2 N 3842	Sem, Sty	Si-P	Chopper, 120/120/120V, 0.1A, 0.3W	2a	TO-18	-	-	-
2 N 3843(A)	USA, Gen, Mic	Si-N	HF Imp, Mx, IF, 30V, 0.1A, 0.2W, >60MHz	7c	TO-98	-	-	BF 240...241, BF 254...255, BF 594...595, ++
2 N 3844(A)	USA, Gen, Mic	Si-N	HF Imp, Mx, IF, 30V, 0.1A, 0.2W, >90MHz	7c	TO-98	-	-	BF 240...241, BF 254...255, BF 594...595, ++
2 N 3845(A)	USA, Gen, Mic	Si-N	HF Imp, Mx, IF, 30V, 0.1A, 0.2W, >120MHz	7c	TO-98	-	-	BF 240...241, BF 254...255, BF 594...595, ++
2 N 3846	USA, Tix	Si-N	S P, 300/200V, 20A, 150W(Tc=100°)	49m	TO-63	-	-	2N6324...25
2 N 3847		Si-N	=2N3846: 400/300V	49m	TO-63	-	-	2N6325
2 N 3848	USA, Tix	Si-N	S P, 300/200V, 20A, 150W(Tc=100°)	49m	TO-63	-	-	2N6324...25
2 N 3849		Si-N	=2N3848: 400/300V	49m	TO-63	-	-	2N6325
2 N 3850	USA, Tix	Si-N	S P, 100/80V, 5A, 40W(Tc=100°), hFE=50...150	49m	TO-59	-	-	2N5002, 2N5004, 2N5284...85
2 N 3851		Si-N	=2N3850: hFE=30...90	49m	TO-59	-	-	2N5002, 2N5004, 2N5284...85
2 N 3852		Si-N	=2N3850: 60V	49m	TO-59	-	-	2N5002, 2N5004, 2N5284...85
2 N 3853		Si-N	=2N3850: 60V, hFE=30...90	49m	TO-59	-	-	2N5002, 2N5004, 2N5284...85
2 N 3854	USA, Gen, Mic	Si-N	Uni, 18V, 0.1A, 0.2W, >100MHz, hFE=35...70	7c	TO-98	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 N 3854 A		Si-N	=2N3854: 30V	7c	TO-98	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 N 3855		Si-N	=2N3854: >130MHz, hFE=60...120	7c	TO-98	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 N 3855 A		Si-N	=2N3855: 30V	7c	TO-98	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 N 3856		Si-N	=2N3854: >140MHz, hFE=100...200	7c	TO-98	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 N 3856 A		Si-N	=2N3856: 30V	7c	TO-98	BC 546	7a	BC 168, BC 183, BC 238, BC 548, ++
2 N 3857	Sty	Si-P	LF, 45V, 0.5A, 0.6W, >20MHz	2a	TO-5	-	-	BC 160...161, BC 303...304, BC 638, ++
2 N 3858	USA, Mic, ++	Si-N	Uni, 30V, 0.1A, 0.36W, 125MHz, hFE=60...120	7c	TO-98	-	-	BC 168, BC 183, BC 238, BC 548, ++
2 N 3858 A		Si-N	=2N3858: 60V	7c	TO-98	-	-	BC 174, BC 182, BC 190, BC 546, ++
2 N 3859		Si-N	=2N3858: 140MHz, hFE=100...200	7c	TO-98	-	-	BC 168, BC 183, BC 238, BC 548, ++
2 N 3859 A		Si-N	=2N3859: 60V	7c	TO-98	-	-	BC 174, BC 182, BC 190, BC 546, ++
2 N 3860		Si-N	=2N3858: 170MHz, hFE=150...300	7c	TO-98	-	-	BC 168, BC 183, BC 238, BC 548, ++
2 N 3860 A		Si-N	=2N3860: 60V	7c	TO-98	-	-	BC 174, BC 182, BC 190, BC 546, ++
2 N 3861	USA	Si-N	S/Vid, 530/530V, 0.025A, >50MHz	43m	=TO-37	-	-	(BD 232, BD 410, BLX 86...87, 2SC2899)4
2 N 3862	USA	Si-N	S, 50V, 0.2A, 0.36W, <78/50ns	5g	TO-72	-	-	BSX 39, 2N4014...14, 2SC1834
2 N 3863	USA	Si-N	S P, 70/50V, 7.5A, 117W, >0.5MHz	23a	TO-3	-	-	BD 313, BD 545B, 2N3055, 2N5632...34, ++
2 N 3864		Si-N	=2N3863: 110/90V	23a	TO-3	-	-	BD 313, BD 545D, 2N3055, 2N5632...34, ++
2 N 3865		Si-N	=2N3863: 160/150V	23a	TO-3	-	-	BDX 11, BDY 54, 2N3442, 2SD733, ++
2 N 3866(A)	USA, EUR	Si-N	VHF/UHF Os, Drv, 55V, 0.4A, PQ>1W(400MHz)	2a	TO-39	-	-	BFR 97
2 N 3867	USA, Mot, Sgs	Si-P	LFS, 40V, 3A, 1W, >60MHz, <100/400ns	2a	TO-5	-	-	2N3719...20
2 N 3868		Si-P	=2N3867: 60V	2a	TO-5	-	-	2N3720
2 N 3869	USA, Nec	Si-N	HF Drv, 40V, 0.5A, >400MHz	2a	TO-5	-	-	BFS 51, BFR 98, BLW 16, 2SC2852, ++
2 N 3870	Gen, Mot, Rca	50Hz-Thy	100V, 22A(Tc=65°), 35A-, Igt/Ih<40/<70mA	29b	TO-203	-	-	MCR 3835-3, BStE4026M, MCR 63-3
2 N 3871		50Hz-Thy	=2N3870: 200V	29b	TO-203	-	-	MCR 3835-4, BStE4026M, MCR 63-4
2 N 3872		50Hz-Thy	=2N3870: 400V	29b	TO-203	-	-	MCR 3835-6, BStE4026M, MCR 63-6
2 N 3873		50Hz-Thy	=2N3870: 600V	29b	TO-203	-	-	MCR 3835-8, BStE4040M, MCR 63-8
2 N 3876	Ssi, Trw	Si-N	LFS P, 140V, 10A, 125W, >50MHz	-	TO-81	-	-	-
2 N 3877	USA, Mic, Nsc	Si-N	Nixie, 70V, 0.05A, 0.2W, 160MHz	7c	TO-98	BC 546, BF 420A	7a, 7c	BC 546, BSS 38, BSX 21, 2SC1890(A), ++
2 N 3877 A		Si-N	=2N3877: 85V	7c	TO-98	BC 546, BF 420A	7a, 7c	BC 546, BSS 38, BSX 21, 2SC1890(A), ++
2 N 3878	USA, Rca, Tix	Si-N	LFS P, 120V, 4A, 35W, >40MHz	22a	TO-66	-	-	BDV 10...12, BDY 79, 2SD722(A,B)
2 N 3879	USA, Rca, Tix	Si-N	LFS P, 120V, 7A, 35W, >40MHz	22a	TO-66	-	-	MJE 15030
2 N 3880	USA, Fch, Sgs	Si-N	UHF, 30V, 0.2W, >1200MHz	5g	TO-72	-	-	BF 357, BF 377...378, BFR 37, BFW 99, ++
2 N 3881	Idi, Sca, Ssi	Si-N	LF, 60V, 1A, 0.6W, >70MHz	2a	TO-5	-	-	BC 140...141, 2N1990, 2N2102, 2N2405, ++
2 N 3882	Ray	MOS-P-FET-e	Uni, 30V, Idss>0.25mA, Up<3V	5k(DGSsub)	TO-92	-	-	-
2 N 3883	Mot, Ssi	Ge-P	S, 25V, 0.3A, 0.3W, 300MHz, 36/68ns	2a	TO-5	-	-	-
2 N 3886	USA, Mot, Rca	50Hz-Thy	100V, 22A(Tc=65°), 35A-, Igt/Ih<40/<70mA	21b	=TO-48	-	-	MCR70-3, C228A, MCR3935-3, BStE4126M, ++
2 N 3897		50Hz-Thy	=2N3896: 200V	21b	=TO-48	-	-	C228B, MCR3935-4, BStE4126M, C35B, ++
2 N 3898		50Hz-Thy	=2N3896: 400V	21b	=TO-48	-	-	C228D, MCR3935-6, BStE4126M, C35D, ++
2 N 3899		50Hz-Thy	=2N3896: 600V	21b	=TO-48	-	-	C228M, MCR3935-8, BStE4140M, C35M, ++
2 N 3900(A)	USA, Mic, Nsc	Si-N	Uni, In, 18V, 0.1A, 0.36W, 160MHz	7c	TO-98	-	-	BC 169, BC 184, BC 239, BC 549, ++