

2 N 3027	USA, Mot, Tag	F-Thy	30V, 0.5A (Tc=100°), Igt<0.2mA	2a	TO-18	(TAG 103 X)6	2a	(TAG64Y, BRX44, BR103, TAG60Y, TAG62Y)6
2 N 3028		F-Thy	=2N3027: 60V	2a	TO-18	(BRX 49)6	7a	(TAG64F, BRX46, BRX51, TAG60F, TAG62F)6
2 N 3029		F-Thy	=2N3027: 100V	2a	TO-18	(BRX 49)6	7a	(TAG64A, BRX46, BRX51, TAG60A, TAG62A)6
2 N 3030		F-Thy	=2N3027: Igt<0.02mA	2a	TO-18			-
2 N 3031		F-Thy	=2N3028: Igt<0.02mA	2a	TO-18			-
2 N 3032		F-Thy	=2N3029: Igt<0.02mA	2a	TO-18			-
2 N 3033	Sca, Spe, Tix	Si-N	SS, 160V, 0.02A, 0.3W, <5/-ns	2a	TO-18			-
2 N 3034	Sca, Spe, Tix	Si-N	=2N3033: 120V	2a	TO-18			-
2 N 3035	Sca, Spe, Tix	Si-N	=2N3033: 90V	2a	TO-18			-
2 N 3036	USA, Tix	Si-N	LFS, 120/80V, 1.2A, 0.8W, >50MHz, 89/575ns	2a	TO-5			2N2102, 2N2405, 2N3019...20
2 N 3037	Tix	Si-N	LFS, 120V, 0.5A, 0.36W, >50MHz	24b	TO-50			BCX 22, 2N3700...01, 2SD2235, 2SD667, ++
2 N 3038	Tix	Si-N	=2N3037: 100V	24b	TO-50			BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 3039	Tix	Si-P	LFS, 50V, 0.5A, 0.36W, >50MHz	24b	TO-50			BC 327, BC 638, BC 640, 2SB647, ++
2 N 3040	Tix	Si-P	=2N3039: 40V	24b	TO-50			BC 327, BC 636, BC 638, BC 640, ++
2 N 3043	Mot, Ray, Tix	Si-N	=2N2639: 0.35W	10-FLP	TO-89			-
2 N 3044	Mot, Ray, Tix	Si-N	=2N2640: 0.35W	10-FLP	TO-89			-
2 N 3045	Mot, Ray, Tix	Si-N	=2N2641: 0.35W	10-FLP	TO-89			-
2 N 3046	Mot, Ray, Tix	Si-N	=2N2642: 0.35W	10-FLP	TO-89			-
2 N 3047	Mot, Ray, Tix	Si-N	=2N2643: 0.35W	10-FLP	TO-89			-
2 N 3048	Mot, Ray, Tix	Si-N	=2N2644: 0.35W	10-FLP	TO-89			-
2 N 3049	Mot, Sem, Sty	Si-P	Dual, In, 25/20V, 0.1A, 0.35W, >60MHz, F<6dB(1kHz) ΔhFE=0.9...1, ΔUbe<5mV	10-FLP	TO-89			-
2 N 3050	Mot, Sem, Sty	Si-P	=2N3049: ΔhFE=0.8...1, ΔUbe<10mV	10-FLP	TO-89			-
2 N 3051	Mot, Sem, Sty	Si-P	=2N3049: ΔhFE--, ΔUbe--, <35/150ns	10-FLP	TO-89			-
2 N 3052	Ssi, Tix	Si-N	Dual, 35/15V, 0.2A, 0.35W, >200MHz, <62/55ns	10-FLP	TO-89			-
2 N 3053(S)	USA, EUR, Mic	Si-N	LF Drv, 60/40V, 0.7A, 1W, >100MHz (S, AS: TO-39	2a	TO-5	BC 141	2a	BC 140...141, BC 300...302, 2N2218...19, ++
2 N 3053 A	Mot, Rca	Si-N	=2N3053: 80/60V	2a	TO-39	BC 141	2a	BC 140...141, BC 300...302, 2N2218...19A, ++
2 N 3054(S)	USA, EUR, Mic	Si-N	LF P, 90/55V, 4A, 25W, >0.8MHz, hFE=25...100 {BDX 14	22a	TO-66	BD 243 C	17j	BD 243B, BD 539C, 2N3767, 2SD712, ++
	Sie		S: hFE=25...100, S-4: hFE=25...63, S-6: hFE=40...100		SOT-9			
2 N 3054 A	Mot	Si-N	=2N3054: 75W, -10A, >3MHz {2N6049	22a	TO-66	BD 243 C	17j	BD 243B, BD 539C, 2N3767, 2SD712, ++
2 N 3055(E, H, S, U)	USA, EUR	Si-N	LFS P, 100/60V, 15A, 115W, >2.5MHz, hFE=20...70 {BDX15, 2N6246...48	23a	TO-3	2N3055	23a	BD 317, BD 745C, BDW 51C, 2N5629...31, ++
2N3055 A	Mot	Si-N	<4.5/9μs(4A)	23a	TO-3			
2 N 3055 C, V	Sgs	Si-N	=2N3055: 80/60V	23a	TO-3	2N3055	23a	BD 315, BD 745B, BDW 51B, 2N5629...31, ++
2 N 3056	USA, Fch	Si-N	Uni, 100/60V, 1A, 0.4W, >80MHz, hFE=40...120	2a	TO-46			BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 3056 A		Si-N	=2N3056: 140/80V	2a	TO-46			2N3700...01, 2SC2383, 2SC3228
2 N 3057	USA, Fch	Si-N	=2N3056: hFE=100...300	2a	TO-46			BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 3057 A		Si-N	=2N3056: 140/80V, hFE=100...300	2a	TO-46			2N3700...01, 2SC2383, 2SC3228
2 N 3058	USA, Tdy	Si-P	S, Chopper, 6/6/6V, 0.1A, 0.4W	2a	TO-46			-
2 N 3059	USA, Tdy	Si-P	S, Chopper, 10/10/10V, 0.1A, 0.4W	2a	TO-46			-
2 N 3060	USA, Tdy	Si-P	S, Chopper, 70/60/30V, 0.1A, 0.4W	2a	TO-46			-
2 N 3061	USA, Tdy	Si-P	S, Chopper, 70/60/30V, 0.1A, 0.4W	2a	TO-46			-
2 N 3062	Tdy	Si-P	S, Chopper, 90/80/40V, 0.1A, 0.4W	2a	TO-46			-
2 N 3063	Tdy	Si-P	S, Chopper, 90/80/40V, 0.1A, 0.4W	2a	TO-46			-
2 N 3064	Tdy	Si-P	S, Chopper, 110/100/50V, 0.1A, 0.4W	2a	TO-46			-
2 N 3065	Tdy	Si-P	S, Chopper, 110/100/50V, 0.1A, 0.4W	2a	TO-46			-
2 N 3066(A)	Sol, Tix	N-FET	Uni, 50V, Idss>0.8mA, Up<9.5V	2b	TO-18			-
2 N 3067(A)	Sol, Tix	N-FET	Uni, 50V, Idss>0.2mA, Up<4.5V	2b	TO-18			-
2 N 3068(A)	Sol, Tix	N-FET	Uni, 50V, Idss>0.05mA, Up<2.2V	2b	TO-18			-
2 N 3069(A)	Nsc, Sol, Tix	N-FET	Uni, 50V, Idss>2mA, Up<10V	2b	TO-18			-
2 N 3070(A)	Nsc, Sol, Tix	N-FET	Uni, 50V, Idss>0.5mA, Up<5V	2b	TO-18			-
2 N 3071	Nsc, Sol, Tix	N-FET	Uni, 50V, Idss>0.1mA, Up<2.5V	2b	TO-18			-
2 N 3072	USA, Mot, Sgs	Si-P	S, 60V, 0.5A, 0.8W, >130MHz, <40/100ns	2a	TO-39			BSW 23, 2N2904...05(A), 2N3468, 2SA742, ++
2 N 3073	USA, Mot, Sgs	Si-P	=2N3072: 0.36W	2a	TO-18			BSW 24, 2N2906...07(A), 2N4026...29
2 N 3074	Amp, Sty	Ge-P	HF, 30V, 0.02A, 0.14W	5g	TO-12			AF 139, AF 239(S), 2N3283...86
2 N 3075	Amp, Sty	Ge-P	HF, 35V, 0.02A, 0.14W	5g	TO-12			AF 139, AF 239(S), 2N3283...86
2 N 3076	Sca, Ssi, Trw	Si-N	S P, 140V, 10A, 125W, >50MHz					-
2 N 3077	USA	Si-N	Uni, In, 80V, 0.05A, 0.36W, >60MHz, hFE>80	2a	TO-18			2SC1775(A), 2SC2240, 2SC2390, 2SC2459, ++
2 N 3078	USA	Si-N	=2N3077: hFE=25	2a	TO-18			2SC1775(A), 2SC2240, 2SC2390, 2SC2459, ++
2 N 3079	Del, Spc	Si-N	S P, 200/200V, 5A, 150W, >2MHz	38a	TO-36			-
2 N 3080	Del, Spc	Si-N	=2N3079: 300/300V	38a	TO-36			-
2 N 3081	USA, Mot	Si-P	S, 70V, 0.6A, 0.6W, >150MHz, <60/175ns	2a	TO-5			BSW 40, 2N4031, 2N4033, 2N4036
2 N 3082	Gen, Tho	Si-N	Dual, Chopper, 25V, 0.1A, 0.5W	TO-77	(E-BCB-E)			-
2 N 3083	Gen, Tho	Si-N	Dual, Chopper, 25V, 0.1A, 0.5W	TO-77	(E-BCB-E)			-
2 N 3084	Sol, Tdy	N-FET	Uni, 30V, Idss>0.8mA, Up<10V	2f	TO-5			-
2 N 3085	Sol, Tdy	N-FET	=2N3084:	2f	TO-18			-
2 N 3086	Sol, Tdy	N-FET	Uni, 40V, Idss>0.8mA, Up<10V	2f	TO-5			-
2 N 3087	Sol, Tdy	N-FET	=2N3086:	2f	TO-18			-
2 N 3088(A)	Sol, Tdy	N-FET	Uni, 15V, Idss>0.5mA, Up<5V	2f	TO-5			-
2 N 3089(A)	Sol, Tdy	N-FET	Uni, 15V, Idss>0.5mA, Up<5V	2f	TO-18			-
2 N 3107	USA, Sgs, Tix	Si-N	LFS, 100/60V, 1A, 0.8W, >70MHz, hFE=100...300	2a	TO-39	BC 141	2a	BC 141, BSW 66, BSX 46...47, 2N1990, ++
2 N 3108	USA, Sgs, Tix	Si-N	=2N3107: hFE=40...120	2a	TO-39	BC 141	2a	BC 141, BSW 66, BSX 46...47, 2N1990, ++
2 N 3109	USA, Sgs, Tix	Si-N	=2N3107: 80/40V	2a	TO-39	BC 141	2a	BC 140, BSW 65, BSX 45...47, 2N1990, ++
2 N 3110(S)	USA, Sgs, Tix	Si-N	=2N3107: 80V, hFE=40...120	2a	TO-39	BC 141	2a	BC 140, BSW 65, BSX 45...47, 2N1990, ++
2 N 3112	Six	P-FET	Uni, 20V, Idss>0.035mA, Up<4V	5n	TO-72			2N5797
2 N 3113	Six	P-FET	=2N3112:	2a	TO-18			2N5797
2 N 3114(S)	USA, Mot, Tix	Si-N	Vid, 150V, 0.2A, 0.8W, >40MHz	2a	TO-5	BF 259	2a	BF 257...259, BF 657...659, BFR 57...59, ++
2 N 3115	USA, Mot, Mic	Si-N	=2N2958: 0.4W	2a	TO-18			BSS 26, BSV 59, BSX 49, 2N2221...22(A), ++
2 N 3116	USA, Mot, Mic	Si-N	=2N2959: 0.4W	2a	TO-18			BSS 26, BSV 59, BSX 49, 2N2221...22(A), ++
2 N 3117	USA, Sgs, Tix	Si-N	LFS, In, 60V, 0.05A, 0.36W, >60MHz	2a	TO-18	2SC2632	7c(9mm)	2SC1775(A), 2SC2240, 2SC2390, 2SC2459, ++
2 N 3118	USA, Rca	Si-N	FM/VHF A, Drv, 85/60V, 0.5A, PQ>0.4W(150MHz)	2a	TO-5			BFW 47, 2N3553, 2SC2852
2 N 3119	USA, Rca	Si-N	S, 100/80V, 0.5A, 1W, >250MHz, <40/700ns	2a	TO-5			BSW 39, 2N3723
2 N 3120	USA, Mot, Sgs	Si-P	S, 45V, 0.5A, 0.8W, >130MHz, <40/100ns	2a	TO-5			2N3468, 2SA717, 2SA742
2 N 3121	USA, Mot, Sgs	Si-P	=2N3120: 0.36W	2a	TO-18			BSW 24, BSX 36
2 N 3122	USA	Si-N	LF Drv, 50V, 0.5A, 0.8W, >60MHz	2a	TO-5			BC 140...141, BC 300...302, 2N3053, ++
2 N 3123	Sty	Si-N	HFS, 60V, 0.5A, 0.8W, >400MHz	2a	TO-5			BFW 47, BSV 77, BSV 95, 2N3553, ++
2 N 3124	Gen, Csr, Gpd	Ge-P	LFS P, 40V, 15A, 90W	23a	TO-3			AUY 29, 2N1549...60
2 N 3125	Gen, Csr, Gpd	Ge-P	LFS P, 80V, 3.3A, 90W	23a	TO-3			AL 102...103, AUY 20, 2N2141, 2N2146, ++
2 N 3126	Gen, Csr, Gpd	Ge-P	LFS P, 100V, 15A, 90W	23a	TO-3			2N1552, 2N1556, 2N1560
2 N 3127	USA, Mot	Ge-P	VHF/UHF, 25V, 0.05A, 0.1W, >400MHz	5g	TO-72			AF 139, AF 239(S), 2N3283...86
2 N 3128	Nsc	Si-N	Min, LF, 20V, 0.1A, 0.15W, >60MHz	=7c				BC 122...123, BC 146
2 N 3129	Nsc	Si-N	Min, LF, 45V, 0.1A, 0.15W, >60MHz	=7c				BC 123
2 N 3130	Nsc	Si-N	Min, LF, 60V, 0.1A, 0.15W, >60MHz	=7c				-