

TRANSISTOR NUMBER	PM OALT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BFY12	NS	T05	L04	60V	40V	5V	500MA	180C	600MWF	180M		20/300	100MA	RMG	ATB	BSW54	2N2219	1
BFY12B	NS	T05	L04	60V	40V	5V	500MA	180C	600MWF	180M		20/60	100MA	RMG	ATB	BSW54	2N2219	1
BFY12C	NS	T05	L04	60V	40V	5V	500MA	180C	600MWF	180M		40/120	100MA	RMG	ATB	BSW54	2N2219	1
BFY12D	NS	T05	L04	60V	40V	5V	500MA	180C	600MWF	180M		100MN	100MA	RMG	ATB	BSW54	2N2219	1
BFY13	NS	T05	L04	80V	60V	5V	360MA	180C	750MWF	180M		20/300	100MA	RMH	ATB	BSW54	2N2219	1
BFY13B	NS	T05	L04	80V	60V	5V	360MA	180C	750MWF	180M		20/60	100MA	RMH	ATB	BSW54	2N2218A	1
BFY13C	NS	T05	L04	80V	60V	5V	360MA	180C	750MWF	180M		40/120	100MA	RMH	ATB	BSW54	2N2218A	1
BFY13D	NS	T05	L04	80V	60V	5V	360MA	180C	750MWF	180M		100MN	100MA	RMH	ATB	BSW54	2N2219A	1
BFY14	NS	T05	L04	100V	80V	5V	360MA	180C	750MWF	180M		20/300	100MA	AMH	SID	BSW66	2N4001	1
BFY14B	NS	T05	L04	100V	80V	5V	360MA	180C	750MWF	180M		20/60	100MA	AMH	SID	BSW66	2N4001	1
BFY14C	NS	T05	L04	100V	80V	5V	360MA	180C	750MWF	180M		40/120	100MA	AMH	SID	BSW66	2N4001	1
BFY14D	NS	T05	L04	100V	80V	5V	360MA	180C	750MWF	180M		100MN	100MA	AMH	SID	BSW66	2N4001	1
BFY15	NS	T05	L04		20V	6V	1A5	175C	600MWF	50M	48P	8/40	100MA	AMG	OBS	BFY50	2N2297	2
BFY16	NS	T05	L04		20V	6V	1A5	175C	600MWF	100M	47P	20/62	100MA	AMG	OBS	BFY50	2N2297	2
BFY17	NS	T05	L04	40V	30V	3V	120MA		600MWF	100M	5P	40MN	10MA	ALG	ITB	BFY50	2N2297	1
BFY18	NS	T018	L01	60V	40V	3V	100MA	175C	300MWF	200M	7P	30MN	10MA	RLG	ITB	BSW64	2N2222A	0
BFY19	NS	T018	L01	30V	20V	5V	100MA	175C	300MWF	300M	7P	50MN	10MA	RLG	ITB	BSW64	2N2222A	0
BFY22	NS	X25	L55	5V	5V	3V	50MA	125C	50MWF	20M		50MN	50MA	ALG	ITB	BFY87Y	2N	1
BFY23	NS	X25	L55	5V	5V	3V	50MA	125C	50MWF	20M		70MN	50MA	ALG	ITB	BFY87V		1
BFY23A	NS	X25	L55	5V	5V	3V	50MA	125C	50MWF	20M		200MN	200MA	ALN	ITB	BFY87W		1
BFY24	NS	X25	L55	5V	5V	3V	50MA	125C	50MWF	20M		45MN	200MA	ALN	ITB	BFY87A		1
BFY25	NS	T05	L04	60V	40V	6V	100MA	200C	600MWF	200M	6P	30MN	10MA	ALG	ITB	BFY50	2N2297	1
BFY26	NS	T018	L01	60V	40V	6V	200MA		360MWF	200M	6P	30MN	10MA	RMG	ITB	BSW64	2N2897	1
BFY27	NS	T018	L01	70V	50V	5V	200MA	200C	360MWF	250M	4P	40/160	10MA	RLS	ITB	BSW64	2N2222A	1
BFY28	NS	T018	L01	30V	30V	6V	200MA	185C	300MWF	300M	4P	50MN	10MA	VLA	OBS	BSW64	2N2222A	2
BFY29	NS	X16	L55	30V	30V	5V	50MA	150C	50MWF	10M		50MN	50MA	ALG	OBS	BCW36	2N4953	2
BFY30	NS	X16	L55	30V	30V	5V	50MA	150C	50MWF	10M		70MN	50MA	ALG	OBS	BCW36	2N4953	2
BFY31	NS	T039	L04	45V	30V	5V	500MA	175C	2.6WC	60M	25P	40/120	150MA	AMG	OBS	BFY50	2N2297	2
BFY33	NS	T05	L04	50V	30V	7V	500MA	200C	800MWF	40M		40MN	150MA	RMG	SID	BSW54	2N2219	1
BFY34	NS	T039	L04	75V	50V	7V	1A	200C	800MWF	60M	25P	40MN	150MA	AMG	ATTI	BFY51	2N2297	0
BFY37	NS	T018	L01	25V	20V	5V	100MA	175C	300MWF	200M	4P	35MN	10MA	RLG	ITB	BSW64	2N2222A	0
BFY39	NS	T018	L01	45V	25V	5V	100MA	175C	300MWF	100M	8P	35MN	10MA	ALG	ITB	BC107	2N929	0
BFY39/1	NS	T018	L01	45V	25V	5V	100MA	175C	300MWF	100M	8P	35MN	10MA	ALG	VAL	BC107	2N930	1
BFY39/2	NS	T016	L01	45V	25V	5V	100MA	175C	300MWF	100M	8P	100MN	10MA	ALG	VAL	BC107	2N930	1
BFY39/3	NS	T018	L01	45V	25V	5V	100MA	175C	300MWF	100M	8P	200MN	10MA	ALG	VAL	BC107	2N930	1
BFY40	NS	T05	L04	60V	30V	7V	800MA	200C	800MWF	40M	20P	50MN	50MA	AMG	TIB	BFY51	2N2297	0
BFY41	NS	T05	L04	100V	60V	7V	500MA	200C	500MWF	60M	15P	50/150	10MA	AMH	TIB	BFY65	2N4001	1
BFY43	NS	T05	L04	140V	140V	5V	100MA	175C	8007WF	30M		25MN	10MA	TVH	ITB	BF257		1
BFY44	NS	T039	L04	80V	60V	4V	1A	200C	5WC	100M	13P	5MN	500MA	RHP	MBL	BF139		1
BFY45	NS	T039	L04	140V	90V	5V	30MA	200C	700MWF	100M	3P5	40MN	10MA	ALH	SID	BF156	2N1990	0
BFY46	NS	T039	L04	75V	30V	7V	500MA	200C	2.6WC	100M		100MN	150MA	RMG	TIB	BFY52	2N2297	1
BFY47	NS	X16	L55		5V	5V	50MA	125C	75MWF	30M		50/150	250MA	ALN	OBS			2
BFY48	NS	X16	L55		20V	5V	50MA	125C	75MWF	30M		50/150	250MA	ALN	OBS			2
BFY49	NS	X16	L55		30V	5V	50MA	125C	75MWF	30M		50/150	250MA	ALN	OBS			2
BFY50	NS	T05	L04	80V	35V	6V	1A	200C	800MWF	60M	12P	30MN	150MA	AMG	MUB	BFY50	2N1893	0
BFY50E	NS	T05	L04	80V	40V	6V	1A	200C	800MWF	60M	12P	44MN	150MA	AMG	RTC	BFY51	2N2297	0
BFY50I	NS	T018	L01	5V	5V	5V	100MA	175C	500MWF	60M		60MN	100MA	ALN	OBS	BC109	2N930	2
BFY51	NS	T05	L04	60V	30V	6V	1A	200C	800MWF	50	12P	40MN	150MA	AMG	MUB	BFY51	2N2297	0
BFY51I	NS	T018	L01	20V	20V	5V	100MA	175C	250MWF	60M		60MN	100MA	ALN	OBS	BC109	2N930	2
BFY52	NS	T05	L04	40V	20V	6V	1A	200C	800MWF	50M	12P	60MN	150MA	AMG	MUB	BFY51	2N2297	0
BFY53	NS	T05	L04	40V	20V	6V	1A	200C	800MWF	50M	12P	30MN	150MA	AMG	MUB	BFY51	2N2297	0
BFY55	NS	T05	L04	80V	35V	7V	1A	200C	800MWF	60P	12P	40MN	150MA	AMG	RTC	BFY51	2N2297	0
BFY56	NS	T039	L04	80V	55V	7V	1A	200C	800MWF	40M	25P	30MN	150MA	AMG	SGI	BFY51	2N2297	0
BFY56A	NS	T039	L04	80V	45V	7V	1A	200C	800MWF	50M	25P	40MN	150MA	AMG	SGI	BFY51	2N2297	0
BFY56B	NS	T039	L04	80V	45V	7V	1A	200C	800MWF	50M	25P	50/300	150MA	AMG	ATB	BFY51	2N2297	1
BFY57	NS	T039	L04	125V	125V	5V	100MA	200C	800MWF	40M	12P	30/150	30MA	ALE	ATB	BF337	2N4927	1
BFY59	NS	T072	L06	30V	20V		100MA	175C	360MWF			30MN	10MA	RLG	SID	BFX73	2N918	1
BFY63	NS	T039	L04	30V	15V	4V	100MA	200C	650MWF	500M	3P5	20/120	50MA	RMA	ATB	BSW54	2N2219	1
BFY64	PS	T05	L04	40V	40V	5V		200C	700MWF	200M	10P	80MN	10MA	RMG	MCB	BFX29	2N2905A	0
BFY65	NS	T039	L04	100V	80V	7V	100MA	175C	565MWF	50M	15P	50MN	10MA	ALH	TFK	BF156	2N1990	0
BFY66	NS	T01H	L06	30V	15V	3V	100MA	200C	200MWF	60M		20MN	3MA	ULA	TIB	BFY90	2N2857	1
BFY67	NS	T039	L04	75V	30V	7V	500MA	200C	800MWF	60M	25P	40MN	150MA	AMG	VAL	BFY51	2N2297	0
BFY67A	NS	T05	L04	60V	40V	7V	500MA	200C	800MWF	60M	25P	40MN	150MA	AMG	VAL	BFY51	2N2297	1
BFY67B	NS	T05	L04	50V	25V	7V	500MA	200C	800MWF	60M	25P	20MN	50MA	AMG	VAL	BFY51	2N2297	1
BFY67C	NS	T05	L04	50V	25V	5V	500MA	200C	3WC	60M	25P	30MN	150MA	AMG	VAL	BFY51	2N2297	1
BFY68	NS	T039	L04	75V	30V	7V	500MA	200C	800MWF	70M	25P	100MN	150MA	AMG	VAL	BFY51	2N2297	0
BFY68A	NS	T05	L04	60V	40V	7V	500MA	200C	800MWF	60M	25P	50/150	1MA	AMG	VAL	BFY51	2N2297	1
BFY69	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		50MN	2MA	ALN	TFK			1
BFY69A	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		50MN	2MA	ALN	OBS			2
BFY69B	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		50MN	2MA	ALN	OBS			2
BFY69G	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		85/140	500MA	ALN	TFK			1
BFY69R	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		40/65	500MA	ALN	TFK			1
BFY69V	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		130MN	500MA	ALN	TFK			1
BFY69Y	NS	X25	L80	25V	15V	5V	50MA	125C	105MWF	50M		55/95	500MA	ALN	TFK			1
BFY70	NS	T05	L04	60V	40V	4V	1A	200C	5WC	100M	13P	5MN	500MA	VHP	TIB	BFY44		1