

BUK 455-200A,B	Phi	MOS-N-FET-e	=BUK 445-200A,B: A=14/56A, B=13/52A, 125W	17p	TO-220	-
BUK 455-400A,B	Phi	MOS-N-FET-e	=BUK 445-400A,B: A=7,3/29A, B=6,5/26A, 100W	17p	TO-220	-
BUK 455-450B	Phi	MOS-N-FET-e	=BUK 445-450B: 5,7A, 100W	17p	TO-220	-
BUK 455-500A,B	Phi	MOS-N-FET-e	=BUK 445-500A,B: A=5,7/23A, B=5,3/21A, 100W	17p	TO-220	BUK 455/600A,B 17p
BUK 455-600A,B	Phi	MOS-N-FET-e	=BUK 445-600A,B: A=4,5/18A, B=4/16A, 100W	17p	TO-220	BUK 455/600A,B 17p
BUK 456-50A,B	Phi	MOS-N-FET-e	VFET, 50/30V, 150W, 90/290ns(3A) A: 52/208A, <28mΩ(29A), B: 51/200A, <30mΩ(29A)	17p	TO-220	-
BUK 456-60A,B	Phi	MOS-N-FET-e	=BUK 456-50A,B: 60/30V	17p	TO-220	-
BUK 456-100A,B	Phi	MOS-N-FET-e	VFET, 100/30V, 150W, 60/215ns(3A) A: 34/136A, <57mΩ(15A), B: 32/128A, <65mΩ(15A)	17p	TO-220	-
BUK 456-200A,B	Phi	MOS-N-FET-e	VFET, 200/30V, 150W, 60/195ns(3A) A: 19/76A, <0,16Ω(10A), B: 17/68A, <0,2Ω(10A)	17p	TO-220	-
BUK 456-800A,B	Phi	MOS-N-FET-e	VFET, 800/30V, 125W, 35/170ns(2,3A) A: 4/16A, <3Ω(1,5A), B: 3,5/14A, <4Ω(1,5A)	17p	TO-220	-
BUK 456-1000A,B	Phi	MOS-N-FET-e	VFET, 1000/30V, 125W, 35/170ns(2,3A) A: 3,5/14A, <4Ω(1,5A), B: 3,1/12A, <5Ω(1,5A)	17p	TO-220	-
BUK 457-400A,B	Phi	MOS-N-FET-e	VFET, 400/30V, 150W, 80/275ns(2,8A) A: 13/52A, <0,4Ω(6,5A), B: 11/44A, <0,5Ω(6,5A)	17p	TO-220	-
BUK 457-450B	Phi	MOS-N-FET-e	VFET, 450/30V, 10A, 150W, <0,6Ω(6,5A), 80/275ns	17p	TO-220	-
BUK 457-500A,B	Phi	MOS-N-FET-e	VFET, 500/30V, 150W, 80/275ns(2,8A) A: 10/40A, <0,6Ω(6,5A), B: 9/36A, <0,8Ω(6,5A)	17p	TO-220	-
BUK 457-600A,B	Phi	MOS-N-FET-e	VFET, 600/30V, 150W, 80/275ns(2,8A) A: 8/32A, <1Ω(6,5A), B: 7,1/28A, <1,2Ω(6,5A)	17p	TO-220	-
BUK 471-....	Phi	MOS-N-FET-e	=BUK 441-....	17c	TO-220Iso	*BUK 441-....
BUK 472-....	Phi	MOS-N-FET-e	=BUK 442-....	17c	TO-220Iso	*BUK 442-....
BUK 473-....	Phi	MOS-N-FET-e	=BUK 443-....	17c	TO-220Iso	*BUK 443-....
BUK 474-....	Phi	MOS-N-FET-e	=BUK 444-....	17c	TO-220Iso	*BUK 444-....
BUK 475-....	Phi	MOS-N-FET-e	=BUK 445-....	17c	TO-220Iso	*BUK 445-....
BUK 476-....	Phi	MOS-N-FET-e	=BUK 446-....	17c	TO-220Iso	*BUK 446-....
BUK 539-60A	Phi	MOS-N-FET-e	VFET, LogL, 60/15V, 50/400A, 230W, <15mΩ(50A)	18p	TO-3P	-
BUK 541-60A,B	Phi	MOS-N-FET-e	VFET, LogL, 60/15V, 20W, 36/40ns(3A) A: 5/20A, <0,4Ω(4A), B: 4,8/20A, <0,5Ω(4A)	17c	SOT-186	BUK 542-100, BUK 554-200, 2SK1260
BUK 541-100A,B	Phi	MOS-N-FET-e	VFET, LogL, 100/15V, 3/12A, 20W, 36/30ns(3A) A: <0,85Ω(2,5A), B: <1,1Ω(2,5A)	17c	SOT-186	BUK 542-200, 2SK1260
BUK 542-50A,B	Phi	MOS-N-FET-e	VFET, LogL, 50/15V, 22W, 72/95ns(3A) A: 9,2/37A, <0,15Ω(8,5A), B: 8,4/33A, <0,18Ω(8,5A)	17c	SOT-186	BUK 543-50, 2SK1033, 2SK1256, 2SK1344,++
BUK 542-60A,B	Phi	MOS-N-FET-e	=BUK 542-50A,B: 60/15V	17c	SOT-186	BUK 543-60, 2SK1033, 2SK1256, 2SK1344,++
BUK 542-100A,B	Phi	MOS-N-FET-e	VFET, LogL, 100/15V, 22W, 57/80ns(3A) A: 6,3/25A, <0,28Ω(5,5A), B: 5,6/22A, <0,35Ω(5,5A)	17c	SOT-186	BUK 543-100, 2SK1261, 2SK1305, 2SK1556++
BUK 543-50A,B	Phi	MOS-N-FET-e	VFET, LogL, 50/15V, 25W, 115/145ns(3A) A: 13/52A, <85mΩ(10A), B: 12/48A, <0,1Ω(10A)	17c	SOT-186	BUK 545-100, 2SK1033, 2SK1256, 2SK1344++
BUK 543-60A,B	Phi	MOS-N-FET-e	=BUK 543-50A,B: 60/15V	17c	SOT-186	BUK 545-100, 2SK1033, 2SK1256, 2SK1344
BUK 543-100A,B	Phi	MOS-N-FET-e	VFET, LogL, 100/15V, 25W, 55/130ns(3A) A: 8,3/33A, <0,18Ω(5A), B: 7,5/30A, <0,22Ω(5A)	17c	SOT-186	BUK 545-100, 2SK1035, 2SK1261, 2SK1305++
BUK 545-50A,B	Phi	MOS-N-FET-e	VFET, LogL, 50/15V, 30W, 145/270ns(3A) A: 20/80A, <42mΩ(20A), B: 18/72A, <55mΩ(20A)	17c	SOT-186	2SK943, 2SK1095, 2SK1345...46, 2SK1951,++
BUK 545-60A,B	Phi	MOS-N-FET-e	=BUK 545-50A,B: 60/15V	17c	SOT-186	2SK943, 2SK1095, 2SK1345...46, 2SK1951,++
BUK 545-100A,B	Phi	MOS-N-FET-e	VFET, LogL, 100/15V, 30W, 90/215ns(3A) A: 13/52A, <85mΩ(13A), B: 12/48A, <0,11Ω(13A)	17c	SOT-186	2SK1034...35, 2SK1306, 2SK1558
BUK 545-200A,B	Phi	MOS-N-FET-e	VFET, LogL, 200/15V, 30W, 70/180ns(3A) A: 7,6/30A, <0,23Ω(7A), B: 7/28A, <0,28Ω(7A)	17c	SOT-186	2SK2160...61
BUK 551-100A,B	Phi	MOS-N-FET-e	=BUK 541-100A,B: 40W	17p	TO-220	-
BUK 552-50A,B	Phi	MOS-N-FET-e	=BUK 542-50A,B: A=14/56A, B=13/56A, 60W	17p	TO-220	2SK971, 2SK1555
BUK 552-60A,B	Phi	MOS-N-FET-e	=BUK 542-60A,B: A=14/56A, B=13/52A, 60W	17p	TO-220	2SK971, 2SK1300...01, 2SK1559, 2SK1561,++
BUK 552-100A,B	Phi	MOS-N-FET-e	=BUK 542-100A,B: A=10/40V, B=8,5/34A, 60W	17p	TO-220	2SK1300...01, 2SK1559, 2SK1561
BUK 553-50A,B	Phi	MOS-N-FET-e	=BUK 543-50A,B: A=21/84A, B=20/80A, 75W	17p	TO-220	2SK972, 2SK1115...16, 2SK1302, 2SK1347,++
BUK 553-60A,B	Phi	MOS-N-FET-e	=BUK 543-60A,B: A=21/84A, B=20/80A, 75W	17p	TO-220	2SK972, 2SK1115...16, 2SK1302, 2SK1347,++
BUK 553-100A,B	Phi	MOS-N-FET-e	=BUK 543-100A,B: A=13/52A, B=12/48A, 75W	17p	TO-220	2SK1301, 2SK1559, 2SK1561
BUK 554-200A,B	Phi	MOS-N-FET-e	VFET, LogL, 200/15V, 90W, 91/170ns(2,9A) A: 9,2/36A, <0,4Ω(3,5A), B: 8,2/33A, <0,5Ω(3,5A)	17p	TO-220	BUK 555-200
BUK 555-50A,B	Phi	MOS-N-FET-e	=BUK 545-50A,B: A=39/156A, B=35/140A, 125W	17p	TO-220	-
BUK 555-60A,B	Phi	MOS-N-FET-e	=BUK 545-60A,B: A=39/156A, B=35/140A, 125W	17p	TO-220	-
BUK 555-100A,B	Phi	MOS-N-FET-e	=BUK 545-100A,B: A=25/100A, B=22/88A, 125W	17p	TO-220	-
BUK 555-200A,B	Phi	MOS-N-FET-e	=BUK 545-200A,B: A=14/56A, B=13/52A, 125W	17p	TO-220	-
BUK 556-60A	Phi	MOS-N-FET-e	VFET, LogL, 60/15V, 50/200A, 150W, <26mΩ(25A)	17p	TO-220	2SK1542
BUK 571-....	Phi	MOS-N-FET-e	=BUK 541-....	17c	TO-220Iso	*BUK 541-....
BUK 572-....	Phi	MOS-N-FET-e	=BUK 542-....	17c	TO-220Iso	*BUK 542-....
BUK 573-....	Phi	MOS-N-FET-e	=BUK 543-....	17c	TO-220Iso	*BUK 543-....
BUK 575-....	Phi	MOS-N-FET-e	=BUK 545-....	17c	TO-220Iso	*BUK 545-....
BUK 617-500AE,BE	Phi	MOS-N-FET-e	FREDFET, 500/30V, 310W, 110/400ns(29A) A: 29/116A, <0,15Ω(16A), B: 27/108A, <0,18Ω(16A)	=67	SOT-227A (SGDauxS)	-
BUK 627-400A,B	Phi	MOS-N-FET-e	FREDFET, 400V, 45W, 80/275ns(2,8A) A: 6,9A, <0,5Ω(6,5A), B: 6,2A, <0,6Ω(6,5A)	16c	SOT-199	-
BUK 627-450B	Phi	MOS-N-FET-e	FREDFET, 450/30V, 5,6A, 45W, <0,65Ω, 80/275ns	16c	SOT-199	-
BUK 627-500A,B,C	Phi	MOS-N-FET-e	FREDFET, 500/30V, 45W, 80/275ns(2,8A), A: 5,6/22A, <0,65Ω, B: 4,8/19A, <0,8Ω, C: 4,5/-A, <0,9Ω(6,5A)	16c	SOT-199	-
BUK 627-600A,B,C	Phi	MOS-N-FET-e	FREDFET, 600/30V, 45W, 80/275ns(2,8A), A: 4,3/-A, <0,1Ω, B: 3,9/-A, <1,2Ω, C: 3,5/-A, <1,4Ω(6,5A)	16c	SOT-199	-
BUK 637-400A,B	Phi	MOS-N-FET-e	=BUK 627-400A,B: A=14/56A, B=12/48A, 180W	18p	TO-3P	BUK 638-500
BUK 637-450B	Phi	MOS-N-FET-e	=BUK 627-450B: 11A, 180W	18p	TO-3P	BUK 638-500
BUK 637-500A,B,C	Phi	MOS-N-FET-e	=BUK 627-500...: A=11/44A, B=10/40A, C=9,5/-A, 180W	18p	TO-3P	BUK 638-500
BUK 637-600A,B,C	Phi	MOS-N-FET-e	=BUK 627-600...: A=9/-A, B=7,8/-A, C=7/-A, 180W	18p	TO-3P	BUK 638-800
BUK 638-500A,B	Phi	MOS-N-FET-e	FREDFET, 500/30V, 220W, 120/410ns(2,8A) A: 14,6/58A, <0,48Ω(8A), B: 13/52A, <0,6Ω(8A)	18p	TO-3P	-
BUK 638-800A,B	Phi	MOS-N-FET-e	FREDFET, 800/30V, 220W, 160/450ns(2,5A) A: 7,3/29A, <1,8Ω(4A), B: 6,3/25A, <2,4Ω(4A)	18p	TO-3P	-
BUK 638-1000A,B	Phi	MOS-N-FET-e	FREDFET, 1000/30V, 220W, 160/450ns(2,5A) A: 6,2/25A, <2,4Ω(3,5A), B: 5,6/22A, <3Ω(3,5A)	18p	TO-3P	-
BUK 655-450B	Phi	MOS-N-FET-e	FREDFET, 450V, 5,7/23A, 100W, <1,3Ω(2,5A), 55/140ns	17p	TO-220	(BUZ 215)?
BUK 655-500A,B,C	Phi	MOS-N-FET-e	FREDFET, 500/30V, 100W, 55/140ns(2,6A), A: 5,7/23A, <1,3Ω(2,5A), B: 5,3/21A, <1,5Ω(2,5A), C: 5/-A, <1,7Ω	17p	TO-220	-
BUK 657-400A,B	Phi	MOS-N-FET-e	=BUK 627A,B: A=13/52A, B=11/44A, 150W	17p	TO-220	-
BUK 657-450B	Phi	MOS-N-FET-e	=BUK 627-450B: 10/-A, 150W	17p	TO-220	-