

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE MFR	EUR EQUIV	USA EQUIV	ISS	
PN3646	NS	T092	L14	40V	15V	5V	500MA	150C	600MWF	350M	5P	30/120	30MA	UMS	NAT	BSX59	2N3646	2
PN3691	NS	T092	L14	35V	20V	4V	100MA	150C	600MWF	200M	3P5	40/160	10MA	VLA	NAT	BF368	2N3691	2
PN3692	NS	T092	L14	35V	20V	4V	100MA	150C	600MWF	200M	3P5	100MN	10MA	VLA	NAT	BF369	2N3692	2
PN3694	NS	T092	L14	45V	45V	4V	100MA	150C	600MWF	200M	6P	100MN	10MA	VLA	NAT	BSW64	2N3694	2
PN4121	PS	T092	L14	40V	40V	5V	1A	150C	600MWF	400M	4P5	70/200	10MA	RMS	NAT	BC309	2N4121	2
PN4122	PS	T092	L14	40V	40V	5V	1A	150C	600MWF	450M	4P5	150MN	10MA	RMS	NAT	BC309	2N4122	2
PN4141	NS	T092	L14	60V	30V	5V	1A	150C	600MWF	250M	8P	100MN	150MA	RMG	NAT	BSW64	2N4141	2
PN4142	PS	T092	L14	60V	40V	5V	1A	150C	600MWF	200M	8P	40/120	150MA	RMG	NAT	BC328	2N4142	2
PN4143	PS	T092	L14	60V	40V	5V	1A	150C	600MWF	200M	8P	100MN	150MA	RMG	NAT	BC328	2N4143	2
PN4146	NS	T092	L14	60V	30V	5V	1A	150C	600MWF	250M	8P	40/120	150MA	RMG	NAT	BC387	2N4140	2
PN4248	PS	T092	L14	40V	40V	5V	100MA	150C	600MWF	100M	5P	50MN	100UA	ALN	NAT	BC206	2N4248	2
PN4249	PS	T092	L14	60V	50V	5V	100MA	150C	600MWF	100M	5P	100MN	100UA	ALN	NAT	BC204	2N4249	2
PN4250	PS	T092	L14	40V	40V	5V	100MA	150C	600MWF	100M	5P	250MN	100UA	ALN	NAT	BC206	2N4250	2
PN4250A	PS	T092	L14	60V	60V	5V	100MA	150C	600MWF	100M	5P	250MN	100UA	ALN	NAT	BC206	2N4250A	2
PN4258	PS	T092	L14	12V	12V	4V5	100MA	150C	600MWF	700M	3P	30/120	10MA	ULS	NAT	BSW25	2N4258	2
PN4258A	PS	T092	L14	12V	12V	4V5	100MA	150C	600MWF	700M	3P	30/120	10MA	ULS	NAT	BSW25	2N4258A	2
PN4274	NS	T092	L14	30V	12V	4V5	300MA	150C	600MWF	400M	4P	35/120	10MA	ULS	NAT	BSX20	2N4274	2
PN4275	NS	T092	L14	40V	15V	4V5	300MA	150C	600MWF	400M	4P	35/120	10MA	ULS	NAT	BSX20	2N4275	2
PN4354	PS	T092	L14	60V	60V	5V	1A	150C	600MWF	100M	30P	50/500	10MA	RMG	NAT	BF593	2N4354	2
PN4355	PS	T092	L14	60V	60V	5V	1A	150C	600MWF	100M	30P	100MN	10MA	RMG	NAT	BF593	2N4355	2
PN4356	PS	T092	L14	80V	80V	5V	1A	150C	600MWF	100M	30P	50/250	10MA	RMH	NAT	BF593	2N4356	2
PN4916	PS	T092	L14	30V	30V	5V	200MA	150C	600MWF	400M	4P5	15/200	50MA	AMG	NAT	BSW24	2N4916	2
PN4917	PS	T092	L14	30V	30V	5V	200MA	150C	600MWF	450M	4P5	150MN	10MA	AMG	NAT	BSW24	2N4917	2
PN5127	NS	T092	L14	20V	12V	3V	100MA	150C	600MWF	150M	3P5	15/300	2MA	RLG	NAT	BC347A	2N5127	2
PN5128	NS	T092	L14	15V	12V	3V	1A	150C	600MWF	200M	10P	35/350	50MA	AMG	NAT	BC387	2N5128	2
PN5129	NS	T092	L14	15V	12V	3V	1A	150C	600MWF	200M	10P	35/350	50MA	AMG	NAT	BC387	2N5129	2
PN5130	NS	T092	L14	30V	12V	1V	30MA	150C	600MWF	450M	1P7	15/250	8MA	ULA	NAT	BF366	2N5130	2
PN5131	NS	T092	L14	20V	15V	3V	100MA	150C	600MWF	100M	6P	35/500	10MA	RLS	NAT	BSX20	2N5131	2
PN5132	NS	T092	L14	20V	20V	3V	100MA	150C	600MWF	200M	3P5	30/400	10MA	RLS	NAT	BSX20	2N5132	2
PN5133	NS	T092	L14	20V	18V	3V	100MA	150C	600MWF	40M	5P	60MN	1MA	ALN	NAT	BC349B	2N5133	2
PN5134	NS	T092	L14	20V	10V	3V5	300MA	150C	600MWF	250M	4P	20/150	10MA	ULS	NAT	BSX20	2N5134	2
PN5135	NS	T092	L14	30V	25V	4V	1A	150C	600MWF	40M	25P	50MN	10MA	AMG	NAT	BC387	2N5135	2
PN5136	NS	T092	L14	30V	20V	3V	1A	150C	600MWF	40M	30P	20/400	150MA	AMG	NAT	BC387	2N5136	2
PN5137	NS	T092	L14	30V	20V	3V	1A	150C	600MWF	40M	30P	20/400	150MA	AMG	NAT	BC387	2N5137	2
PN5138	PS	T092	L14	30V	30V	5V	200MA	150C	600MWF	30M	7P	50/800	100UA	ALG	NAT	BC206	2N5138	2
PN5139	PS	T092	L14	20V	20V	5V	200MA	150C	600MWF	300M	5P	40MN	1MA	ALG	NAT	BC307	2N5139	2
PN5140	PS	T092	L14	5V	5V	4V	100MA	150C	600MWF	400M	5P	20/40	10MA	ULS	NAT	BSW25	2N5140	2
PN5142	PS	T092	L14	20V	20V	4V	500MA	150C	600MWF	100M	10P	30MN	50MA	RMS	NAT	BF595	2N5142	2
PN5143	PS	T092	L14	20V	20V	4V	500MA	150C	600MWF	100V	10P	30MN	50MA	RMS	NAT	BC328	2N5143	2
PN5179	NS	T092	L16	20V	15V	2V5	100MA	150C	600MWF	900M	1P	25/250	3MA	ULA	NAT	BFY90	2N5179	2
PN5910	PS	T092	L14	20V	20V	4V5	100MA	150C	600MWF	700M	3P	30/120	10MA	ULS	NAT	BSW25	2N5910	2
PN7055	NS	T092	L14	220V	220V	7V	100MA	150C	600MWF	50M	3P5	40MN	10MA	TVE	NAT	BF393	2N7055	2
PNP3054	PS	T066	L43	90V	55V		4A	200C	25WC	400K		25MN	500MA	AHG	RSC	BDX14	2N5954	2
PNP3055	PS	T03	L05	100V	60V		15A	200C	115WC	400K		20MN	4A	AHG	RSC	BDX18	2N6029	2
PPC3055	NS	TOP66	L32	100V	60V		15A	200C	90WC			20MN	4A	AHG	PPC	BDX73	2N6101	2
PPC5038	NS	T03	L05	110V	90V	5V	20A	200C	175WC	60M		20MN	12A	AHH	PPC	BDY76	2N5269	2
PPC5038P	PS	T03	L05	110V	90V	5V	20A	200C	175WC	60M		20MN	12A	AHH	PPC	BLX84	2N6331	2
PPC5671	NS	T03	L05	110V	90V	5V	30A	200C	175WC	50M		20MN	15A	AHH	PPC			2
PPC5671P	PS	T03	L05	110V	90V	5V	30A	200C	175WC	50M		20MN	15A	AHH	PPC			2
PPD6385	PS	T03	L05	80V	80V	5V	10A	200C	100WC	5M		1KMN	5A	AHD	PPC	BDX64B	2N6052	2
PPR1007	NS	T060	L61	60V	40V	10V			35WC			15MN	3A	AHG	PPC			2
RC5683	NS	T039	L04	40V	40V	5V	6A	150C	10WC	20M	60P	1KMN	2A	AHO	RCU		2N5426	2
RCA1A01	NS	T039	L04	70V	4V	1A	200C	5WC	120M	40MN		10MA	ALG	MOU	BSW66	2N4001	2	
RCA1A02	PS	T039	L04	50V	4V	1A	200C	7WC	60M	30MN		100UA	ALN	MOU	BF23	2N4929	2	
RCA1A03	NS	T039	L04	95V	4V	2A	200C	10WC	50M	70MN		300MA	AMH	MOU	BFT39	2N5682	2	
RCA1A04	PS	T039	L04	95V	4V	2A	200C	10WC	50M	70MN		300MA	AMH	MOU	BC345	2N4033	2	
RCA1A05	PS	T039	L04	75V	4V	1A	200C	5WC	60M	50MN		150MA	AMG	MOU	SC345	2N4033	2	
RCA1A06	NS	T039	L04	75V	4V	1A	200C	5WC	120M	50MN		150MA	AMG	MOU	BSW66	2N4001	2	
RCA1A07	NS	T039	L04	50V	40V	3V	1A	200C	5WC	120M		50MN	3MA	ALG	MOU	BSW66	2N4001	2
RCA1A08	PS	T039	L04	50V	40V	5V	1A	200C	7WC	60M		70MN	50MA	AMG	MOU	BF595	2N4033	2
RCA1A09	NS	T039	L04		175V	6V	1A	200C	10WC	15M		20MN	10MA	AME	MOU	BD150	2N3439	2
RCA1A10	PS	T039	L04		175V	6V	1A	200C	10WC	15M		40MN	10MA	AME	MOU	BFT19B	2N5416	2
RCA1A11	NS	T039	L04		175V	6V	1A	200C	10WC	15M		40MN	1MA	AME	MOU	BD150	2N3439	2
RCA1A15	NS	T039	L04		100V	5V	1A	200C	10WC	15M		20MN	10MA	AMH	MOU	BSW67	2N5682	2
RCA1A16	PS	T039	L04		100V	5V	1A	200C	10WC	15M		40MN	10MA	AMH	MOU	BFT19B	2N5416	2
RCA1A17	NS	T039	L04		90V	4V	1A	200C	5WC	120M		40MN	10MA	AMH	MOU	BSW66	2N4001	2
RCA1A18	NS	T039	L04		10V	4V	1A	200C	7WC	120M		40MN	10MA	AMG	MOU	BFY50	2N2297	2
RCA1A19	PS	T039	L04		10V	4V	1A	200C	7WC	60M		40MN	10MA	AMG	MOU	BF595	2N1132	2
RCA1B01	NS	T03	L05	95V	7V	15A	200C	115WC	800K	20MN		20MN	4A	AHG	MOU	BDX40	2N3772	2
RCA1C03	NS	TOP66	L32	120V	100V	5V	4A	150C	40WC	4M		50MN	1A	AHH	MOU	BD241C		2
RCA1C04	PS	TOP66	L32	120V	100V	5V	4A	150C	40WC	10M		50MN	1A	AHH	MOU	BD244C		2
RCA1C05	NS	TOP66	L32	140V	120V	5V	4A	150C	40WC	4M		40MN	1A	AHH	MOU	BU409		2
RCA1C06	PS	TOP66	L32	140V	120V	5V	4A	150C	40WC	10M		40MN	1A	AHH	MOU			2
RCA1E02	NS	T066	L43	200V	175V	5V	2A	200C	35WC			30MN	300MA	AHE	MOU	BUX67A	2N3738	2
RCA1E03	PS	T066	L43	200V	175V	5V	2A	200C	35WC			30MN	300MA	AHE	MOU	BUX66C	2N6214	2