

2 N 6231	Si-P	=2N6229: 140V	23a	MJ 15016	23a	
2 N 6236	50Hz-Thy	30V, 2,6A(Tc=90°), Igt/Ih<0,2/<5mA	14e	TIC 106 M	17e	4
2 N 6237	50Hz-Thy	=2N6236: 50V	14e	TIC 106 M	17e	4
2 N 6238	50Hz-Thy	=2N6236: 100V	14e	TIC 106 M	17e	4
2 N 6239	50Hz-Thy	=2N6236: 200V	14e	TIC 106 M	17e	4
2 N 6240	50Hz-Thy	=2N6236: 400V	14e	TIC 106 M	17e	4
2 N 6241	50Hz-Thy	=2N6236: 600V	14e	TIC 106 M	17e	4
2 N 6246	Si-P	NF/S-L, 70V, 15A, 125W, >6MHz	23a	BD 318	23a	
2 N 6247	Si-P	=2N6246: 90V	23a	BD 318	23a	
2 N 6248	Si-P	=2N6246: 110V	23a	BD 318	23a	
2 N 6249	Si-N	S-L, 300/200V, 10A, 175W, 8MHz	23a	(S 2530 A)	23a	
2 N 6250	Si-N	=2N6249: 375/275V	23a	(S 2530 A)	23a	
2 N 6251	Si-N	=2N6249: 450/350V	23a	(S 2530 A)	23a	
2 N 6288	Si-N	NF/S-L, 40V, 7A, 40W, >4MHz	17j	BD 809	17j	
2 N 6289	Si-N	=2N6288	17j	BD 809	17j	
2 N 6290	Si-N	=2N6288: 60V	17j	BD 809	17j	
2 N 6291	Si-N	=2N6288: 60V	17j	BD 809	17j	
2 N 6292	Si-N	=2N6288: 80V	17j	BD 809	17j	
2 N 6293	Si-N	=2N6288: 80V	17j	BD 809	17j	
2 N 6342	Triac	200V, 8A(Tc=80°), Igt/Ih<50/<40mA	17j	-	-	
2 N 6343	Triac	=2N6342: 400V	17j	-	-	
2 N 6344	Triac	=2N6342: 600V	17j	-	-	
2 N 6345	Triac	=2N6342: 800V	17j	-	-	
2 N 6346	Triac	200V, 8A(Tc=80°), Igt/Ih<75/<40mA	17j	-	-	
2 N 6347	Triac	=2N6346: 400V	17j	-	-	
2 N 6348	Triac	=2N6346: 600V	17j	-	-	
2 N 6349	Triac	=2N6346: 800V	17j	-	-	
2 N 6394	50Hz-Thy	50V, 12A(Tc=90°), Igt/Ih<30/<40mA	17e	-	-	
2 N 6395	50Hz-Thy	=2N6394: 100V	17e	-	-	
2 N 6396	50Hz-Thy	=2N6394: 200V	17e	-	-	
2 N 6397	50Hz-Thy	=2N6394: 400V	17e	-	-	
2 N 6398	50Hz-Thy	=2N6394: 600V	17e	-	-	
2 N 6399	50Hz-Thy	=2N6394: 800V	17e	-	-	
2 N 6469	Si-P	NF/S-L, 50V, 15A, 125W, >10MHz	23a	BD 318	23a	
2 N 6470	Si-N	NF/S-L, 50V, 15A, 125W, >5MHz	23a	BD 317	23a	
2 N 6471	Si-N	=2N6470: 70V	23a	BD 317	23a	
2 N 6472	Si-N	=2N6470: 90V	23a	BD 317	23a	
2 N 6515	Si-N	NF/S/Vid, 250V, 0,5A, 0,625W, >40MHz	7e	BF 420 A	7c	
2 N 6516	Si-N	=2N6515: 300V	7e	BF 420 A	7c	
2 N 6517	Si-N	=2N6515: 350V	7e	-	-	
2 N 6518	Si-P	NF/S/Vid, 250V, 0,5A, 0,625W, >40MHz	7e	BF 421 A	7c	
2 N 6519	Si-P	=2N6518: 300V	7e	BF 421 A	7c	
2 N 6520	Si-P	=2N6518: 350V	7e	-	-	
2 N 6551	Si-N	NF/S-L, 60V, 1A, 10W, >75MHz	13m	(2SC4135)	30j	4
2 N 6552	Si-N	=2N6551: 80V	13m	(2SC4135)	30j	4
2 N 6553	Si-N	=2N6551: 100V	13m	(2SC4135)	30j	4
2 N 6554	Si-P	NF/S-L, 60V, 1A, 10W, >75MHz	13m	(2SA1593)	30j	4
2 N 6555	Si-P	=2N6554: 80V	13m	(2SA1593)	30j	4
2 N 6556	Si-P	=2N6554: 100V	13m	(2SA1593)	30j	4
2 N 6564	50Hz-Thy	300V, 0,5A(Tc=55°), Igt/Ih<0,2/<5mA	7n	BRX 49	7a	
2 N 6565	50Hz-Thy	=2N6564: 400V	7n	BRX 49	7a	
2 N 6605	50Hz-Thy	30V, 0,275A(Ta=55°), Igt/Ih<0,2/<5mA	2a	(TAG 103 X)	2a	6
2 N 6606	50Hz-Thy	=2N6605: 60V	2a	(BRX 49)	7a	6
2 N 6607	50Hz-Thy	=2N6605: 100V	2a	(BRX 49)	7a	6
2 N 6608	50Hz-Thy	=2N6605: 200V	2a	(BRX 49)	7a	6
2 N 6609	Si-P	NF/S-L, 160/140V, 16A, 150W, >2MHz	23a	MJ 15016	23a	