

MPSW 01	Si-N	NF-Tr/E, 40V, 1A, 1W, >50MHz	7e(9mm)	2SD1207	7c(9mm)
MPSW 01 A	Si-N	=MPSW 01: 50V	7e(9mm)	2SD1207	7c(9mm)
MPSW 05	Si-N	Uni, 60V, 0.5A, 1W, >50MHz	7e(9mm)	2SD1812	7c(9mm)
MPSW 06	Si-N	=MPSW 05: 80V	7e(9mm)	2SD1812	7c(9mm)
MPSW 10	Si-N	Vid, 300/300V, 0.5A, 1W, >45MHz	7e(9mm)	BF 420 A	7c
MPSW 13	Si-N-Darl	Uni, 30V, 1A, 1W, >125MHz, B>10000	7e(9mm)	2SD1153	7c(9mm)
MPSW 14	Si-N-Darl	=MPSW 13: B>20000	7e(9mm)	(2SD1153)	7c(9mm) 13
MPSW 42	Si-N	Vid, 300/300V, 0.5A, 1W, >50MHz	7e(9mm)	BF 420 A	7c
MPSW 43	Si-N	=MPSW 42: 200/200V	7e(9mm)	BF 420 A	7c
MPSW 45	Si-N-Darl	Uni, 50V, 1A, 1W, >100MHz, B>25000	7e(9mm)	-	
MPSW 45A	Si-N-Darl	=MPSW 45: 60V	7e(9mm)	-	
MPSW 51	Si-P	NF-Tr/E, 40V, 1A, 1W, >50MHz	7e(9mm)	2SB892	7c(9mm)
MPSW 51 A	Si-P	=MPSW 51: 50V	7e(9mm)	2SB892	7c(9mm)
MPSW 55	Si-P	Uni, 60V, 0.5A, 1W, >50MHz	7e(9mm)	2SB1212	7c(9mm)
MPSW 56	Si-P	=MPSW 55: 80V	7e(9mm)	2SB1212	7c(9mm)
MPSW 60	Si-P	Vid, 300/300V, 0.5A, 1W, >60MHz	7e(9mm)	BF 421 A	7c
MPSW 63	Si-P-Darl	Uni, 30V, 0.5A, 1W, >125MHz, B>10000	7e(9mm)	2SB865	7c(9mm)
MPSW 64	Si-P-Darl	=MPSW 63: B>20000	7e(9mm)	(2SB865)	7c(9mm) 13
MPSW 92	Si-P	Vid, 300/300V, 0.5A, 1W, >50MHz	7e(9mm)	BF 421 A	7c
MPSW 93	Si-P	=MPSW 92: 200/200V	7e(9mm)	BF 421 A	7c

MR

MR-1	Si-Di	Gl, Uni, 400V, 1,2A	31a	BYD 33 M	31a
MR-1 C	Si-Di	=MR-1: 1000V	31a	BYD 33 M	31a
MR-1 Z	Si-Di	=MR-1: 200V	31a	BYD 33 M	31a
MR 1-1000	Si-Di	Gl, 1000V, 1A	31a	BYD 33 M	31a
MR 1-1200	Si-Di	Gl, 1200V, 1A	31a	BY 228	31a
MR 1-1400	Si-Di	Gl, 1400V, 1A	31a	BY 228	31a
MR 1-1600	Si-Di	Gl, 1600V, 1A	31a	BY 228	31a
MR 05	Si-Di	Gl, S, 50V, 0,1A, <1µs	31a	BA 159	31a
MR 11	Si-Di	=MR 05: 100V	31a	BA 159	31a
MR 21	Si-Di	=MR 05: 250V	31a	BA 159	31a
MR 31	Si-Di	=MR 05: 350V	31a	BA 159	31a
MR 41	Si-Di	=MR 05: 450V	31a	BA 159	31a
MR 251	Si-Di	=BY 251	31a	BY 255	31a
MR 500	Si-Di	Gl, Uni, 50V, 3A	31a	BY 255	31a
MR 501	Si-Di	=MR 500: 100V	31a	BY 255	31a
MR 502	Si-Di	=MR 500: 200V	31a	BY 255	31a
MR 504	Si-Di	=MR 500: 400V	31a	BY 255	31a
MR 506	Si-Di	=MR 500: 600V	31a	BY 255	31a
MR 508	Si-Di	=MR 500: 800V	31a	BY 255	31a
MR 510	Si-Di	=MR 500: 1000V	31a	BY 255	31a
MR 750	Si-Di	Gl, Uni, 50V, 6A	31a	BY 500/800	31a 7
MR 751	Si-Di	=MR 750: 100V	31a	BY 500/800	31a 7
MR 752	Si-Di	=MR 750: 200V	31a	BY 500/800	31a 7
MR 754	Si-Di	=MR 750: 400V	31a	BY 500/800	31a 7
MR 756	Si-Di	=MR 750: 600V	31a	BY 500/800	31a 7
MR 758	Si-Di	=MR 750: 800V	31a	BY 500/800	31a 7
MR 760	Si-Di	=MR 750: 1000V	31a	BY 329/1200	17k 6
MR 810	Si-Di	Gl, S, 50V, 1A, <750ns	31a	BYD 33 M	31a
MR 811	Si-Di	=MR 810: 100V	31a	BYD 33 M	31a
MR 812	Si-Di	=MR 810: 200V	31a	BYD 33 M	31a
MR 813	Si-Di	=MR 810: 300V	31a	BYD 33 M	31a
MR 814	Si-Di	=MR 810: 400V	31a	BYD 33 M	31a