

DTA 143 EU(A)		Si-P+R	=DTA 143E... SMD	35a(2mm)	SOT-323	-	
DTA143T(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=4,7kΩ, Rbe=-, 50/50V, 100mA, 0,3W, 250MHz	9c, 41c		AN 1L3Z, RN 2010, UN 4116, 2SA1511,++	
DTA 143 TE		Si-P+R	=DTA 143T... SMD	35a(1,6mm)	SS Mini	-	
DTA 143 TK(A)		Si-P+R	=DTA 143T... SMD	35a(2,9mm)	SOT-23	FN 1L3Z, RN 2410, UN 2116, 2SA1510,++	
DTA 143 TU(A)		Si-P+R	=DTA 143T... SMD	35a(2mm)	SOT-323	-	
DTA143X(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=4,7k, Rbe=10kΩ, 50V, 100mA, 0,3W, 250MHz	9c, 41c		AN 1L3N, KSR 2005, UN 411F, 2SA1654	
DTA 143 XE		Si-P+R	=DTA 143X... SMD	35a(1,6mm)	SS Mini	-	
DTA 143 XK(A)		Si-P+R	=DTA 143X... SMD	35a(2,9mm)	SOT-23	FN 1L3N, KSR 2105, UN 211F, 2SA1653	
DTA 143 XU(A)		Si-P+R	=DTA 143X... SMD	35a(2mm)	SOT-323	-	
DTA143Z(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=4,7k, Rbe=47kΩ, 50V, 100mA, 0,3W, 250MHz	9c, 41c		RN 2006, 2SA1591, 2SA1616	
DTA 143 ZE		Si-P+R	=DTA 143Z... SMD	35a(1,6mm)	SS Mini	-	
DTA 143 ZK(A)		Si-P+R	=DTA 143Z... SMD	35a(2,9mm)	SOT-23	RN 2406, 2SA1597	
DTA 143 ZU(A)		Si-P+R	=DTA 143Z... SMD	35a(2mm)	SOT-323	-	
DTA144E(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=Rbe=47kΩ, 50V, 30/100mA, 0,3W, 250MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c DTA...(...): 100mA Version Serie/Series	9c, 41c	(BC 556) <sup>18</sup>	7a AN 1L4M, RN 2004, UN 4113, 2SA1345,++	
DTA 144 EE		Si-P+R	=DTA 144E... SMD	35a(1,6mm)	SS Mini	-	
DTA 144 EK(A)		Si-P+R	=DTA 144E... SMD	35a(2,9mm)	SOT-23	FN 1L4M, RN 2404, UN 2113, 2SA1341,++	
DTA 144 EU(A)		Si-P+R	=DTA 144E... SMD	35a(2mm)	SOT-323	2SA1676	
DTA144G(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=-, Rbe=47kΩ, 50/50V, 100mA, 0,3W, 250MHz	9c, 41c	(BC 556) <sup>15</sup>	7a 2SA1572	
DTA 144 GE		Si-P+R	=DTA 144G... SMD	35a(1,6mm)	SS Mini	-	
DTA 144 GK(A)		Si-P+R	=DTA 144G... SMD	35a(2,9mm)	SOT-23	2SA1571	
DTA 144 GU(A)		Si-P+R	=DTA 144G... SMD	35a(2mm)	SOT-323	-	
DTA144T(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=47kΩ, Rbe=-, 50/50V, 100mA, 0,3W, 250MHz	9c, 41c	(BC 556) <sup>18</sup>	7a AN 1L4Z, KSR 2012, UN 4110, 2SA1509	
DTA 144 TE		Si-P+R	=DTA 144T... SMD	35a(1,6mm)	SS Mini	-	
DTA 144 TK(A)		Si-P+R	=DTA 144T... SMD	35a(2,9mm)	SOT-23	FN 1L4Z, KSR 2112, UN 2210, 2SA1508	
DTA 144 TU(A)		Si-P+R	=DTA 144T... SMD	35a(2mm)	SOT-323	-	
DTA124V(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=47k, Rbe=10kΩ, 50V, 30/100mA, 0,3W, 250MHz	9c, 41c	(BC 556) <sup>18</sup>	7a UN 411D	
DTA 144 VE		Si-P+R	=DTA 144V... SMD	35a(1,6mm)	SS Mini	-	
DTA 144 VK(A)		Si-P+R	=DTA 144V... SMD	35a(2,9mm)	SOT-23	UN 211D	
DTA 144 VU(A)		Si-P+R	=DTA 144V... SMD	35a(2mm)	SOT-323	-	
DTA144W(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=47k, Rbe=22kΩ, 50V, 30/100mA, 0,3W, 250MHz	9c, 41c	(BC 556) <sup>18</sup>	7a AN 1L4L, RN 2009, UN 411E, 2SA1347,++	
DTA 144 WE		Si-P+R	=DTA 144W... SMD	35a(1,6mm)	SS Mini	-	
DTA 144 WK(A)		Si-P+R	=DTA 144W... SMD	35a(2,9mm)	SOT-23	FN 1L4L, RN 2409, UN 211E, 2SA1343,++	
DTA 144 WU(A)		Si-P+R	=DTA 144W... SMD	35a(2mm)	SOT-323	-	
<b>DTB</b>							
DTB 3 B...G	Say	Triac	100...600V, 3A=(Tc=71°), Igt/Ih<30/<25mA B=100V, C=200V, E=400V, G=600V	13j	TO-202	TAG 136-..., TAG 137-...	
DTB113E(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=Rbe=1kΩ, 50V, 500mA, 0,6W, 200MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		RN 2221	
DTB 113 EK		Si-P+R	=DTB 113E... SMD	35a(2,9mm)	SOT-23	-	
DTB113Z(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=1kΩ, Rbe=10kΩ, 50V, 500mA, 0,6W, 200MHz	9c, 41c		RN 2226	
DTB 113 ZK		Si-P+R	=DTB 113Z... SMD	35a(2,9mm)	SOT-23	-	
DTB114E(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=Rbe=10kΩ, 50V, 500mA, 0,6W, 200MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		RN 2224, UN 4123, 2SA1522, 2SA1526	
DTB 114 EK		Si-P+R	=DTB 114E... SMD	35a(2,9mm)	SOT-23	UN 2123, 2SA1518	
DTB114G(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=-, Rbe=10kΩ, 50/50V, 500mA, 0,6W, 200MHz	9c, 41c		-	
DTB 114 GK		Si-P+R	=DTB 114G... SMD	35a(2,9mm)	SOT-23	-	
DTB114T(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=10kΩ, Rbe=-, 50/40V, 500mA, 0,6W, 200MHz	9c, 41c		-	
DTB 114 TK		Si-P+R	=DTB 114T... SMD	35a(2,9mm)	SOT-23	-	
DTB122J(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=220Ω, Rbe=4,7kΩ, 50V, 500mA, 0,6W, 250MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		-	
DTB 122 JK		Si-P+R	=DTB 122J... SMD	35a(2,9mm)	SOT-23	-	
DTB123E(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=Rbe=2,2kΩ, 50V, 500mA, 0,6W, 200MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		RN 2222, UN 4121, 2SA1525, 2SA1529	
DTB 123 EK		Si-P+R	=DTB 123E... SMD	35a(2,9mm)	SOT-23	UN 2121, 2SA1521	
DTB123T(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=2,2kΩ, Rbe=-, 50/40V, 500mA, 0,6W, 200MHz	9c, 41c		-	
DTB 123 TK		Si-P+R	=DTB 123T... SMD	35a(2,9mm)	SOT-23	-	
DTB123Y(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=2,2k, Rbe=10kΩ, 50V, 500mA, 0,6W, 200MHz	9c, 41c		RN 2227, UN 4124, 2SA1524, 2SA1528	
DTB 123 YK		Si-P+R	=DTB 123Y... SMD	35a(2,9mm)	SOT-23	UN 2124, 2SA1520	
DTB133H(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=3,3k, Rbe=10kΩ, 50V, 500mA, 0,6W, 200MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		-	
DTB 133 HK		Si-P+R	=DTB 133H... SMD	35a(2,9mm)	SOT-23	-	
DTB143E(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=Rbe=4,7kΩ, 50V, 500mA, 0,6W, 200MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		RN 1223, UN 4122, 2SA1523, 2SA1527	
DTB 143 EK		Si-P+R	=DTB 143E... SMD	35a(2,9mm)	SOT-23	UN 2122, 2SA1519	
DTB143T(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=4,7kΩ, Rbe=-, 50/40V, 500mA, 0,6W, 200MHz	9c, 41c		-	
DTB 143 TK		Si-P+R	=DTB 143T... SMD	35a(2,9mm)	SOT-23	-	
DTB163T(A,F,L,S,V)	Rhm	Si-P+R	S, Rb=6,8kΩ, Rbe=-, 50/40V, 500mA, 0,6W, 200MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c	9c, 41c		-	
DTB 163 TK		Si-P+R	=DTB 163T... SMD	35a(2,9mm)	SOT-23	-	
<b>DTC</b>							
DTC1D3R(A,F,L,S,V)	Rhm	Si-N+R	S, Rb=2,7k, Rbe=1kΩ, 50V, 70/100mA, 0,3W, 250MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c DTC...(...): 100mA Version Serie/Series	9c, 41c		-	
DTC 1 D3RE		Si-N+R	=DTC 1D3R... SMD	35a(1,6mm)	SS Mini	-	
DTC 1 D3RK(A)		Si-N+R	=DTC 1D3R... SMD	35a(2,9mm)	SOT-23	-	
DTC 1 D3RU(A)		Si-N+R	=DTC 1D3R... SMD	35a(2mm)	SOT-323	-	
DTC 8 C...G(-N)	Say	Triac	200...600V, 8A=(Tc=105°), Igt/Ih<50/<50mA C=200V, E=400V, G=600V	17j	TO-220	T 2800-..., T 2850-..., TAG 224-...	
DTC 10 C-N...G-N	Say	Triac	200...600V, 10A=(Tc=98°), Igt/Ih<50/<50mA C-N=200V, E-N=400V, G-N=600V	17j	TO-220	BTA 22-..., TAG 250-..., TAG 251-...	
DTC 12 C...G(-N)	Say	Triac	200...600V, 12A=(Tc=98°), Igt/Ih<50/<50mA C=200V, E=400V, G=600V	17j	TO-220	BTA23-..., BT138-..., TAG255-..., TAG256-...	
DTC113Z(A,F,L,S,V)	Rhm	Si-N+R	S, Rb=1k, Rbe=10kΩ, 50V, 100mA, 0,3W, 250MHz A,F,L,V(ATR,FTR,FTL,ATV): Fig.9c, S(SPT): Fig.41c DTC...(...): 100mA Version Serie/Series	9c, 41c		AA 1A3Q, UN 4219	
DTC 113 ZE		Si-N+R	=DTC 113Z... SMD	35a(1,6mm)	SS Mini	-	
DTC 113 ZK(A)		Si-N+R	=DTC 113Z... SMD	35a(2,9mm)	SOT-23	FA 1A3Q, UN 2219	
DTC 113 ZU(A)		Si-N+R	=DTC 113Z... SMD	35a(2mm)	SOT-323	-	