

TRANSISTOR NUMBER	PM QLT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE MFR	EUR EQUIV	USA EQUIV	ISS	
OC36	PG	T03	L05	80V	32V	40V	8A	100C	30WH	200K	200P	30MN	1A	AHG	MUB	ASZ16	2N1536	0
OC41	PG	X01	L03	16V	15V	10V	50MA	80C	50MWF	4M	12P	35TP	50MA	RLS	MUB	OC44N	2N2614	0
OC41N	PG	T01	L02	16V	15V	12V	50MA	80C	83MWF	4M	12P	20MN	50MA	RLS	VAL	OC44N	2N2614	0
OC42	PG	X01	L03	16V	15V	10V	50MA	80C	50MWF	7M	12P	70TP	50MA	RLS	MUB	OC44N	2N2614	0
OC42N	PG	T01	L02	16V	15V	12V	50MA	80C	83MWF	5M	12P	40MN	50MA	RLS	VAL	OC44N	2N2614	0
OC43	PG	X01	L03	15V	15V	12V	50MA	80C	80MWF	15M	12P	100TP	50MA	RLS	MUB	OC44N	2N2614	0
OC43N	PG	T01	L02	15V	15V	12V	50MA	80C	83MWF	12M	12P	50MN	50MA	RLS	VAL	OC44N	2N2614	0
OC44	PG	X01	L03	15V	12V	12V	10MA	80C	83MWF	8M	12P	100TP	1MA	RLA	MUB	OC44N	2N2614	0
OC44N	PG	T01	L02	15V	15V	12V	5MA	75C	83MWF	8M	12P	45MN	1MA	RLA	NEM	OC44N	2N2614	0
OC45	PG	X01	L03	15V	15V	12V	10MA	80C	83MWF	4M	12P	50TP	1MA	RLA	MUB	OC44N	2N2614	0
OC45N	PG	T01	L02	15V	15V	12V	5MA	80C	83MWF	4M	12P	25MN	1MA	RLA	VAL	OC44N	2N2614	0
OC46	PG	X01	L03	20V	20V	15V	125MA	80C	83MWF	2M	12P	80TP	3MA	RLA	VAL	OC44N	2N2614	0
OC47	PG	X01	L03	20V	20V	15V	125MA	80C	83MWF	4M	12P	200TP	15MA	RLG	VAL	OC44N	2N2614	0
OC65N	PG	T01	L02	10V	10V	10V	10MA	65C	25MWF	100K	40P	30MN	4MA	ALA	NEM	AC125	2N406	0
OC66N	PG	T01	L02	10V	10V	10V	10MA	65C	25MWF	100K	40P	50MN	2MA	ALA	NEM	AC125	2N406	0
OC70	PG	X01	L03	20V	20V	10V	10MA	80C	125MWF	200K	30P	15MN	5MA	ALG	OBS	AC107	2N406	0
OC70N	PG	T01	L02	30V	10V	10V	10MA	75C	125MWF	200K	40P	20MN	500UA	ALA	NEM	AC125	2N406	0
OC71	PG	X01	L03	20V	20V	10V	10MA	80C	125MWF	300K	30P	30MN	5MA	ALG	OBS	AC107	2N406	0
OC71N	PG	T01	L02	30V	10V	10V	10MA	75C	125MWF	200K	40P	30MN	1MA	ALA	NEM	AC125	2N406	0
OC72	PG	X02	L03	16V	16V	10V	125MA	80C	165MWF	250K	40P	30MN	80MA	AMG	OBS	AC128	2N2706	0
OC72N	PG	T01	L02	32V	16V	10V	125MA	75C	125MWF	200K	40P	45MN	10MA	ALA	NEM	AC125	2N406	0
OC73	PG	X01	L03	32V	30V	20V	10MA	80C	125MWF	300K	30P	25MN	10MA	ALG	OBS	AC125	2N406	0
OC73N	PG	T01	L02	32V	16V	10V	10MA	75C	125MWF	200K	40P	30MN	500UA	ALA	NEM	AC125	2N406	0
OC74	PG	X02	L03	20V	20V	6V	300MA	75C	550MWH	100K	50P	40MN	50MA	AMG	OBS	AC128	2N2706	0
OC74N	PG	T01	L02	20V	10V	6V	300MA	75C	550MWH	100K	50P	60MN	50MA	AMG	NEM	AC128	2N2706	0
OC75	PG	X01	L03	20V	20V	10V	10MA	75C	125MWF	100K	50P	55MN	10MA	ALG	MUB	AC125	2N406	0
OC75N	PG	T01	L02	30V	10V	10V	10MA	75C	125MWF	200K	40P	60MN	3MA	ALA	NEM	AC125	2N406	0
OC76	PG	X02	L03	32V	32V	10V	125MA	75C	125MWF	100K	40P	30MN	80MA	AMG	OBS	AC128	2N2706	0
OC76N	PG	T01	L02	32V	16V	10V	125MA	75C	125MWF	200K	40P	45MN	10MA	ALG	NEM	AC125	2N406	0
OC77	PG	X02	L03	60V	60V	10V	250MA	80C	125MWF	250K	40P	45MN	10MA	AMH	OBS	OC77N	2N1176B	0
OC77M	PG	T05	L04	60V	60V	10V	125MA	80C	180MWF	200K	40P	25MN	125MA	AMH	OBS	OC77N	2N1176B	0
OC77N	PG	T01	L02	60V	45V	10V	125MA	80C	180MWF	200K	50P	25MN	125MA	ALS	NEM	OC77N	2N1176B	0
OC78	PG	X02	L03	15V	10V	6V	70MA	80C	500MWH	200K	40P	15MN	70MA	AMG	OBS	AC128	2N2706	0
OC78D	PG	X02	L03	12V	9V	6V	10MA	80C	125MWF	200K	40P	30MN	3MA	ALG	OBS	AC125	2N406	0
OC78N	PG	T01	L02	20V	12V	10V	200MA	90C	200MWF	500K	50P	25MN	2MA	ALA	NEM	AC125	2N406	0
OC79	PG	X02	L03	26V	13V	6V	300MA	80C	550MWH	200K	50P	50MN	5MA	AMG	OBS	AC128	2N2706	0
OC79N	PG	T01	L02	20V	12V	12V	200MA	90C	200MWF	500K	60P	25MN	125MA	ALA	NEM	AC125	2N406	0
OC81	PG	X02	L03	32V	10V	3V	200MA	90C	600MWH	1M	70P	50MN	100MA	AMG	OBS	AC128	2N2706	0
OC81D	PG	X02	L03	16V	16V	3V	10MA	80C	150MWF	200K	40P	20MN	5MA	ALG	OBS	AC125	2N406	0
OC81N	PG	T01	L02	32V	18V	10V	500MA	85C	200MWF			50MN	50MA	AMG	NEM	AC128	2N2706	0
OC81Z	PG	X02	L03	50V	40V	10V	200MA	90C	600MWH	1M	70P	50MN	100MA	AMH	OBS			0
OC81DM	PG	T01	L02	16V	16V	3V	10MA	80C	125MWF	200K	40P	20MN	5MA	ALG	OBS	AC125	2N406	0
OC82	PG	X02	L03	16V	16V	6V	200MA	80C	600MWH	400K	40P	15MN	3MA	ALG	OBS	AC125	2N406	0
OC82D	PG	X02	L03	16V	16V	6V	10MA	80C	150MWF	200K	40P	30MN	3MA	ALG	OBS	AC125	2N406	0
OC82DM	PG	T01	L02	16V	16V	6V	10MA	80C	170MWF	200K	40P	30MN	3MA	ALG	OBS	AC125	2N406	0
OC83	PG	T01	L02	32V	20V	3V	500MA	100C	600MWH	1M	100P	40MN	300MA	AMG	OBS	AC128	2N2706	0
OC83N	PG	T01	L02	32V	20V	10V	1A	90C	220MWF	400K	80P	40MN	300MA	AMG	NEM	AC128	2N2706	0
OC84	PG	T01	L02	32V	20V	3V	500MA	100C	600MWF	1M	100P	50MN	300MA	AMG	OBS	AC128	2N2706	0
OC84N	PG	T01	L02	32V	20V	10V	1A	90C	220MWF	500K	80P	50MN	300MA	AMG	NEM	AC128	2N2706	0
OC170	PG	T07	L07	20V	20V	1V	10MA	80C	80MWF	60M	5P	150TP	1MA	RLA	OBS	AF124	2N990	0
OC171	PG	T07	L07	20V	20V	1V	10MA	80C	80MWF	60M	5P	150TP	1MA	RLA	OBS	AF124	2N990	0
OC200	PS	X02	L03	30V	25V	20V	100MA	150C	250MWF	450K	60P	15MN	1MA	ALA	MUB	BCY32	2N1475	0
OC201	PS	X02	L03	25V	20V	20V	100MA	150C	250MWF	2M	50P	20MN	1MA	ALA	MUB	BCY32	2N1475	0
OC202	PS	X02	L03	15V	10V	10V	100MA	150C	250MWF	1M	50P	40MN	1MA	ALA	MUB	BCY32	2N1475	0
OC203	PS	X02	L03	60V	50V	30V	100MA	150C	250MWF	300K	50P	10MN	1MA	ALA	MUB	BCY32	2N1475	0
OC204	PS	X02	L03	32V	32V	12V	250MA	150C	300MWF	450K	50P	10MN	150MA	ALA	MUB	BCY32	2N1475	0
OC205	PS	X02	L03	60V	60V	12V	250MA	150C	300MWF	450K	50P	10MN	150MA	ALA	MUB	BCY32	2N1475	0
OC206	PS	X02	L03	32V	32V	12V	250MA	150C	300MWF	850K	50P	16MN	150MA	ALA	MUB	BCY32	2N1475	0
OC303	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	300K		26TP	1MA	ALG	M1S	AC125	2N406	0
OC304	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	400K		65TP	1MA	ALG	M1S	AC125	2N406	0
OC304/1	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	300K		40TP	1MA	ALG	M1S	AC125	2N406	0
OC304/2	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	400K		65TP	1MA	ALG	M1S	AC125	2N406	0
OC304/3	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	500K		100TP	1MA	ALG	M1S	AC125	2N406	0
OC305	PG	T01A	L02	32V	8V	10V	50MA	75C	110MWF	600K		200TP	1MA	ALG	M1S	AC125	2N406	0
OC305/1	PG	T01A	L02	32V	8V	10V	50MA	75C	110MWF	600K		150TP	1MA	ALG	M1S	AC125	2N406	0
OC305/2	PG	T01A	L02	32V	8V	10V	50MA	75C	110MWF	1M		230TP	1MA	ALG	M1S	AC125	2N406	0
OC306	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	300K		70TP	1MA	ALG	M1S	AC125	2N406	0
OC306/1	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	300K		40TP	1MA	ALG	M1S	AC125	2N406	0
OC306/2	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	400K		65TP	1MA	ALG	M1S	AC125	2N406	0
OC306/3	PG	T01A	L02	32V	15V	10V	50MA	75C	110MWF	500K		100TP	1MA	ALG	M1S	AC125	2N406	0
OC307	PG	T01	L02	32V	18V	10V	250MA	75C	110MWF	200K		40TP	250MA	AMG	M1S	AC128	2N2706	0
OC307/1	PG	T01	L02	32V	18V	10V	250MA	75C	110MWF	200K		30TP	250MA	AMG	M1S	AC128	2N2706	0
OC307/2	PG	T01	L02	32V	18V	10V	250MA	75C	110MWF	200K		40TP	250MA	AMG	M1S	AC128	2N2706	0
OC307/3	PG	T01	L02	32V	18V	10V	250MA	75C	110MWF	200K		70TP	250MA	AMG	M1S	AC128	2N2706	0
OC308	PG	T01	L02	32V	18V	10V	250MA	75C	75MWF	500K		30MN	80MA	AMG	M1S	AC128	2N2706	0