

2 N 5985	Si-N	=2N5983: 100V	16h	(BD 809)	17j	5
2 N 6027	PUT	Ip<5µA, Iv>70µA	7a(KGA)	-		
2 N 6028	PUT	=2N6027: Ip<1µA, Iv>25µA	7a(KGA)	-		
2 N 6029	Si-P	NF/S-L, 100V, 16A, 200W, >1MHz	23a	BD 318	23a	
2 N 6030	Si-P	=2N6029: 120V	23a	MJ 15016	23a	
2 N 6031	Si-P	=2N6029: 140V	23a	MJ 15016	23a	
2 N 6040	Si-P-Darl+Di	NF/S-L, 60V, 8A, 75W, B>1000	17j	BD 902	17j	
2 N 6041	Si-P-Darl+Di	=2N6040: 80V	17j	BD 902	17j	
2 N 6042	Si-P-Darl+Di	=2N6040: 100V	17j	BD 902	17j	
2 N 6043	Si-N-Darl+Di	NF/S-L, 60V, 8A, 75W, B>1000	17j	BD 901	17j	
2 N 6044	Si-N-Darl+Di	=2N6043: 80V	17j	BD 901	17j	
2 N 6045	Si-N-Darl+Di	=2N6043: 100V	17j	BD 901	17j	
2 N 6050	Si-P-Darl+Di	NF/S-L, 60V, 12A, 150W, B>750	23a	BDW 84 C	18j	
2 N 6051	Si-P-Darl+Di	=2N6050: 80V	23a	BDW 84 C	18j	
2 N 6052	Si-P-Darl+Di	=2N6050: 100V	23a	BDW 84 C	18j	
2 N 6053	Si-P-Darl+Di	NF/S-L, 60V, 8A, 100W, B>750	23a	BDW 84 C	18j	
2 N 6054	Si-P-Darl+Di	=2N6053: 80V	23a	BDW 84 C	18j	
2 N 6055	Si-N-Darl+Di	NF/S-L, 60V, 8A, 100W, B>750	23a	BDW 83 C	18j	
2 N 6056	Si-N-Darl+Di	=2N6055: 80V	23a	BDW 83 C	18j	
2 N 6057	Si-N-Darl+Di	NF/S-L, 60V, 12A, 150W, B>750	23a	BDW 83 C	18j	
2 N 6058	Si-N-Darl+Di	26057: 80V	23a	BDW 83 C	18j	
2 N 6059	Si-N-Darl+Di	=2N6057: 100V	23a	BDW 83 C	18j	
2 N 6068	Triac	25V, 4A(Tc=85°), Igt/Ih<30/<30mA	14j	TAG 232-600	17j	4
2 N 6069	Triac	=2N6068: 50V	14j	TAG 232-600	17j	4
2 N 6070	Triac	=2N6068: 100V	14j	TAG 232-600	17j	4
2 N 6071	Triac	=2N6068: 200V	14j	TAG 232-600	17j	4
2 N 6072	Triac	=2N6068: 300V	14j	TAG 232-600	17j	4
2 N 6073	Triac	=2N6068: 400V	14j	TAG 232-600	17j	4
2 N 6074	Triac	=2N6068: 500V	14j	TAG 232-600	17j	4
2 N 6075	Triac	=2N6068: 600V	14j	TAG 232-600	17j	4
2 N 6068...6075 A	Triac	=2N6068...6075: Igt/Ih<10/<15mA	14j	TAG 232-600	17j	4
2 N 6068...6075 B	Triac	=2N6068...6075: Igt/Ih<5/<15mA	14j	(TAG 232-600)	17j	4
2 N 6098	Si-N	NF/S-L, 70V, 10A, 75W, >0,8MHz	17j	BD 809	17j	
2 N 6099	Si-N	=2N6098	17j	BD 809	17j	
2 N 6100	Si-N	=2N6098: 80V	17j	BD 809	17j	
2 N 6101	Si-N	=2N6098: 80V	17j	BD 809	17j	
2 N 6102	Si-N	=2N6098: 45V, 16A	17j	-		
2 N 6103	Si-N	=2N6098: 45V, 16A	17j	-		
2 N 6106	Si-P	NF/S-L, 80V, 7A, 40W, >10MHz	17j	BD 810	17j	
2 N 6107	Si-P	=2N6106	17j	BD 810	17j	
2 N 6108	Si-P	=2N6106: 60V	17j	BD 810	17j	
2 N 6109	Si-P	=2N6106: 60V	17j	BD 810	17j	
2 N 6110	Si-P	=2N6106: 40V	17j	BD 810	17j	
2 N 6111	Si-P	=2N6106: 40V	17j	BD 810	17j	
2 N 6121	Si-N	NF/S-L, 45V, 4A, 40W, >2,5MHz	17j	BD 243 C	17j	
2 N 6122	Si-N	=2N6121: 60V	17j	BD 243 C	17j	
2 N 6123	Si-N	=2N6121: 80V	17j	BD 243 C	17j	
2 N 6124	Si-P	NF/S-L, 45V, 4A, 40W, >2,5W	17j	BD 244 C	17j	
2 N 6125	Si-P	=2N6124: 60V	17j	BD 244 C	17j	
2 N 6126	Si-P	=2N6124: 80V	17j	BD 244 C	17j	
2 N 6178	Si-N	NF/S-L, 100V, 2A, 25W, >50MHz	14m	(BD 139)	14h	5
2 N 6179	Si-N	=2N6178: 75V	14m	(BD 139)	14h	5
2 N 6180	Si-P	NF/S-L, 100V, 2A, 25W, >50MHz	14m	(BD 139)	14h	5
2 N 6181	Si-P	=2N6182: 75V	14m	(BD 140)	14h	5
2 N 6229	Si-P	NF/S-L, 100V, 10A, 150W, >1MHz	23a	BD 318	23a	
2 N 6230	Si-P	=2N6229: 120V	23a	MJ 15016	23a	