

2 N 2078(A)	USA,Mot	Ge-P	=2N2075: 40V	38a	TO-36			2N1980...82, 2N2490...93
2 N 2079(A)	USA,Mot	Ge-P	S P, 80V, 15A, 170W, hFE=35...70	38a	TO-36			2N1982, 2N2492...93
2 N 2080(A)	USA,Mot	Ge-P	=2N2079: 70V	38a	TO-36			2N1981...82, 2N2492...93
2 N 2081(A)	USA,Mot	Ge-P	=2N2079: 50V	38a	TO-36			2N1980...82, 2N2490...93
2 N 2082(A)	USA,Mot	Ge-P	=2N2079: 40V	38a	TO-36			2N1980...82, 2N2490...93
2 N 2083	Gen,Sty	Ge-P	HF, 30V, 10mA, 0,06W, >30MHz	1g	TO-7			AF 124...126, AF 200
2 N 2084	Spe,Sty	Ge-P	HF, 40V, 10mA, 0,125W, >100MHz	5g	TO-33			AF 106, AF 109R, AF 306
2 N 2085	USA	Ge-N	LFS, 33V, 0,5A, 0,15W, 8MHz	2a	TO-5			ASY 28, ASY 73...75
2 N 2086	USA	Si-N	LFS, 120V, 0,5A, 0,6W, >150MHz, hFE>20	2a	TO-5			BC 300, 2N1893(A), 2N2102, 2N2405, ++
2 N 2087	USA	Si-N	=2N2086: hFE=40...120	2a	TO-5			BC 300, 2N1893(A), 2N2102, 2N2405, ++
2 N 2089	Amp	Ge-P	HF, 20V, 10mA, 0,1W, >44MHz	1g	TO-7			AF 124...126, AF 200
2 N 2090	Amp	Ge-P	HF, 20V, 10mA, 0,1W, >44MHz	1g	TO-7			AF 124...126, AF 200
2 N 2091	Amp	Ge-P	HF, 20V, 10mA, 0,1W, >44MHz	1g	TO-7			AF 124...126, AF 200
2 N 2092	Amp	Ge-P	HF, 20V, 10mA, 0,1W, >30MHz	1g	TO-7			AF 124...126, AF 200
2 N 2093	Amp	Ge-P	HF, 25V, 10mA, 0,1W, >30MHz	1g	TO-7			AF 124...126, AF 200
2 N 2094	Spr	Si-N	Uni, 60/40V, 0,6W, >200MHz	2a	TO-5			BFR10, BFX96...97, 2N3722...23, 2SC1385, ++
2 N 2094 A		Si-N	=2N2094: 60/60V	2a	TO-5			BFR10, BFX96...97, 2N3722...23, 2SC1385, ++
2 N 2095	Ssi	Ge-P	HF P, 30V, 0,3A, >500MHz	49m	TO-31			-
2 N 2096	USA,Mot	Ge-P	S, 25V, 0,5A, 0,5W, -/130ns	49m	TO-31			2N1494
2 N 2097	USA,Mot	Ge-P	S, 40V, 0,5A, 0,5W, -/90ns	49m	TO-31			2N1496
2 N 2098	Spr	Ge-P	HF, 30V, 0,3A, 1W, >500MHz	2a	TO-9			-
2 N 2099	USA,Mot	Ge-P	=2N2096: 0,3W	2a	TO-5			2N1495
2 N 2100(A)	USA,Mot	Ge-P	=2N2097: 0,3W	2a	TO-5			2N1495
2 N 2101	USA	Si-N	S P, 60V, 3A, 75W	49m	TO-61			2N3487...92
2 N 2102(A,L,S)	USA, EUR	Si-N	LFS, 120V, 1A, 1W, >120MHz	2a	TO-5	(BC 141)7	2a	BSS 42...43, BSX 47, 2N2405, 2N3019...20++
2 N 2104	old	Si-P	LFS, 50V, 0,6A, 0,8W, 60MHz, hFE=25...80	2a	TO-5			BC 161, BC 303...304, 2N2303, 2SA606, ++
2 N 2105	old	Si-P	=2N2104: hFE=15...40	2a	TO-5			BC 161, BC 303...304, 2N2303, 2SA606, ++
2 N 2106	USA	Si-N	LFS, 60V, 0,5A, 1W, hFE=12...36	2a	TO-5			BC 140...141, BC 300...302, 2N3053, ++
2 N 2107	USA	Si-N	=2N2106: hFE=30...90	2a	TO-5			BC 140...141, BC 300...302, 2N3053, ++
2 N 2108		Si-N	=2N2106: hFE=75...200	2a	TO-5			BC 140...141, BC 300...302, 2N3053, ++
2 N 2109	USA,Whs	Si-N	S P, 50V, 30A, 250W(Tc=60°)	21b	TO-83			2N6324...25
2 N 2110	USA,Whs	Si-N	=2N2109: 100V	21b	TO-83			2N6324...25
2 N 2111	USA,Whs	Si-N	=2N2109: 150V	21b	TO-83			2N6324...25
2 N 2112	USA,Whs	Si-N	=2N2109: 200V	21b	TO-83			2N6324...25
2 N 2113	USA,Whs	Si-N	=2N2109: 250V	21b	TO-83			2N6324...25
2 N 2114	USA,Whs	Si-N	=2N2109: 300V	21b	TO-83			2N6324...25
2 N 2115	USA,Whs	Si-N	=2N2109: 350V	21b	TO-83			2N6324...25
2 N 2116	USA,Whs	Si-N	S P, 50V, 30A, 250W(Tc=60°)	21b	TO-83			2N6324...25
2 N 2117	USA,Whs	Si-N	=2N2116: 100V	21b	TO-83			2N6324...25
2 N 2118	USA,Whs	Si-N	=2N2116: 150V	21b	TO-83			2N6324...25
2 N 2119	USA,Whs	Si-N	=2N2116: 200V	21b	TO-83			2N6324...25
2 N 2120	USA,Whs	Si-N	=2N2116: 250V	21b	TO-83			2N6324...25
2 N 2121	USA,Whs	Si-N	=2N2116: 300V	21b	TO-83			2N6324...25
2 N 2122	USA,Whs	Si-N	=2N2116: 350V	21b	TO-83			2N6324...25
2 N 2123	USA,Whs	Si-N	S P, 50V, 30A, 250W(Tc=60°)	21b	TO-83			2N6324...25
2 N 2124	USA,Whs	Si-N	=2N2123: 100V	21b	TO-83			2N6324...25
2 N 2125	USA,Whs	Si-N	=2N2123: 150V	21b	TO-83			2N6324...25
2 N 2126	USA,Whs	Si-N	=2N2123: 200V	21b	TO-83			2N6324...25
2 N 2127	USA,Whs	Si-N	=2N2123: 250V	21b	TO-83			2N6324...25
2 N 2128	USA,Whs	Si-N	=2N2123: 300V	21b	TO-83			2N6324...25
2 N 2129	USA,Whs	Si-N	=2N2123: 350V	21b	TO-83			2N6324...25
2 N 2130	USA,Whs	Si-N	S P, 50V, 30A, 250W(Tc=60°)	21b	TO-83			2N6324...25
2 N 2131	USA,Whs	Si-N	=2N2130: 100V	21b	TO-83			2N6324...25
2 N 2132	USA,Whs	Si-N	=2N2130: 150V	21b	TO-83			2N6324...25
2 N 2133	USA,Whs	Si-N	=2N2130: 200V	21b	TO-83			2N6324...25
2 N 2134	USA,Whs	Si-N	=2N2130: 250V	21b	TO-83			2N6324...25
2 N 2135	USA,Whs	Si-N	=2N2130: 300V	21b	TO-83			2N6324...25
2 N 2136	USA,Whs	Si-N	=2N2130: 350V	21b	TO-83			2N6324...25
2 N 2137(A)	USA,Mot	Ge-P	LFS P, 30V, 3A, 70W, hFE>30	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1529...48, ++
2 N 2138(A)	USA,Mot	Ge-P	=2N2137: 45V	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1545...48, ++
2 N 2139(A)	USA,Mot	Ge-P	=2N2137: 60V	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1545...48, ++
2 N 2140(A)	USA,Mot	Ge-P	=2N2137: 75V	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1546...48, ++
2 N 2141(A)	USA,Mot	Ge-P	=2N2137: 90V	23a	TO-3	AL 102	23a	AL 102...103, AUY 28, 2N1547...48, ++
2 N 2142(A)	USA,Mot	Ge-P	LFS P, 30V, 3A, 70W, hFE>50	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1529...48, ++
2 N 2143(A)	USA,Mot	Ge-P	=2N2142: 45V	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1545...48, ++
2 N 2144(A)	USA,Mot	Ge-P	=2N2142: 60V	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1545...48, ++
2 N 2145(A)	USA,Mot	Ge-P	=2N2142: 75V	23a	TO-3	AL 102	23a	AL 102...103, AUY 19...20, 2N1546...48, ++
2 N 2146(A)	USA,Mot	Ge-P	=2N2142: 90V	23a	TO-3	AL 102	23a	AL 102...103, AUY 28, 2N1547...48, ++
2 N 2147	USA,Rca	Ge-P	LF P, 75V, 5A, 12,5W(Tc=81°)	23a	TO-3	AL 102	23a	AL 102...103, AUY 22, 2N3617...18, ++
2 N 2148	USA,Rca	Ge-P	=2N2147: 60V	23a	TO-3	AL 102	23a	AL 102...103, AUY 22, 2N3617...18, ++
2 N 2149	Nec	Si-N	100V					-
2 N 2150	USA,Tix	Si-N	S P, 125V, 2A, 30W(Tc=100°), hFE=20...60	=49m	TO-111a			2N5284...85
2 N 2151	USA,Tix	Si-N	=2N2150: hFE=40...120	=49m	TO-111a			2N5284...85
2 N 2152(A)	USA,Mot	Ge-P	LFS P, 45V, 30A, 170W, hFE=50...100	38a	TO-36			-
2 N 2153(A)	USA,Mot	Ge-P	=2N2152: 60V	38a	TO-36			-
2 N 2154(A)	USA,Mot	Ge-P	=2N2152: 75V	38a	TO-36			-
2 N 2155(A)	USA,Mot	Ge-P	=2N2152: 90V	38a	TO-36			-
2 N 2156(A)	USA,Mot	Ge-P	LFS P, 45V, 30A, 170W, hFE=80...160	38a	TO-36			-
2 N 2157(A)	USA,Mot	Ge-P	=2N2156: 60V	38a	TO-36			-
2 N 2158(A)	USA,Mot	Ge-P	=2N2156: 75V	38a	TO-36			-
2 N 2159(A)	USA,Mot	Ge-P	=2N2156: 90V	38a	TO-36			-
2 N 2160	Gen, Ssc, Tix	UJT-P	=2N1671A	5e,2f	TO-33, TO-5			-
2 N 2161	Gen	Si-N	LFS, 55V, 0,05A, 0,2W, <350/700ns	2a	TO-5			BC 167, BC 182, BC 237, BC 547, ++
2 N 2162	USA	Si-P	Chopper, 30/-/30V, 0,15W	2a	TO-5			2N2946
2 N 2163	USA	Si-P	Chopper, 15/-/15V, 0,15W	2a	TO-5			2N2946
2 N 2164	USA	Si-P	Chopper, 12/-/12V, 0,15W	2a	TO-5			2N2946
2 N 2165	USA	Si-P	Chopper, 30/-/30V, 0,15W	2a	TO-5			2N2946
2 N 2166	USA	Si-P	Chopper, 15/-/15V, 0,15W	2a	TO-5			2N2946
2 N 2167	USA	Si-P	Chopper, 12/-/12V, 0,15W	2a	TO-5			2N2946
2 N 2168	USA	Ge-P	S, 20V, 0,1A, 0,06W, 450MHz	2a	TO-9			(2N2635, 2N2955...57)
2 N 2169	USA	Ge-P	S, 15V, 0,1A, 0,06W, 450MHz	2a	TO-9			(2N705, 2N964(A), 2N2635, 2N2955...57)
2 N 2170	USA	Ge-P	S, 15V, 0,1A, 0,06W, 350MHz	2a	TO-9			(2N705, 2N964(A), 2N2635, 2N2955...57)
2 N 2171	USA,Mot	Ge-P	LFS, 50V, 0,4A, 0,225W, 7,5MHz	2a	TO-5			ASY 77, 2N1189...90