

| | | | | | | | | |
|-----------------|---------------|-------|--|-------|-------------|-----------|-----|---|
| 2 N 2078(A) | USA,Mot | Ge-P | =2N2075: 40V | 38a | TO-36 | | | 2N1980...82, 2N2490...93 |
| 2 N 2079(A) | USA,Mot | Ge-P | S P, 80V, 15A, 170W, hFE=35...70 | 38a | TO-36 | | | 2N1982, 2N2492...93 |
| 2 N 2080(A) | USA,Mot | Ge-P | =2N2079: 70V | 38a | TO-36 | | | 2N1981...82, 2N2492...93 |
| 2 N 2081(A) | USA,Mot | Ge-P | =2N2079: 50V | 38a | TO-36 | | | 2N1980...82, 2N2490...93 |
| 2 N 2082(A) | USA,Mot | Ge-P | =2N2079: 40V | 38a | TO-36 | | | 2N1980...82, 2N2490...93 |
| 2 N 2083 | Gen,Sty | Ge-P | HF, 30V, 10mA, 0,06W, >30MHz | 1g | TO-7 | | | AF 124...126, AF 200 |
| 2 N 2084 | Spe,Sty | Ge-P | HF, 40V, 10mA, 0,125W, >100MHz | 5g | TO-33 | | | AF 106, AF 109R, AF 306 |
| 2 N 2085 | USA | Ge-N | LFS, 33V, 0,5A, 0,15W, 8MHz | 2a | TO-5 | | | ASY 28, ASY 73...75 |
| 2 N 2086 | USA | Si-N | LFS, 120V, 0,5A, 0,6W, >150MHz, hFE>20 | 2a | TO-5 | | | BC 300, 2N1893(A), 2N2102, 2N2405, ++ |
| 2 N 2087 | USA | Si-N | =2N2086: hFE=40...120 | 2a | TO-5 | | | BC 300, 2N1893(A), 2N2102, 2N2405, ++ |
| 2 N 2089 | Amp | Ge-P | HF, 20V, 10mA, 0,1W, >44MHz | 1g | TO-7 | | | AF 124...126, AF 200 |
| 2 N 2090 | Amp | Ge-P | HF, 20V, 10mA, 0,1W, >44MHz | 1g | TO-7 | | | AF 124...126, AF 200 |
| 2 N 2091 | Amp | Ge-P | HF, 20V, 10mA, 0,1W, >44MHz | 1g | TO-7 | | | AF 124...126, AF 200 |
| 2 N 2092 | Amp | Ge-P | HF, 20V, 10mA, 0,1W, >30MHz | 1g | TO-7 | | | AF 124...126, AF 200 |
| 2 N 2093 | Amp | Ge-P | HF, 25V, 10mA, 0,1W, >30MHz | 1g | TO-7 | | | AF 124...126, AF 200 |
| 2 N 2094 | Spr | Si-N | Uni, 60/40V, 0,6W, >200MHz | 2a | TO-5 | | | BFR10, BFX96...97, 2N3722...23, 2SC1385, ++ |
| 2 N 2094 A | | Si-N | =2N2094: 60/60V | 2a | TO-5 | | | BFR10, BFX96...97, 2N3722...23, 2SC1385, ++ |
| 2 N 2095 | Ssi | Ge-P | HF P, 30V, 0,3A, >500MHz | 49m | TO-31 | | | - |
| 2 N 2096 | USA,Mot | Ge-P | S, 25V, 0,5A, 0,5W, -/130ns | 49m | TO-31 | | | 2N1494 |
| 2 N 2097 | USA,Mot | Ge-P | S, 40V, 0,5A, 0,5W, -/90ns | 49m | TO-31 | | | 2N1496 |
| 2 N 2098 | Spr | Ge-P | HF, 30V, 0,3A, 1W, >500MHz | 2a | TO-9 | | | - |
| 2 N 2099 | USA,Mot | Ge-P | =2N2096: 0,3W | 2a | TO-5 | | | 2N1495 |
| 2 N 2100(A) | USA,Mot | Ge-P | =2N2097: 0,3W | 2a | TO-5 | | | 2N1495 |
| 2 N 2101 | USA | Si-N | S P, 60V, 3A, 75W | 49m | TO-61 | | | 2N3487...92 |
| 2 N 2102(A,L,S) | USA, EUR | Si-N | LFS, 120V, 1A, 1W, >120MHz | 2a | TO-5 | (BC 141)7 | 2a | BSS 42...43, BSX 47, 2N2405, 2N3019...20++ |
| 2 N 2104 | old | Si-P | LFS, 50V, 0,6A, 0,8W, 60MHz, hFE=25...80 | 2a | TO-5 | | | BC 161, BC 303...304, 2N2303, 2SA606, ++ |
| 2 N 2105 | old | Si-P | =2N2104: hFE=15...40 | 2a | TO-5 | | | BC 161, BC 303...304, 2N2303, 2SA606, ++ |
| 2 N 2106 | USA | Si-N | LFS, 60V, 0,5A, 1W, hFE=12...36 | 2a | TO-5 | | | BC 140...141, BC 300...302, 2N3053, ++ |
| 2 N 2107 | USA | Si-N | =2N2106: hFE=30...90 | 2a | TO-5 | | | BC 140...141, BC 300...302, 2N3053, ++ |
| 2 N 2108 | | Si-N | =2N2106: hFE=75...200 | 2a | TO-5 | | | BC 140...141, BC 300...302, 2N3053, ++ |
| 2 N 2109 | USA,Whs | Si-N | S P, 50V, 30A, 250W(Tc=60°) | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2110 | USA,Whs | Si-N | =2N2109: 100V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2111 | USA,Whs | Si-N | =2N2109: 150V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2112 | USA,Whs | Si-N | =2N2109: 200V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2113 | USA,Whs | Si-N | =2N2109: 250V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2114 | USA,Whs | Si-N | =2N2109: 300V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2115 | USA,Whs | Si-N | =2N2109: 350V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2116 | USA,Whs | Si-N | S P, 50V, 30A, 250W(Tc=60°) | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2117 | USA,Whs | Si-N | =2N2116: 100V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2118 | USA,Whs | Si-N | =2N2116: 150V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2119 | USA,Whs | Si-N | =2N2116: 200V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2120 | USA,Whs | Si-N | =2N2116: 250V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2121 | USA,Whs | Si-N | =2N2116: 300V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2122 | USA,Whs | Si-N | =2N2116: 350V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2123 | USA,Whs | Si-N | S P, 50V, 30A, 250W(Tc=60°) | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2124 | USA,Whs | Si-N | =2N2123: 100V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2125 | USA,Whs | Si-N | =2N2123: 150V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2126 | USA,Whs | Si-N | =2N2123: 200V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2127 | USA,Whs | Si-N | =2N2123: 250V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2128 | USA,Whs | Si-N | =2N2123: 300V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2129 | USA,Whs | Si-N | =2N2123: 350V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2130 | USA,Whs | Si-N | S P, 50V, 30A, 250W(Tc=60°) | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2131 | USA,Whs | Si-N | =2N2130: 100V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2132 | USA,Whs | Si-N | =2N2130: 150V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2133 | USA,Whs | Si-N | =2N2130: 200V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2134 | USA,Whs | Si-N | =2N2130: 250V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2135 | USA,Whs | Si-N | =2N2130: 300V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2136 | USA,Whs | Si-N | =2N2130: 350V | 21b | TO-83 | | | 2N6324...25 |
| 2 N 2137(A) | USA,Mot | Ge-P | LFS P, 30V, 3A, 70W, hFE>30 | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1529...48, ++ |
| 2 N 2138(A) | USA,Mot | Ge-P | =2N2137: 45V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1545...48, ++ |
| 2 N 2139(A) | USA,Mot | Ge-P | =2N2137: 60V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1545...48, ++ |
| 2 N 2140(A) | USA,Mot | Ge-P | =2N2137: 75V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1546...48, ++ |
| 2 N 2141(A) | USA,Mot | Ge-P | =2N2137: 90V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 28, 2N1547...48, ++ |
| 2 N 2142(A) | USA,Mot | Ge-P | LFS P, 30V, 3A, 70W, hFE>50 | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1529...48, ++ |
| 2 N 2143(A) | USA,Mot | Ge-P | =2N2142: 45V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1545...48, ++ |
| 2 N 2144(A) | USA,Mot | Ge-P | =2N2142: 60V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1545...48, ++ |
| 2 N 2145(A) | USA,Mot | Ge-P | =2N2142: 75V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 19...20, 2N1546...48, ++ |
| 2 N 2146(A) | USA,Mot | Ge-P | =2N2142: 90V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 28, 2N1547...48, ++ |
| 2 N 2147 | USA,Rca | Ge-P | LF P, 75V, 5A, 12,5W(Tc=81°) | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 22, 2N3617...18, ++ |
| 2 N 2148 | USA,Rca | Ge-P | =2N2147: 60V | 23a | TO-3 | AL 102 | 23a | AL 102...103, AUY 22, 2N3617...18, ++ |
| 2 N 2149 | Nec | Si-N | 100V | | | | | - |
| 2 N 2150 | USA,Tix | Si-N | S P, 125V, 2A, 30W(Tc=100°), hFE=20...60 | =49m | TO-111a | | | 2N5284...85 |
| 2 N 2151 | USA,Tix | Si-N | =2N2150: hFE=40...120 | =49m | TO-111a | | | 2N5284...85 |
| 2 N 2152(A) | USA,Mot | Ge-P | LFS P, 45V, 30A, 170W, hFE=50...100 | 38a | TO-36 | | | - |
| 2 N 2153(A) | USA,Mot | Ge-P | =2N2152: 60V | 38a | TO-36 | | | - |
| 2 N 2154(A) | USA,Mot | Ge-P | =2N2152: 75V | 38a | TO-36 | | | - |
| 2 N 2155(A) | USA,Mot | Ge-P | =2N2152: 90V | 38a | TO-36 | | | - |
| 2 N 2156(A) | USA,Mot | Ge-P | LFS P, 45V, 30A, 170W, hFE=80...160 | 38a | TO-36 | | | - |
| 2 N 2157(A) | USA,Mot | Ge-P | =2N2156: 60V | 38a | TO-36 | | | - |
| 2 N 2158(A) | USA,Mot | Ge-P | =2N2156: 75V | 38a | TO-36 | | | - |
| 2 N 2159(A) | USA,Mot | Ge-P | =2N2156: 90V | 38a | TO-36 | | | - |
| 2 N 2160 | Gen, Ssc, Tix | UJT-P | =2N1671A | 5e,2f | TO-33, TO-5 | | | - |
| 2 N 2161 | Gen | Si-N | LFS, 55V, 0,05A, 0,2W, <350/700ns | 2a | TO-5 | | | BC 167, BC 182, BC 237, BC 547, ++ |
| 2 N 2162 | USA | Si-P | Chopper, 30/-/30V, 0,15W | 2a | TO-5 | | | 2N2946 |
| 2 N 2163 | USA | Si-P | Chopper, 15/-/15V, 0,15W | 2a | TO-5 | | | 2N2946 |
| 2 N 2164 | USA | Si-P | Chopper, 12/-/12V, 0,15W | 2a | TO-5 | | | 2N2946 |
| 2 N 2165 | USA | Si-P | Chopper, 30/-/30V, 0,15W | 2a | TO-5 | | | 2N2946 |
| 2 N 2166 | USA | Si-P | Chopper, 15/-/15V, 0,15W | 2a | TO-5 | | | 2N2946 |
| 2 N 2167 | USA | Si-P | Chopper, 12/-/12V, 0,15W | 2a | TO-5 | | | 2N2946 |
| 2 N 2168 | USA | Ge-P | S, 20V, 0,1A, 0,06W, 450MHz | 2a | TO-9 | | | (2N2635, 2N2955...57) |
| 2 N 2169 | USA | Ge-P | S, 15V, 0,1A, 0,06W, 450MHz | 2a | TO-9 | | | (2N705, 2N964(A), 2N2635, 2N2955...57) |
| 2 N 2170 | USA | Ge-P | S, 15V, 0,1A, 0,06W, 350MHz | 2a | TO-9 | | | (2N705, 2N964(A), 2N2635, 2N2955...57) |
| 2 N 2171 | USA,Mot | Ge-P | LFS, 50V, 0,4A, 0,225W, 7,5MHz | 2a | TO-5 | | | ASY 77, 2N1189...90 |