

TYPE NO	CONSTRUCTION	PACKAGE & PINOUT	V <sub>DS</sub>	I <sub>D</sub>	T <sub>J</sub>	P <sub>TOT</sub>	V <sub>ESOFF</sub> or V <sub>ES(TH)</sub>	I <sub>LOSS</sub> or I <sub>D(OH)</sub>	G <sub>FS</sub>	R <sub>DS(ON)</sub>	C <sub>ISS</sub>	C <sub>RSS</sub>	USE	MNF	SUBSTITUTE		
																MAX	MAX
1G2	NJD	T072	Ek	50V	16mA	200C	300mWF	6.5Vmx	16mA	4mSmn		7P5	-	ALG	OBS	BFW61	2N3822
2G2	NJD	T072	Ek	50V	8mA	200C	300mWF	4Vmx	8mA	2mSmn		7P5	-	ALG	OBS	BFW12	2N3822
2N2386	PJD	T039	F	20V	20mA	200C	500mWF	8Vmx	0.9/9mA	1mSmn		50P	-	ALG	TEL	BF320	2N2386A
2N2386A	PJD	T039	F	20V	15mA	200C	500mWF	8Vmx	1/1.5mA	2.2/5mS		18P	-	ALG	TEL	BF320	2N2386A
2N2497	PJD	T039	F	20V	3mA	200C	500mWF	5Vmx	1/3mA	1/2mS		32P	-	ALG	TEL	BF320A	2N3329
2N2497JAN	PJD	T039	F	20V	10mA	200C	500mWF	5Vmx	3mA	1/2mS	1K0	32P	-	RLS	TEL	-	2N2497
2N2498	PJD	T039	F	20V	6mA	200C	500mWF	6Vmx	2/6mA	1.5/3mS		32P	-	ALG	TEL	BF320B	2N3330
2N2498JAN	PJD	T039	F	20V	10mA	200C	500mWF	6Vmx	6mA	1.5/3mS	800R	32P	-	ALG	TEL	-	2N2498
2N2499	PJD	T039	F	20V	15mA	200C	500mWF	8Vmx	5/15mA	2/4mS		32P	-	ALG	TEL	BF320	2N2386A
2N2499A	PJD	T039	F	20V	15mA	200C	500mWF	10Vmx	5/15mA	1.7mStp		32P	-	ALG	TEL	BF320	2N3909
2N2499JAN	PJD	T039	F	20V	25mA	200C	500mWF	8Vmx	15mA	2/4mS	600R	32P	-	RLS	TEL	-	2N2498
2N2500	PJD	T039	F	20V	6mA	200C	500mWF	8Vmx	1/6mA	1/2.2mS		32P	-	ALG	TEL	BF320B	2N3332
2N2500JAN	PJD	T039	F	20V	10mA	200C	500mWF	6Vmx	6mA	1/2.2mS		32P	-	RLS	TEL	-	2N2499
2N2606	PJD	T018	F	30V	500µA	175C	300mWF	1/4V	100/500µA	100µSmn		6P0	-	ALG	INS	BF320A	2N2843
2N2606JAN	PJD	T018	F	30V	500µA	200C	300mWF	4Vmx	500µAmx	110/600µS		6P0	-	ALG	INS	BF320A	2N2606
2N2607	PJD	T018	F	30V	1500µA	175C	300mWF	1/4V	0.3/1.5mA	330µSmn		10P	-	ALG	INS	BF320A	2N2844
2N2607JAN	PJD	T018	F	30V	30V	200C	300mWF	4Vmx	0.33/1mS	0.33/1mS		10P	-	ALG	INS	BF320A	2N2607
2N2608	PJD	T018	F	30V	4500µA	175C	300mWF	1/4V	0.9/4.5mA	1mSmn		17P	-	ALG	SLX	BF320A	2N5460
2N2608CHP	PJD	CHIP	-	30V	10mA	200C	300mWF	1/4V	0.9/4.5mA	1mSmn		17P	-	ALG	SLX	-	2N5460
2N2608JAN	PJD	T018	F	30V	30V	200C	300mWF	4Vmx	4.5mA	1/2.5mS		17P	-	ALG	SLX	BF320B	2N2608
2N2609	PJD	T018	F	30V	10mA	175C	300mWF	1/4V	2/10mA	2.5mSmn		30P	-	ALG	INS	BF320	2N5464
2N2609CHP	PJD	CHIP	-	30V	10mA	200C	300mWF	1/4V	2/10mA	2.5mSmn		30P	-	ALG	SLX	-	2N5464
2N2609JAN	PJD	T018	F	30V	30V	200C	300mWF	4Vmx	10mA	2.5/6.2mS		30P	-	ALG	SLX	BF320B	2N2609
2N2620	NJD	T018	B	50V	200mA	175C	300mWF	4Vmx	1.5/5mA	100µSmn		30P	-	ALG	OBS	BFW12	2N3822
2N2794	PJD	T05	B	20V	5mA	175C	400mWF	1.5/5mA	100µSmn	100µSmn		30P	-	ALG	OBS	BF320A	2N3820
2N2841	PJD	T018	F	30V	2200µA	200C	300mWF	1.7Vmx	125µAmx	60µSmn		6P0	-	RLS	SLX	J177	2N3573
2N2842	PJD	T018	F	30V	2200µA	200C	300mWF	1.7Vmx	325µAmx	180µSmn		10P	-	RLS	SLX	J177	2N3574
2N2843	PJD	T018	F	30V	2200µA	200C	300mWF	1.7Vmx	0.2/1mA	540µSmn		10P	-	RLS	SLX	J177	2N3574
2N2844	PJD	T018	F	30V	2200µA	200C	300mWF	1.7Vmx	0.4/2.2mA	1.4mSmn		30P	-	RLS	SLX	BF320A	2N2606
2N3066	NJD	T018	E	50V	4mA	200C	300mWF	9.5Vmx	0.8/4mA	0.4/1mS		10P	1P5	ALG	SLX	BF800	2N4302
2N3066A	NJD	T018	E	50V	4mA	200C	300mWF	9.5Vmx	0.8/4mA	0.4/1mS		10P	1P5	ALG	SLX	BF800	2N4302
2N3067	NJD	T018	E	50V	4mA	200C	300mWF	4.5Vmx	0.2/1mA	0.3/1mS		10P	1P5	ALG	SLX	BF800	2N3686A
2N3067A	NJD	T018	E	50V	4mA	200C	300mWF	4.5Vmx	0.2/1mA	0.3/1mS		10P	1P5	ALG	SLX	BF800	2N3686A
2N3068	NJD	T018	E	50V	4mA	200C	300mWF	2.2Vmx	250µAmx	0.2/1mS		10P	1P5	ALG	SLX	BF800	2N3687A
2N3068A	NJD	T018	E	50V	4mA	200C	300mWF	2.2Vmx	250µAmx	0.2/1mS		10P	1P5	ALG	SLX	BF800	2N3687A
2N3069	NJD	T018	E	50V	10mA	200C	350mWF	9.5Vmx	2/10mA	1/2.5mS		15P	1P5	ALG	SLX	BFW12	2N3822
2N3069A	NJD	T018	E	50V	10mA	200C	350mWF	9.5Vmx	2/10mA	1/2.5mS		15P	1P5	ALN	SLX	BFW56	2N3685A
2N3070	NJD	T018	E	50V	10mA	200C	350mWF	4.5Vmx	0.5/2.5mA	0.75/2.5mS		15P	1P5	ALG	SLX	BF808	2N3685A
2N3070A	NJD	T018	E	50V	10mA	200C	350mWF	4.5Vmx	0.5/2.5mA	0.75/2.5mS		15P	1P5	ALN	SLX	BF808	2N3685A
2N3071	NJD	T018	E	50V	10mA	200C	350mWF	2.2Vmx	100/600µA	0.5/2.5mS		15P	1P5	ALG	SLX	BF347	2N3687A
2N3084	NJD	T05	B	30V	3mA	200C	400mWF	10Vmx	3mA	0.4/2mS		14P	-	ALG	OBS	BF808	2N3685
2N3085	NJD	T018	B	30V	3mA	200C	400mWF	10Vmx	3mA	0.4/2mS		14P	-	ALG	TEL	BF808	2N3621
2N3086	NJD	T05	B	40V	3mA	200C	400mWF	10Vmx	3mA	0.4/2mS		14P	-	ALG	OBS	BF808	2N3685
2N3087	NJD	T018	B	40V	3mA	200C	400mWF	10Vmx	3mA	0.4/2mS		14P	-	ALG	TEL	BF808	2N3621
2N3088	NJD	T05	B	15V	3mA	200C	400mWF	5Vmx	2mA	0.4/4mS		14P	-	ALG	OBS	BF808	2N4339
2N3088A	NJD	T05	B	15V	3mA	200C	400mWF	5Vmx	2mA	0.4/2mS		14P	-	ALG	OBS	BF808A	2N3821
2N3089	NJD	T018	B	30V	2mA	200C	400mWF	1/5V	0.5/2mA	0.3/2mS		6P0	2P0	ALG	SLX	BF800	2N3687A
2N3089A	NJD	T018	B	30V	2mA	200C	400mWF	1/5V	0.5/2mA	0.3/2mS		6P0	2P0	ALN	SLX	BF200	2N3687A
2N3112	PJD	T018	F	20V	10mA	200C	300mWF	4Vmx	180µAmx	50/120µS		3P5	-	ALG	SLX	-	2N2606
2N3113	PJD	T018	F	20V	1mA	200C	300mWF	4Vmx	180µAmx	50µSmn		2P0	-	ALG	SLX	-	2N3573
2N3277	PJD	T012	Fk	25V	10mA	200C	400mWF	5Vmx	150/500µA	100µSmn		4P5	-	ALG	INS	-	2N2606
2N3278	PJD	T012	Fk	25V	10mA	200C	400mWF	5Vmx	500/900µA	150µSmn		4P5	-	ALG	INS	-	2N2606
2N3328	PJD	T072	Fk	20V	1mA	200C	300mWF	6Vmx	1mA	100µSmn		4P0	-	ALG	SLX	BF320A	2N5265
2N3329	PJD	T072	Fk	20V	15mA	200C	300mWF	5Vmx	1/3mA	1/2mS	1K0	20P	-	ALN	SLX	BF320A	2N5266
2N3329CHP	PJD	CHIP	-	20V	3mA	200C	300mWF	5Vmx	1/3mA	1/2mS	1K0	20P	-	ALG	SLX	-	2N5266
2N3329JAN	PJD	T072	Fk	20V	10mA	200C	300mWF	5Vmx	3mA	1/2mS	1K0	20P	-	ALG	SLX	BF320A	2N3329
2N3330	PJD	T072	Fk	20V	15mA	200C	300mWF	6Vmx	2/6mA	1.5/3mS	800R	20P	-	ALN	SLX	BF320B	2N3378
2N3330CHP	PJD	CHIP	-	20V	6mA	200C	300mWF	6Vmx	2/6mA	1.5/3mS	800R	20P	-	ALG	SLX	-	2N3378
2N3330JAN	PJD	T072	Fk	20V	10mA	200C	300mWF	6Vmx	6mA	1.5/3mS	800R	20P	-	ALG	SLX	BF320B	2N3330
2N3331	PJD	T072	Fk	20V	15mA	200C	300mWF	8Vmx	5/15mA	2/4mS	600R	20P	-	ALN	SLX	BF320C	2N5482
2N3331CHP	PJD	CHIP	-	20V	15mA	200C	300mWF	8Vmx	5/15mA	2/4mS	600R	20P	-	ALG	SLX	-	2N5482
2N3331JAN	PJD	T072	Fk	20V	10mA	200C	300mWF	8Vmx	15mA	2/4mS	600R	20P	-	ALG	SLX	BF320	2N3331
2N3332	PJD	T072	Fk	20V	15mA	200C	300mWF	6Vmx	1/6mA	1/2.2mS		20P	-	ALN	SLX	BF320B	2N2500
2N3332JAN	PJD	T072	Fk	20V	10mA	200C	300mWF	6Vmx	6mA	1/2.2mS	800R	20P	-	ALG	SLX	BF320B	2N3332
2N3333	PJD	T089	-	20V	10mA	200C	400mWF	1.6Vmx	1mA	0.6/1.8mS		30P	-	DUA	TIS	-	2N3332
2N3334	PJD	T089	-	20V	10mA	200C	400mWF	1.6Vmx	1mA	0.6/1.8mS		30P	-	DUA	TIS	-	2N3334
2N3335	PJD	T089	-	20V	10mA	200C	400mWF	1.6Vmx	1mA	0.6/1.8mS		30P	-	DUA	TIS	-	2N3335
2N3336	PJD	T089	-	20V	10mA	200C	400mWF	1.6Vmx	1mA	0.6/1.8mS		30P	-	DUA	TIS	-	2N3336
2N3365	NJD	T018	E	40V	4mA	150C	300mWF	11.5Vmx	0.8/4mA	0.4/2mS		15P	2P5	ALG	SLX	BF808	2N3685A
2N3366	NJD	T018	E	40V	4mA	150C	300mWF	6.5Vmx	0.2/1mA	0.25/1mS		15P	2P5	ALG	SLX	BF800	2N3687A
2N3367	NJD	T018	E	40V	4mA	150C	300mWF	2.2Vmx	250µAmx	0.1/1mS		15P	2P5	ALG	SLX	BF800	2N3687A
2N3368	NJD	T018	E	40V	12mA	150C	300mWF	11.5Vmx	2/12mA	1/4mS		20P	3P0	ALG	SLX	BFW61	2N5458
2N3369	NJD	T018	E	40V	12mA	150C	300mWF	6.5Vmx	2.5mA	0.6/2.5mS		20P	3P0	ALG	SLX	BF347	2N3821
2N3370	NJD	T018	E	40V	12mA	150C	300mWF	3.2Vmx	100/600µA	0.3/2.5mS		20P	3P0	ALG	SLX	BF800	2N3687A
2N3376	PJD	T072	Fk	30V	50mA	175C	300mWF	1/5V	0.6/6mA	0.8/2.3mS	1K5	10P	-	RLS	SLX	BF320B	2N3376