

2 N 3131	Nsc	Si-N	Min, S, 40V, 0.1A, 0.15W, >250MHz	≈7c	-	-
2 N 3132	Gen,Sty	Ge-P	L.F.S P, 100V, 5A, 90W	23a	TO-3	AL 102...103, 2N1542...43, 2N1547...48, ++
2 N 3133(S)	USA,Mot,Phi	Si-P	H.F.S, 50V, 0.6A, 0.6W, 26/70ns, hFE=40...120	2a	TO-5	2N3468, 2SA717, 2SA742
2 N 3134(S)	USA,Mot,Phi	Si-P	=2N3133: hFE=100...300	2a	TO-5	2N3468, 2SA717, 2SA742
2 N 3135	USA,Mot,Phi	Si-P	=2N3133: 0.4W	2a	TO-18	BSW 24, BSX 36
2 N 3136	USA,Mot,Phi	Si-P	=2N3133: 0.4W, hFE>100	2a	TO-18	BSW 24, BSX 36
2 N 3137	USA,Mot,Tho	Si-N	VHF/UHF A,Drv, 40/20V, 0.15A, PQ=0.6W(250MHz)	2a	TO-5	BFW 16...17, BFS 50, BFR 36, 2SC2852, ++
2 N 3137 T	Tix	Si-N	=2N3137: 0.5A	2a	TO-5	BFS 50, MRF 629, 2N3948, 2SC2852, ++
2 N 3138	Sca,Sem,Ssi	Si-N	S P, 65V, 2A, 20W	49m	TO-62	2N5002, 2N5004, 2N5284...85
2 N 3139	Sca,Sem,Ssi	Si-N	S P, 140V, 2A, 20W	49m	TO-62	-
2 N 3140	Sca,Sem,Ssi	Si-N	S P, 65V, 2A, 20W	49m	TO-62	2N5002, 2N5004, 2N5284...85
2 N 3141	Sca,Sem,Ssi	Si-N	S P, 140V, 2A, 20W	49m	TO-62	-
2 N 3142	Sca,Sem,Ssi	Si-N	S P, 65V, 2A, 20W	49a	TO-61	2N5002, 2N5004, 2N5284...85
2 N 3143		Si-N	S P, 140V, 2A, 20W	49a	TO-61	-
2 N 3144		Si-N	S P, 65V, 2A, 20W	49a	TO-61	2N5002, 2N5004, 2N5284...85
2 N 3145		Si-N	S P, 140V, 2A, 20W	49a	TO-61	-
2 N 3146	Csr,Gpd,Sty	Ge-P	S P, 150V, 15A, 150W	23a	TO-3	-
2 N 3147	Csr,Gpd,Sty	Ge-P	=2N3146: 180V	23a	TO-3	-
2 N 3148	Spr	Ge-P	S, 11V, 0.05A, 0.025W, >25MHz	37d	TO-24	ASZ 21, 2N705, 2N960...967, 2N2955...57
2 N 3149	USA	Si-N	S P, 80/80V, 70A, 300W	49m	=TO-114	2N9309...11
2 N 3150	USA	Si-N	=2N3149: 100/100V	49m	=TO-114	2N9309...11
2 N 3151	USA	Si-N	=2N3149: 150/150V	49m	=TO-114	-
2 N 3152	Sca,Spe,Sty	Si-N	S, 120V, 0.1A, 2.5W(Tc=100°), >200MHz	49a	-	-
2 N 3153	Idi,Tdy	Si-N	Chopper, 15/15/15V, 0.1A, 0.3W, >30MHz	2a	TO-18	-
2 N 3154	Gpd,Stc	Ge-P	S P, 40V, 3A, 38W, hFE=60...180	-	-	-
2 N 3155		Ge-P	=2N3154: 60V	-	-	-
2 N 3156		Ge-P	=2N3154: 80V	-	-	-
2 N 3157		Ge-P	=2N3154: 100V	-	-	-
2 N 3158		Ge-P	=2N3154: hFE=30...75	-	-	-
2 N 3159		Ge-P	=2N3154: 60V, hFE>30	-	-	-
2 N 3160		Ge-P	=2N3154: 80V, hFE>30	-	-	-
2 N 3161		Ge-P	=2N3154: 100V, hFE>30	-	-	-
2 N 3162	Fch,Sty	Si-N	Matched, 45V, 0.3W, hFE=50...200	5	TO-33	-
2 N 3163	Sca,Ssi	Si-P	S P, 40V, 3A, 85W	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3164		Si-P	=2N3163: 60V	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3165		Si-P	=2N3163: 80V	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3166		Si-P	=2N3163: 100V	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3167		Si-P	=2N3163:	-	TO-53	(BD 246, BDV 92, 2SB688, 2SB775...776++) ⁴
2 N 3168		Si-P	=2N3163: 60V	-	TO-53	(BD 246A, BDV 94, 2SB688, 2SB775...776++) ⁴
2 N 3169		Si-P	=2N3163: 80V	-	TO-53	(BD 246B, BDV 94, 2SB688, 2SB775...776++) ⁴
2 N 3170		Si-P	=2N3163: 100V	-	TO-53	(BD 246C, BDV 96, 2SB688, 2SB775...776++) ⁴
2 N 3171	USA	Si-P	=2N3163: 75W	23a	TO-3	BD 246, BDV 92, BDX 92, 2SA980, ++
2 N 3172		Si-P	=2N3163: 60V, 75W	23a	TO-3	BD 246A, BDV 92, BDX 92, 2SA980, ++
2 N 3173		Si-P	=2N3163: 80V, 75W	23a	TO-3	BD 246B, BDV 94, BDX 94, 2SA980, ++
2 N 3174		Si-P	=2N3163: 100V, 75W	23a	TO-3	BD 246C, BDV 96, BDX 96, 2SA980, ++
2 N 3175	Sca,Ssi	Si-P	S P, 40V, 5A, 85W	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3176		Si-P	=2N3175: 60V	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3177		Si-P	=2N3175: 80V	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3178		Si-P	=2N3175: 100V	49m	TO-61	2N5003, 2N5005, 2N5286...87
2 N 3179		Si-P	=2N3175:	-	TO-53	(BD 246, BDV 92, 2SB688, 2SB775...776++) ⁴
2 N 3180		Si-P	=2N3175: 60V	-	TO-53	(BD 246A, BDV 92, 2SB688, 2SB775...776++) ⁴
2 N 3181		Si-P	=2N3175: 80V	-	TO-53	(BD 246B, BDV 94, 2SB688, 2SB775...776++) ⁴
2 N 3182		Si-P	=2N3175: 100V	-	TO-53	(BD 246C, BDV 96, 2SB688, 2SB775...776++) ⁴
2 N 3183	USA	Si-P	=2N3175: 75W	23a	TO-3	BD 246, BDV 92, BDX 92, 2SA980, ++
2 N 3184		Si-P	=2N3175: 60V, 75W	23a	TO-3	BD 246A, BDV 92, BDX 92, 2SA980, ++
2 N 3185		Si-P	=2N3175: 80V, 75W	23a	TO-3	BD 246B, BDV 94, BDX 94, 2SA980, ++
2 N 3186		Si-P	=2N3175: 100V, 75W	23a	TO-3	BD 246C, BDV 96, BDX 96, 2SA980, ++
2 N 3187	Sca,Ssi	Si-P	S P, 40V, 5A, 85W	49m	TO-61	2N5003, 2N5005, 2B5286...87
2 N 3188		Si-P	=2N3187: 60V	49m	TO-61	2N5003, 2N5005, 2B5286...87
2 N 3189		Si-P	=2N3187: 80V	49m	TO-61	2N5003, 2N5005, 2B5286...87
2 N 3190		Si-P	=2N3187: 100V	49m	TO-61	2N5003, 2N5005, 2B5286...87
2 N 3191		Si-P	=2N3187:	-	TO-53	(BD 246, BDV 92, 2SB688, 2SB775...776++) ⁴
2 N 3192		Si-P	=2N3187: 60V	-	TO-53	(BD 246A, BDV 92, 2SB688, 2SB775...776++) ⁴
2 N 3193		Si-P	=2N3187: 80V	-	TO-53	(BD 246B, BDV 94, 2SB688, 2SB775...776++) ⁴
2 N 3194		Si-P	=2N3187: 100V	-	TO-53	(BD 246C, BDV 96, 2SB688, 2SB775...776++) ⁴
2 N 3195	USA	Si-P	=2N3187: 75W	23a	TO-3	BD 246, BDV 92, BDX 92, 2SA980, ++
2 N 3196		Si-P	=2N3187: 60V, 75W	23a	TO-3	BD 246A, BDV 92, BDX 92, 2SA980, ++
2 N 3197		Si-P	=2N3187: 80V, 75W	23a	TO-3	BD 246B, BDV 94, BDX 94, 2SA980, ++
2 N 3198		Si-P	=2N3187: 100V, 75W	23a	TO-3	BD 246C, BDV 96, BDX 96, 2SA980, ++
2 N 3199	Ssi,Tra	Si-P	S P, 40V, 3A, 40W	49m	TO-59	2N5003, 2N5005, 2N5286...87
2 N 3200		Si-P	=2N3199: 60V	49m	TO-59	2N5003, 2N5005, 2N5286...87
2 N 3201		Si-P	=2N3199: 80V	49m	TO-59	2N5003, 2N5005, 2N5286...87
2 N 3202	Ssi,Tra,++	Si-P	=2N3199: 8.7W(Tc=25°)	2a	TO-5	BSS 46, BUY 90, 2N6190...93
2 N 3203		Si-P	=2N3199: 60V, 8.7W(Tc=25°)	2a	TO-5	BSS 46, BUY 90, 2N6190...93
2 N 3204		Si-P	=2N3199: 80V, 8.7W(Tc=25°)	2a	TO-5	BSS 46, BUY 90, 2N6190...93
2 N 3205	Sca,Ssi,Tra	Si-P	S P, 40V, 2A, 40W	49m	TO-59	2N5003, 2N5005, 2N5286...87
2 N 3206		Si-P	=2N3205: 60V	49m	TO-59	2N5003, 2N5005, 2N5286...87
2 N 3207		Si-P	=2N3205: 100V	49m	TO-59	2N5003, 2N5005, 2N5286...87
2 N 3208	USA	Si-P	L.F.S, 40V, 2A, 8.7W(Tc=25°)	2a	TO-5	BSS 46, BUY 90, 2N6190...93
2 N 3209	USA,Sgs,Tix	Si-P	S, 20V, 0.2A, 0.36W, <60/90ns	2a	TO-18	BSW 24, BSX 36, 2N4125...26
2 N 3210	USA,Mot	Si-N	S, 40V, 0.5A, 0.36W, <40/40ns	2a	TO-18	BSS 10, BSX 26, BSX 39, 2N3261
2 N 3211	USA,Mot	Si-N	S, 40V, 0.5A, 0.36W, >350MHz	2a	TO-18	BSS 10, BSX 26, BSX 39, 2N3261
2 N 3212	Del,Gpd,Stc	Ge-P	L.F.S P, 100V, 5A, 14W	43m	TO-37	-
2 N 3213		Ge-P	=2N3212: 80V	43m	TO-37	-
2 N 3214		Ge-P	=2N3212: 60V	43m	TO-37	-
2 N 3215		Ge-P	=2N3212: 40V	43m	TO-37	-
2 N 3216	Gen,Stc	Ge-P	L.F.S, 20/10/20V, 0.5A, 0.15W, >9MHz	2a	TO-5	(ASY 76...77, 2N1189...90)
2 N 3217	USA	Si-P	Chopper, 15/10/15V, 0.1A, 0.4W	2a	TO-46	2N2944
2 N 3218	USA	Si-P	Chopper, 25/20/25V, 0.1A, 0.4W	2a	TO-46	2N2945
2 N 3219	USA	Si-P	Chopper, 40/35/40V, 0.1A, 0.4W	2a	TO-46	2N2946
2 N 3220	USA	Si-N	S P, 100V, 2A, >10MHz, hFE=20...60	49a	=TO-111	2N5002, 2N5004, 2N5284...85
2 N 3221		Si-N	=2N3220: hFE=40...120	49a	=TO-111	2N5002, 2N5004, 2N5284...85
2 N 3222		Si-N	=2N3220: 80V	49a	=TO-111	2N5002, 2N5004, 2N5284...85