

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE MFR	EUR EQUIV	USA EQUIV	ISS
BD135/6	NS	T0126	L31	45V	45V	5V	1A	150C	12WC	100M		40/100	150MA	AMG TFK	BD189	2N4923	2
BD135/10	NS	T0126	L31	45V	45V	5V	1A	150C	12WC	100M		63/160	150MA	AMG TFK	BD189	2N4923	2
BD135/16	NS	T0126	L31	45V	45V	5V	1A	150C	12WC	100M		100MN	150MA	AMG TFK	BD189	2N4923	2
BD136	PS	T0126	L31	45V	45V	5V	1A	150C	12WC	50M		40/250	150MA	AMG MUB	BD140	2N4920	0
BD136G	PS	X17	L35	45V	45V	5V	1A	150C	12.5WC			40/250	150MA	AMG GEB	BD520	2N6556	2
BD136/6	PS	T0126	L31	45V	45V	5V	1A	150C	12WC	50M		40/100	150MA	AMG TFK	BD562	2N4920	2
BD136/10	PS	T0126	L31	45V	45V	5V	1A	150C	12WC	50M		63/160	150MA	AMG TFK	BD189	2N4923	2
BD136/16	PS	T0126	L31	45V	45V	5V	1A	150C	12WC	50M		100MN	150MA	AMG TFK	BD189	2N4923	2
BD137	NS	T0126	L31	60V	60V	5V	1A	150C	12WC	50M		40/160	150MA	AMG MUB	BD169	2N4923	0
BD137G	NS	X17	L35	60V	60V	5V	1A	150C	12.5WC	80M		40/160	150MA	AMH GEB	BD519	2N6553	2
BD137/6	NS	T0126	L31	60V	60V	5V	1A	150C	12WC	50M		40/100	150MA	AMG TFK	BD189	2N4923	2
BD137/10	NS	T0126	L31	60V	60V	5V	1A	150C	12WC	50M		63/160	150MA	AMH TFK	BD189	2N4923	2
BD138	PS	T0126	L31	60V	60V	5V	1A	150C	12WC	50M		40/180	150MA	AMG MUB	BD140	2N4920	0
BD138G	PS	X17	L35	60V	60V	5V	1A	150C	12.5WC			40/160	150MA	AMG GEB	BD520	2N6556	2
BD138/6	PS	T0126	L31	60V	60V	5V	1A	150C	12WC	50M		40/100	150MA	AMG TFK	BD140	2N4920	2
BD138/10	PS	T0126	L31	60V	60V	5V	1A	150C	12WC	50M		63/160	150MA	AMG TFK	BD140	2N4920	2
BD139	NS	T0126	L31	80V	80V	5V	1A	150C	12WC	50M		40/160	150MA	AMH MUB	BD169	2N4923	0
BD139G	NS	X17	L35	80V	80V	5V	1A	150C	12WC	50M		40/160	150MA	AMH TFK	BD519	2N6553	2
BD139/6	NS	T0126	L31	80V	80V	5V	1A	150C	12WC	50M		40/100	150MA	AMH TFK	BD179	2N4923	2
BD139/10	NS	T0126	L31	80V	80V	5V	1A	150C	12WC	50M		63/160	150MA	AMH TFK	BD179	2N4923	2
BD140	PS	T0126	L31	80V	80V	5V	1A	150C	12WC	50M		40/250	150MA	AMH MUB	BD140	2N4920	0
BD140G	PS	X17	L35	80V	80V	5V	1A	150C	12WC	50M		40/160	150MA	AMH GEB	BD520	2N6556	2
BD140/6	PS	T0126	L31	80V	80V	5V	1A	150C	12WC	50M		40/100	150MA	AMH TFK	BD179	2N5192	2
BD140/10	PS	T0126	L31	80V	80V	5V	1A	150C	12WC	50M		63/160	150MA	AMH TFK	BD179	2N5192	2
BD141	NS	T03	L05	140V	120V	7V	8A	200C	117WC			20/70	2A	AHH ATB	BDY74	2N3442	1
BD142	NS	T03	L05	50V	40V	5V	15A	200C	117WC	700K		13/160	4A	AHG SEU	BDY20	2N3055	0
BD144	NS	T03	L05	400V	400V	5V	250MA	135C	8WC	6M		5MN	5A	AME MUB	BU105	2N5157	1
BD145	NS	T03	L05	60V	60V	5V	5A	175C	15WC	50M		45MN	500MA	RHG MBL	BDY24	2N3448	1
BD148	NS	X03	L05	40V	40V	7V	4A	200C	31WC	1M3		40MN	500MA	AHG SID	BD163		1
BD148B	NS	X03	L05	45V	40V	7V	4A	200C	30WC	1M3		100MN	500MA	AHG SID			1
BD148C	NS	X03	L05	45V	40V	7V	4A	200C	30WC	1M3		63/160	500MA	AHG SID			1
BD148/6	NS	X03	L05	40V	40V	7V	4A	200C	31WC	1M3		40/100	500MA	AHG SID	BD163		1
BD148/10	NS	X03	L05	40V	40V	7V	4A	200C	31WC	1M3		63/160	500MA	AHG SID	BD161		1
BD148/16	NS	X03	L05	40V	40V	7V	4A	200C	31WC	1M3		100MN	500MA	AHG SID	BD161		1
BD149	NS	X03	L05	60V	60V	7V	4A	200C	31WC	1M3		40MN	500MA	AHG SID	BD161		1
BD149B	NS	X03	L05	45V	40V	7V	4A	200C	30WC	1M3		63MN	500MA	AHG SID	BD161		1
BD149/6	NS	X03	L05	60V	60V	7V	4A	200C	31WC	1M3		40/100	500MA	AHG SID	BD161		1
BD149/10	NS	X03	L05	60V	60V	7V	4A	200C	31WC	1M3		63/160	500MA	AHG SID	BD161		1
BD150	NS	T039	L04	220V	220V	6V	500MA	200C	1WF	80M		20MN	80MA	AME SGI		2N3440	0
BD150A	NS	T05	L04	300V	220V	6V	500MA	200C	1WF	80M		20MN	80MA	RME TIB	BUY60	2N3439	1
BD150B	NS	T05	L04	250V	150V	6V	500MA	200C	1WF	80M		20MN	80MA	RME TIB	BUY60	2N3439	1
BD150C	NS	T05	L04	200V	150V	6V	500MA	200C	1WF	80M		20MN	80MA	RME TIB	BUY60	2N3439	1
BD151	PS	T0126	L31	35V	30V	5V	3A	150C	25WC			30/150	1A	AHG MOB	BD238	2N4920	0
BD152	NS	T0126	L31	30V	45V	5V	3A	150C	25WC			30/150	1A	AHG MOB	BD589	2N6123	0
BD153	NS	T0126	L31	70V	60V	5V	3A	150C	25WC			30/150	1A	AHH MOB	BD589	2N6123	0
BD154	NS	T0126	L31	35V	30V	5V	1A	150C	25WC			30/150	1A	AHG MOB	BD589	2N6123	0
BD155	NS	T0126	L31	50V	45V	5V	1A	150C	25WC			30/150	1A	AHG MOB	BD589	2N6123	0
BD156	PS	T0126	L31	70V	60V	5V	3A	150C	25C			30/150	1A	AHH MOB	BD238	2N4920	0
BD157	NS	T0126	L31	275V	250V	5V	500MA	150C	20WC			30/250	50MA	ALE MOB	BD232		0
BD158	NS	T0126	L31	325V	300V	5V	500MA	150C	20WC			30/250	50MA	ALE MOB	BD232		0
BD159	NS	T0126	L31	375V	350V	5V	500MA	150C	20WC			30/250	50MA	ALE MOB	BD232		0
BD160	NS	T03	L05	250V			5A	150C	10WC			5MN	5A	TLM MUB			0
BD161	NS	X03	L05	90V	55V	7V	4A	175C	15WC			50MN	1.5A	AHG ATB	BD149		1
BD162	NS	X03	L05	40V	20V	7V	4A	175C	15WC			30MN	1.5A	AHG ATB	BD148		1
BD163	NS	X03	L05	60V	40V	7V	4A	175C	15WC			20MN	1.5A	AHG ATB	BD149		1
BD165	NS	T0126	L31	45V	45V	5V	1500MA	150C	20WC	3M		40MN	150MA	AMG TFK	BD169	2N4923	0
BD166	PS	T0126	L31	45V	45V	5V	1500MA	150C	20WC	3M		40MN	150MA	AMG TFK	BD140	2N4920	0
BD167	NS	T0126	L31	60V	60V	5V	1500MA	150C	20WC	3M		40MN	150MA	AMG TFK	BD169	2N4923	0
BD168	PS	T0126	L31	60V	60V	5V	1500MA	150C	20WC	3M		40MN	150MA	AMH TFK	BD140	2N4920	0
BD169	NS	T0126	L31	80V	80V	5V	1500MA	150C	20WC	3M		40MN	150MA	AMH TFK	BD169	2N4923	0
BD170	PS	T0126	L31	80V	80V	5V	1500MA	150C	20WC	3M		15MN	500MA	AHH SEU	BD238	2N4920	0
BD171	NS	T0126	L31	100V	90V	5V	500MA	150C	20WC	3M		40MN	50MA	ALE TFK	BD232		0
BD172	NS	T0126	L31	100V	90V	5V	500MA	150C	20WC	3M		40MN	50MA	ALE TFK	BD232		0
BD173	NS	T0126	L31	170V	160V	5V	500MA	150C	20WC	3M		40MN	50MA	ALE TFK	BD232		0
BD175	NS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		40MN	150MA	AHG TFK	BD237	2N4923	0
BD175/6	NS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		40/100	150MA	AHG TFK	BD561	2N4923	2
BD175/10	NS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		63/160	150MA	AHG TFK	BD561	2N5192	2
BD175/16	NS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		100MN	150MA	AHG TFK	BD561	2N5192	2
BD176	PS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		40MN	150MA	AHG TFK	BD238	2N4920	0
BD176/6	PS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		40/100	150MA	AHG TFK	BD236	2N4920	2
BD176/10	PS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		63/160	150MA	AHG TFK	BD236	2N4920	2
BD176/16	PS	T0126	L31	45V	45V	5V	3A	135C	30WC	3M		100MN	150MA	AHG TFK	BD236	2N4920	2
BD177	NS	T0126	L31	60V	60V	5V	3A	135C	30WC	3M		40MN	150MA	AHG TFK	BD237	2N4923	0
BD177/6	NS	T0126	L31	60V	60V	5V	3A	135C	30WC	3M		40/100	150MA	AHG TFK	BD189	2N5192	2
BD177/10	NS	T0126	L31	60V	60V	5V	3A	135C	30WC	3M		63/160	150MA	AHG TFK	BD189	2N5192	2