

| | | | | | | | |
|-------------|-----|-------------|--|---------|-----------|--------------|-----------------|
| STA 441 C | Sak | Si-N | 2x NPN + 2x Di, 180/160V, 1,5/3A, 3,4W Dioden: 30V, 0,2A, Uf<1V(0,2A) | 10-SIP | - | - | - |
| STA 451 C | Sak | Si-N/P | 2xNPN + 2xPNP, 60/60V, 3/6A, 4W, sat<1V(2A) | 10-SIP | - | - | - |
| STA 453 C | Sak | Si-N/P | 2x NPN+PNP, 60/60V, 3/6A, 4W, sat<1V(2A) | 10-SIP | - | - | - |
| STA 455 C | Sak | Si-N/P | 2x NPN+PNP, 50/35V, 7/12A, 4W, sat<0,5V(5A) | 10-SIP | - | - | - |
| STA 457 C | Sak | Si-N/P-Darl | 2x N+P-Darl, Damper-Di, 60/60V, 4/8A, 4W | 10-SIP | - | - | - |
| STA 458 C | Sak | Si-N/P+Di | 2x NPN+PNP, Rbe=600Ω, 50/30V, 5/10A, 4W, 300/600ns | 10-SIP | - | - | - |
| STA 460 C | Sak | Si-N+Di | 2x NPN, int. Z-Di(C-B), 65/65±5V, ±6/10A, 3,2W | 10-SIP | - | - | - |
| STA 471 C | Sak | Si-N | 2x NPN, 60/60V, 3A, hi-hFE>300, sat<1(1A) | 10-SIP | - | - | - |
| STA 2931 | Itt | Z-IC | +5V, 0,15A, f. Kfz/Cars | 7b | TO-92 | - | - |
| STD 20 | | Si-St | =BZ 102/1V4 | | | Z-Diode 1,4V | 31a |
| STG 1700 | Tho | D/A-IC | CRT, True Color Palette, 16-Bit Pixel Port | 44-PLCC | | | |
| STG 1702 | Tho | D/A-IC | CRT,Enhanced True Color Palette, 16-Bit Pixel Port | 44-PLCC | | | |
| STG 1703 | Tho | D/A-IC | CRT, Dual Clock Synth. Palette, 16-Bit Pixel Port | 68-PLCC | | | |
| STHI 07N50 | Tho | MOS-N-IGBT | Iso-Gate, bipolar, 500V, 7A, 100W | 17c | TO-220 | | IGT 4 E10...E11 |
| STHI 07N50R | | MOS-N-IGBT | =STHI 07N50: Iso | 17c | TO-220Iso | | - |
| STHI 10N50 | Tho | MOS-N-IGBT | Iso-Gate, bipolar, 500V, 10A, 100W | 17c | TO-220 | | IGT 4 E10...E11 |
| STHI 10N50R | | MOS-N-IGBT | =STHI 10N50: Iso | 17c | TO-220Iso | | - |

STK....STL

| | | | | | | | |
|------------------|-----|-----------|---|------------|------------|--------------|--|
| STK 011 | Say | Hybrid-IC | =STK 016: 38V, >6,5W(25V/8Ω) | HYB | | | STK 015, STK 016 |
| STK 013(K) | Say | Hybrid-IC | =STK 014: 50V, 2x>9,5W(32V/8Ω) | HYB | | | STK 014 |
| STK 014 | Say | Hybrid-IC | Audio Out, 55V, 2x>15W(38V/8Ω) | HYB | | | - |
| STK 015 | Say | Hybrid-IC | =STK 016: 48V, >10W(32V/8Ω) | HYB | | | STK 016 |
| STK 016 | Say | Hybrid-IC | Audio Out, 54V, >15W(38V/8Ω) | HYB | | | - |
| STK 020 | Say | Hybrid-IC | =STK 027: ±24V, >10W(±16V/8Ω) | HYB | | | STK 027 |
| STK 021 | Say | Hybrid-IC | =STK 035: 54V, >15W(38V/8Ω) | HYB | | | STK 024, STK 031, STK 035 |
| STK 022 | Say | Hybrid-IC | =STK 036: ±27V, >15W(±19V/8Ω) | HYB | | | STK 025, STK 032, STK 036 |
| STK 023 | Say | Hybrid-IC | Audio Out, >20W(44V/8Ω) | HYB | | | - |
| STK 024 | Say | Hybrid-IC | =STK 035: 60V, >20W(44V/8Ω) | HYB | | | STK 031, STK 035 |
| STK 025(G) | Say | Hybrid-IC | =STK 036: ±30V, >20W(±22V/8Ω) | HYB | | | STK 032, STK 036 |
| STK 0025 | Say | Hybrid-IC | =STK 0059: ±35V, 3A, >23W(±24,4V/8Ω) | HYB | | | STK 0029, STK 0039, STK 0049 |
| STK 027 | Say | Hybrid-IC | Audio Out, ±27, V, >15W(±19V/8Ω) | HYB | | | - |
| STK 029 | Say | Hybrid-IC | Audio Out, >25W(48V/8Ω) | HYB | | | - |
| STK 0029 | Say | Hybrid-IC | =STK 0059: ±37V, 5A, >35W(±25V/8Ω) | HYB | | | STK 0039, STK 0049, STK 0059 |
| STK 030 | Say | Hybrid-IC | Audio Out, >25W(±24V/8Ω) | HYB | | | - |
| STK 0030 | Say | Hybrid-IC | =STK 0050: ±40V, 4A, >30W(±28,5V/8Ω) | HYB | | | STK 0040, STK 0050 |
| STK 031 | Say | Hybrid-IC | =STK 035: 66V, >25W(48V/8Ω) | HYB | | | STK 035 |
| STK 032 | Say | Hybrid-IC | =STK 036: ±33V, >25W(±24V/8Ω) | HYB | | | STK 036 |
| STK 035 | Say | Hybrid-IC | Audio Out, 70V, >30W(54V/8Ω) | HYB | | | - |
| STK 0035 | Say | Hybrid-IC | | HYB | | | - |
| STK 036 | Say | Hybrid-IC | Audio Out, ±35V, >30W(±27V/8Ω) | HYB | | | - |
| STK 0039 | Say | Hybrid-IC | =STK 0059: ±45V, 5A, >35W(±31V/8Ω) | HYB | | | STK 0049, STK 0059 |
| STK 040 | Say | Hybrid-IC | =STK 043: ±25V, 2x>10W(±16,5V/8Ω) | HYB | | | STK 041, STK 043 |
| STK 0040 | Say | Hybrid-IC | =STK 0050: ±48V, 5A, >40W(±33V/8Ω) | HYB | | | STK 0050 |
| STK 0040 II | Say | Hybrid-IC | =STK 0050 II: ±48V, 5A, >40W(±36V/8Ω) | HYB | | | STK 0050 II, (STK 0060 II, STK 0070 II) ⁶ |
| STK 041 | Say | Hybrid-IC | =STK 043: ±29V, 2x>15W(±20V/8Ω) | HYB | | | STK 043 |
| STK 043(-105) | Say | Hybrid-IC | Audio Out, ±32,5V, 2x>20W(±22V/8Ω) | HYB | | | - |
| STK 0049 | Say | Hybrid-IC | =STK 0059: ±50V, 5A, >45W(±35V/8Ω) | HYB | | | STK 0059 |
| STK 050(N) | Say | Hybrid-IC | =STK 070: ±45V, >50W(±35V/8Ω) | HYB | | | STK 070 |
| STK 0050 | Say | Hybrid-IC | Audio Out, ±53V, 5A, >50W(±36V/8Ω) | HYB | | | - |
| STK 0050 II | Say | Hybrid-IC | Audio Out, ±53V, 6A, >50W(±39V/8Ω) | HYB | | | (STK 0060 II, STK 0070 II, STK 0080 II) ⁶ |
| STK 054 | Say | Hybrid-IC | =STK 056: ±27,5V, >15W(±19V/8Ω) | HYB | | | STK 056 |
| STK 055 | Say | Hybrid-IC | Audio Out, >15W(±20V/8Ω) | HYB | | | - |
| STK 0055 | Say | Hybrid-IC | =STK 0059: >50W(±38V/8Ω) | HYB | | | STK 0059 |
| STK 056 | Say | Hybrid-IC | Audio Out, ±32V, >20W(±22V/8Ω) | HYB | | | - |
| STK 057 | Say | Hybrid-IC | Audio Out, >20W(±22V/8Ω) | HYB | | | - |
| STK 058 | Say | Hybrid-IC | Audio Out, ±35V, >24W(±24V/8Ω) | HYB | | | - |
| STK 0059 | Say | Hybrid-IC | Audio Out, ±52V, 7A, >55W(±38V/8Ω) | HYB | | | - |
| STK 060 | Say | Hybrid-IC | Audio Out, >30W(±27V/8Ω) | HYB | | | - |
| STK 0060 | Say | Hybrid-IC | =STK 0080: ±55V, 7A, >60W(±40V/8Ω) | HYB | | | STK 0070, STK 0080 |
| STK 0060 II | Say | Hybrid-IC | =STK 0080 II: ±55V, 8A, >60W(±41V/8Ω) | HYB | | | STK 0070 II, STK 0080 II |
| STK 0065 | Say | Hybrid-IC | =STK 0059: >60W(±40V/8Ω) | HYB | | | - |
| STK 067 | Say | Hybrid-IC | Audio Out, 35V, 2,5A, >30W(26,4V/330Ω) | HYB | | | STK 071 |
| STK 070(N) | Say | Hybrid-IC | Audio Out, ±55V, >70W(±42V/8Ω) | HYB | | | - |
| STK 0070 | Say | Hybrid-IC | =STK 0080: ±55V, 7A, >70W(±43V/8Ω) | HYB | | | STK 0080 |
| STK 0070 II | Say | Hybrid-IC | =STK 0080 II: ±60V, 10A, >70W(±45V/8Ω) | HYB | | | STK 0080 II |
| STK 071 | Say | Hybrid-IC | =STK 067: 35V, 5A, >60W(26,4V/165Ω) | HYB | | | - |
| STK 075(G) | Say | Hybrid-IC | =STK 078: ±28V, >15W(±20V/8Ω) | HYB | | | STK 077(G), STK 078(G) |
| STK 077(G) | Say | Hybrid-IC | =STK 078: ±32V, >20W(±22V/8Ω) | HYB | | | STK 078(G) |
| STK 078(G)(-105) | Say | Hybrid-IC | Audio Out, ±35V, >24W(±25V/8Ω) | HYB | | | - |
| STK 080(G) | Say | Hybrid-IC | =STK 082: ±39V, >30W(±27V/8Ω) | HYB | | | STK 082(G) |
| STK 0080 | Say | Hybrid-IC | Audio Out, ±65V, 10A, >80W(±46V/8Ω) | HYB | | | - |
| STK 0080 II | Say | Hybrid-IC | Audio Out, ±65V, 12A, >80W(±47V/8Ω) | HYB | | | - |
| STK 082(G)(-105) | Say | Hybrid-IC | Audio Out, ±43V, >35W(±30V/8Ω) | HYB | | | - |
| STK 083(G) | Say | Hybrid-IC | Audio Out, >40W(±32V/8Ω) | HYB | | | - |
| STK 084(G) | Say | Hybrid-IC | =STK 086: ±50V, 7A, >50W(±35V/8Ω) | HYB | STK 086(G) | HYB | STK 086(G) |
| STK 085(-105) | Say | Hybrid-IC | =STK 086: ±55V, >60W(±38V/8Ω) | HYB | STK 086(G) | HYB | STK 086(G) |
| STK 086(G) | Say | Hybrid-IC | Audio Out, ±55V, 7A, >70W(±42V/8Ω) | HYB | STK 086* | HYB | - |
| STK 0100 | Say | Hybrid-IC | Audio Out, ±75V, >100W(±50V/8Ω) | HYB | | | - |
| STK 0100 II | Say | Hybrid-IC | Audio Out, ±75V, 15A, >100W(±52V/8Ω) | HYB | | | - |
| STK 101 | Say | Hybrid-IC | Moving Coil Abtastverst./MC Head Amp. | 6-SIP | | | - |
| STK 0105 | Say | Hybrid-IC | Audio Out, ±75V, 10A, >100W(±50V) | HYB | | | - |
| STK 183 BB-M | Say | Hybrid-IC | CRT, 3xVideo Out, VGA, 120V, 0,1A, 27MHz | HYB(67x25) | (4128) | | - |
| STK 183 BC-M | Say | Hybrid-IC | =STK 183BB-M: 32MHz | HYB(67x25) | (4128) | | - |
| STK 185 B | Say | Hybrid-IC | CTV, 3xVideo Out, 300V, 0,1A, 17MHz | HYB(64x31) | (4097) | | - |
| STK 0292 | Say | Hybrid-IC | =STK 0452: ±43V, 5A, >25W(±26,5V/8Ω) | HYB | | | STK 0352, STK 0452 |
| STK 301-090 | Say | Hybrid-IC | Dual 7-Band Graphic Equalizer, Ucc=20/7V | 21-SIP | (4143) | | - |
| STK 301-220 | Say | Hybrid-IC | Dual 7-Band Graphic Equalizer, Ucc=36(±18)/7V | 21-SIP | (4143) | | - |
| STK 311-010 | Say | Hybrid-IC | RDS Data Decoder, ARI Decoder, Ucc=6,3V | 19-SIP | (4143) | | - |
| STK 311-110 | Say | Hybrid-IC | RDS Data Decoder, ARI Decoder, Ucc=6,3V | 17-SIP | (4142) | | - |
| STK 350-000 | Say | Hybrid-IC | 2x Audio Drv(Voltage Amp.), ±55V | HYB(53x22) | (4147) | STK 3042 III | HYB(44x30) STK 3042, STK 3062, STK 3082, STK 3102++ |
| STK 350-010 | Say | Hybrid-IC | =STK 350-000: ±59V | HYB(53x22) | (4147) | STK 3122 III | HYB(44x30) STK 3062, STK 3082, STK 3102, STK 3122++ |