

2 SC 5161(F5)	Si-N	S-L, 400/400V, 2A, 10W	30j	-			
2 SC 5162(F5)	Si-N	S-L, -/600V, 1A, 10W	30j	-			
2 SC 5163	Si-N	TV/Monitor-HA, 1500V, 7A, tf<500ns	18c	2SC4770		18c	
2 SC 5164	Si-N	TV/Monitor-HA, 1500V, 10A, tf<600ns	18c	2SC4924		18c	
2 SC 5165	Si-N	TV/Monitor-HA, 1500V, 20A, tf<500ns	18c	-			
2 SC 5166	Si-N	TV/Monitor-HA, 1500V, 10A, tf<800ns	18c	2SC4924		18c	
2 SC 5167	Si-N	TV/Monitor-HA, 1500V, 20A, tf<800ns	18c	-			
2 SC 5171	Si-N	TV, L, 180/180V, 2A, 20W, 200MHz	17c	2SC4159		17c	
2 SC 5172	Si-N	S-Reg, 600/400V, 5A, 25W, <700/3000ns	17c	BUT 11 AF		17c	
2 SC 5173	Si-N	Vid, S-L, 300/300V, 0,1A, 70MHz	15c	(2SC1505)		17j	3
2 SC 5174	Si-N	Uni, 230/230V, 1A, 1,8W, 100MHz	15c	-			
2 SC 5175	Si-N	Uni, io-sat, 60V, 5A, 1,8W, 100MHz	15c	2SC3299		17c	
2 SC 5176	Si-N	Uni, io-sat, 100V, 5A, 1,8W, 120MHz	15c	-			
2 SC 5191	Si-N	SMD, UHF, 9V, 0,1A, 4500MHz	35a	2SC3356		35a	
2 SC 5196	Si-N	NF-HiFi-E, 80/80V, 6A, 60W, 30MHz	18j	BD 245 C		18j	
2 SC 5197	Si-N	NF-HiFi-E, 120/120V, 8A, 80W, 30MHz	18j	BD 245 C		18j	
2 SC 5198	Si-N	NF-HiFi-E, 140/140V, 10A, 100W, 30MHz	18j	2SC2837		18j	
2 SC 5199	Si-N	NF-HiFi-E, 180/180V, 12A, 120W, 30MHz	77j	2SC3281		77j	
2 SC 5200	Si-N	NF-HiFi-E, 230/230V, 15A, 150W, 30MHz	77j	-			
2 SC 5201	Si-N	S, 600/600V, 0,05A, 0,9W, 30MHz	7c(9mm)	-			
2 SC 5206	Si-N	S-L, 500/400V, 5A, 25W, tf=600ns	17c	2SC3795 A		17c	
2 SC 5207 A	Si-N	Display-HA, 1500/800V, 10A, 50W	≈18c	2SC4924		18c	
2 SC 5208	Si-N	S, 600/400V, 0,8A, 1,3W, <-/4μs	≈12b	-			
2 SC 5216	Si-N	SMD, VHF/UHF, 15V, 50mA, 1300MHz	35a	2SC3356		35a	
2 SC 5217	Si-N	S-L, 500/400V, 7A, tf=300ns	17c	BUT 12 AF		17c	
2 SC 5219	Si-N+Di	Display-HA, 1700/-V, 8A, 50W	≈18c	-			
2 SC 5225	Si-N	Vid, 100V, 0,3A, 0,625W, 1,4GHz	7c	-			
2 SC 5230	Si-N	VHF/UHF, 20V, 70mA, 0,4W, 6.5GHz	7f	2SC3355		7f	
2 SC 5235	Si-N	TV/Monitor-HA, 1500V, 20A, tf<300ns	77j	2SC3998		77j	
2 SC 5237	Si-N	Vid-E, 250/250V, 0,15A, 8W, 400MHz	≈14b	-			
2 SC 5239	Si-N	S-L, S-Reg, 900/550V, 3A, 50W, 6MHz	17j	BUT 11 A		17j	
2 SC 5241	Si-N	S-Reg, 600/450V, 5A, 30W, <500/2100ns	17c	BUT 11 AF		17c	
2 SC 5242	Si-N	=2SC5200: 130W	18j	2SC3263		18j	
2 SC 5243	Si-N	Monitor-HA, 1700V, 15A, 200W	77j	-			
2 SC 5244	Si-N	Monitor-HA, 1500V, 20A, 200W	77j	2SC3998		77j	
2 SC 5244 A	Si-N	=2SC5244: 1600	77j	-			
2 SC 5248	Si-N	NF/S-L, 160/160V, 1,5A, 20W, 150MHz	17c	2SC4159		17c	
2 SC 5249	Si-N	S-L, S-Reg, 600/600V, 3A, 35W, 6MHz	17c	BUT 11 AF		17c	
2 SC 5250	Si-N+Di	Display-HA, 1500/-V, 8A, 50W	≈18c	BU 2508 DF		16c	
2 SC 5251	Si-N	Display-HA, 1500/800, 12A, 50W	≈18c	BU 2525 AF		16c	
2 SC 5252	Si-N	Display-HA, 1500/800, 15A, 50W	≈18c	-			
2 SC 5264	Si-N	HA,S-L, 1000/450V, 5A, 30W	17c	-			
2 SC 5265	Si-N	HA,S-L, 1200/600V, 4A, 30W	17c	-			
2 SC 5266	Si-N	S-L, 600/400V, 5A, <700/3000ns	15c	BUT 11 AF		17c	
2 SC 5270	Si-N	TV/Monitor-HA, 1500V, 12A, tf<200ns	18c	BU 2525 AF		16c	
2 SC 5271	Si-N	S-L, S-Reg, 300/200V, 5A, 30W, 10MHz	17c	(BUT 11 AF)		17c	
2 SC 5273	Si-N	S-L, Focus, 1300/1300V, 0,03A, 1,8A	17j	-			
2 SC 5278	Si-N	S-L, 450/400V, 10A, tf=1μs	18j	BUW 12A		18j	
2 SC 5279	Si-N	S-L, 600/400V, 2A, <1/3,5μs	15c	BUT 11 AF		17c	
2 SC 5280	Si-N	CRT HA, 1500/600V, 8A, 50W	18c	BU 2508 AF		16c	
2 SC 5281	Si-N	S-L, 800/500V, 10A, tf=300ns	18c	(BUW 12 A)		3	
2 SC 5282	Si-N	S-L, 900/800V, 4A, tf=300ns	18c	(BUW 11A)		3	
2 SC 5283	Si-N	S-L, 1000/800V, 5A, tf=500ns	18c	(BUW 11A)		3	
2 SC 5284	Si-N	S-L, 1200/800V, 10A, tf=300ns	18c	-			
2 SC 5285	Si-N	S-L, -/500V, 0,5A	30j	-			
2 SC 5287	Si-N	S-L, S-Reg, 900/550V, 5A, 80W, 6MHz	18j	BUW 11 A		18j	