

TRANSISTOR NUMBER	PM O A LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
2N6548	NS	X17	L32	50V	40V	12V	2A	150C	2WF	100M		25KMN	200MA	AMD	MOB	BD279	2N6548	2
2N6549	NS	X17	L32	50V	40V	12V	2A	150C	2WF	100M		15KMN	200MA	AMD	MOB	BD279	2N6548	2
2N6551	NS	X17	L35	60V	60V	5V	1A	150C	2WF	75M		80MN	50MA	RMG	MOB	BD519	2N6553	2
2N6552	NS	X17	L35	80V	80V	5V	1A	150C	2WF	75M		80MN	50MA	RMG	MOB	BD519	2N6553	2
2N6553	NS	X17	L35	100V	100V	5V	1A	150C	2WF	75M		80MN	50MA	RMG	MOB	BD529	2N6553	2
2N6554	PS	X17	L35	60V	60V	5V	1A	150C	2WF	75M		80/300	50MA	RMG	NAT	BD529	2N6555	2
2N6555	PS	X17	L35	80V	80V	5V	1A	150C	2WF	75M		80/300	50MA	RMG	NAT	BD529	2N6556	2
2N6556	PS	X17	L35	100V	100V	5V	1A	150C	2WF	75M		80/300	50MA	RMG	NAT	BD529	2N6556	2
2N6557	NS	X17	L35	250V	250V	6V	500MA	150C	2WF	45M		40MN	30MA	RME	MOB		2N6559	2
2N6558	NS	X17	L35	300V	300V	6V	500MA	150C	2WF	45M		40MN	30MA	RME	MOB		2N6559	2
2N6559	NS	X17	L35	350V	350V	6V	500MA	150C	2WF	45M		40MN	30MA	RME	MOB		2N6559	2
2N6560	NS	T03	L05	450V	450V	5V	10A	200C	220WC	10M		10MN	5A	RHE	KER	BUX25	2N6547	2
2N6561	NS	T03	L05	300V	300V	5V	20A	200C	220WC	15M		10MN	10A	RHE	KER	BUX12	2N6561	2
2N6562	NS	TO61	L46	450V	450V	5V	10A	200C	175WC	10M		10MN	5A	RHE	KER			2
2N6563	NS	TO61	L46	300V	300V	5V	20A	200C	175WC	10M		10MN	10A	RHE	KER			2
2N6566	NS	TO46	L01	30V	30V	30V	100MA	200C	400MWF	3M	10P	100MN	1MA	ALC	CRY			2
2N6567	PS	TO46	L01	30V	30V	30V	100MA	200C	400MWF	3M	10P	30MN	1MN	ALC	CRY	BCY94	2N2946A	2
2N6569	NS	T03	L05	45V	40V	5V	12A	200C	100WC	1M5		15/200	4A	RHS	MOB	BD317	2N3772	2
2N6570	NS	T03	L05	100V	90V	7V	40A	200C	250WC	1M		20/60	15A	AHH	TRW	BUX22	2N6277	2
2N6571	NS	T03	L05	115V	105V	7V	40A	200C	250WC	1M		20/60	15A	AHE	TRW	BUX22	2N6277	2
2N6573	NS	T03	L05	500V	250V	5V	10A	200C	125WC	5M		7/21	7A	RHE	MOB	BUX14	2N6251	2
2N6574	NS	T03	L05	600V	275V	5V	10A	200C	125WC	5M		7/21	7A	RHE	MOB	BUX14	2N6251	2
2N6575	NS	T03	L05	700V	300V	5V	10A	200C	125WC	5M		7/21	7A	RHE	MOB	BUX25	2N6561	2
2N6576	NS	T03	L05	60V	60V	7V	15A	200C	120WC	4M		500MN	10A	AHD	MOB	BDX67B	2N6577	2
2N6577	NS	T03	L05	90V	90V	7V	15A	200C	120WC	4M		500MN	10A	AHD	MOB	BDX67B	2N6578	2
2N6578	NS	T03	L05	125V	120V	7V	15A	200C	120WC	4M		500MN	10A	AHD	MOB	BDX67B	2N6578	2
2N6591	NS	X17	L35	150V	150V	5V	500MA	150C	2WF	70M		40/200	100MA	RME	MOB		2N6592	2
2N6592	NS	X17	L35	200V	200V	5V	500MA	150C	2WF	70M		40/200	100MA	RME	MOB		2N6593	2
2N6593	NS	X17	L35	250V	250V	5V	500MA	150C	2WF	70M		30/200	100MA	RME	MOB		2N6593	2
2N6594	PS	T03	L05	45V	40V	5V	24A	200C	100WC	2M5	750P	15MN	4A	AHG	RCU			2
2N6595	NS	TO72	L06	20V	15V	2V	25MA	200C	200MWF	3500M	1P1	25MN	14MA	SLA	AMP		2N6596	2
2N6596	NS	TO72	L06	20V	15V	2V	25MA	200C	200MWF	4000M	1P1	25MN	14MA	SLA	AMP		2N6596	2
2N6597	NS	TO72	L06	15V	12V	2V	35MA	200C	200MWF	3500M	1P1	25MN	30MA	SLA	AMP		2N6598	2
2N6598	NS	TO72	L06	15V	12V	2V	35MA	200C	200MWF	4000M	1P1	25MN	30MA	SLA	AMP		2N6598	2
2N6599	NS	TO72	L06	20V	15V	3V	75MA	200C	500MWF	3000M	1P7	25MN	50MA	SLA	AMP	BFS55A		2
2N6600	NS	TO72	L06	20V	15V	3V	75MA	200C	300MWF	3500M	1P7	25MN	50MA	SLA	AMP			2
2N6601	NS	TO72	L06	20V	10V	2V5	50MA	200C	250MWF	1000M	1P2	25MN	50MA	SLA	AMP			2
2N6609	PS	T03	L05	160V	140V	7V	16A	200C	150WC	2M	1N	15MN	8A	AHH	RCU			2
2N6648	PS	T03	L05	40V	40V	5V	15A	200C	70WC	20M		1KMN	5A	AHD	RCU			2
2N6649	PS	T03	L05	60V	60V	5V	15A	200C	70WC	20M		1KMN	5A	AHD	RCU			2
2N6650	PS	T03	L05	80V	80V	5V	15A	200C	70WC	20M		1KMN	5A	AHD	RCU			2
2N6666	PS	TOP66	L32	40V	40V	5V	15A	150C	65WC	20M		1KMN	3A	AHD	RCU			2
2N6667	PS	TOP66	L32	60V	60V	5V	15A	150C	65WC	20M		1KMN	5A	AHD	RCU			2
2N6668	PS	TOP66	L32	80V	80V	5V	15A	150C	65WC	20M		1KMN	5A	AHD	RCU			2
2N6669	NS	TOP66	L32	40V	30V	5V	10A	150C	40WC	10M	150P	20MN	5A	AHG	RCU			2
2N6670	NS	X17	L35	100V	50V	3V	1A5	150C	10WC		50P	30MN	400MA	VHA	RCU			2
2N6671	NS	T03	L05	450V	300V	8V	10A	200C	150WC	15M	300P	10MN	5A	AHE	RCU			2
2N6672	NS	T03	L05	550V	350V	8V	10A	200C	150WC	15M	300P	10MN	5A	AHE	RCU			2
2N6673	NS	T03	L05	650V	400V	8V	10A	200C	150WC	15M	300P	10MN	5A	AHE	RCU			2
2N6674	NS	T03	L05	450V	300V	7V	15A	200C	175WC	15M	500P	8MN	10A	AHE	RCU			2
2N6675	NS	T03	L05	650V	400V	7V	15A	200C	175WC	15M	500P	8MN	10A	AHE	RCU			2
2N6676	NS	T03	L05	450V	300V	8V	20A	200C	175WC	15M	500P	8MN	15A	AHE	RCU			2
2N6677	NS	T03	L05	550V	350V	8V	20A	200C	175WC	15M	500P	8MN	15A	AHE	RCU			2
2N6678	NS	T03	L05	650V	400V	8V	20A	200C	175WC	15M	500P	8MN	15A	AHE	RCU			2
2N32525	NS	TO39	L04	60V	30V	5V	1A	175C	1WF	200M	12P	30/90	500MA	RMS	MOU	BSW54	2N2219A	2
25014	NS	T05	L04	40V		1V	20MA	165C	125MWF	10M	3P2	20/55	10MA	RMG	TIB			0
25017	NS	T05	L04	60V	60V	8V	400MA	175C	4WC	2500K		12/36	200MA	RMG	TIB			0
25018	NS	T05	L04	100V	100V	8V	400MA	175C	4WC	2500K		12/36	200MA	RMH	TIB			0
25019	NS	T05	L04	60V	60V	8V	400MA	175C	4WC	2500K		30/90	200MA	RMG	TIB			0
25020	NS	T05	L04	100V	100V	8V	400MA	175C	4WC	2500K		30/90	200MA	RMH	TIB			0
25024	NS	X51	X51	100V	32V	10V	7.5A	200C	100WC	10M		20MN	2A	AHS	TIB			1
25025	NS	X51	X51	150V	60V	10V	7.5A	200C	100WC	10M		20MN	2A	AHS	TIB			1
25026	NS	X51	X51	200V	100V	10V	7.5A	200C	100WC	10M		20MN	2A	AHH	TIB			1
25033	NS	T03	L05	100V	75V		3A	175C	40WC	15M		30/100	1A	RHH	TIB			0
25034	NS	T03	L05	100V	75V		3A	175C	40WC	15M		60/200	1A	RHH	TIB			0
25035	NS	T03	L05	150V	100V		3A	175C	40WC	15M		30/100	1A	RHH	TIB			0
25036	NS	T03	L05	150V	100V		3A	175C	40WC	15M		60/200	1A	RHH	TIB			0
2S95A	NS	TO18	L01	25V	20V	5V	200MA	175C	300MWF	300M		50/200	10MA	VLS	TIB	BSX20	2N2369	0
2S102	NS	TO18	L01	60V	45V	6V	50MA	175C	400MWF	150M	10P	20/50	5MA	RLG	TIB	BSW64	2N2222A	0
2S103	NS	TO18	L02	60V	45V	6V	50MA	175C	400MWF	150M	10P	40/100	5MA	RLG	TIB	BSW64	2N2222A	0
2S104	NS	TO18	L02	60V	45V	6V	50MA	175C	400MWF	150M	10P	80/200	5MA	RLG	TIB	BSW64	2N2222A	0
2S131	NS	TO18	L01	15V	12V	5V	200MA	175C	300MWF	220M		20MN	10MA	VLS	TIB	BSX20	2N2369	0
2S301	PS	T05	L04	80V	80V	30V	100MA	200C	300MWF	350K	65P	10/30	1MA	ALH	TIB			0
2S302	PS	T05	L04	40V	40V	20V	100MA	200C	300MWF	400K	65P	15/35	1MA	ALA	TIB			0
2S302A	PS	T05	L04	25V	25V	10V	150MA	200C	300MWF	350K	65P	15/60	10MA	ALA	TIB			0