

TRANSISTOR NUMBER	PM O A LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
BFJ73	NS	T018	L01	45V	45V	5V	100MA	185C	500MWF	50M	8P	76MN	1MA	RLA	RIZ	BSW64	2N760	2
BFJ74	NS	T018	L01	50V	50V	5V	100MA	185C	360MWF	250M	3P5	40/160	10MA	ALH	RIZ		2N915	2
BFJ75	NS	T018	L01	25V	25V	5V	100MA	185C	360MWF	300M	6P	50/200	10MA	RLA	RIZ	BSW64	2N916	2
BFJ77	NS	T072	L06	15V	15V	4V	25MA	185C	200MWF	800M	1P7	20MN	3MA	ULA	RIZ	BFY90	2N917	2
BFJ78	NS	T072	L06	15V	15V	4V	50MA	185C	200MWF	600M	1P7	20MN	3MA	ULA	RIZ	BFX73	2N918	2
BFJ79	NS	T072	L06	13V	13V	4V	50MA	185C	200MWF	600M	2P5	20/200	4MA	ULA	RIZ	BFX73	2N2865	2
BFJ92	NS	T018	L01	45V	45V	5V	100MA	185C	300MWF		6P	40MN	10UA	ALN	RIZ	BC109	2N929	2
BFJ93	NS	T018	L01	45V	45V	5V	100MA	185C	300MWF		6P	100MN	10UA	ALN	RIZ	BC109	2N930	2
BFJ98	NS	T039	L04	150V	150V	6V	100MA	200C	800MWF		3R	30MN	25MA	ALR	RIZ	BF659	2N3440	2
BFP519	NS	T018	L01	70V			20MA	175C	300MWF	150M		20/200	1MA	FRM	UNR			2
BFP520	NS	T018	L01	50V			20MA	175C	300MWF	150M		20/200	1MA	FRM	UNR			2
BFP521	NS	T018	L01	30V			20MA	175C	300MWF	150M		20/200	1MA	FRM	UNR			2
BFP619	NS	T092	L74	70V			20MA	125C	300MWF	150M		20/500	1MA	FRM	UNR			2
BFP620	NS	T092	L74	50V			20MA	125C	300MWF	150M		20/500	1MA	FRM	UNR			2
BFP621	NS	T092	L74	30V			20MA	125C	300MWF	150M		20/500	1MA	FRM	UNR			2
BFQ17	NS	X90A	X90	40V	25V	2V	300MA	150C	1WH	600M	1P	25MN	150MA	UMP	MUB			2
BFQ18	NS	X90A	X90	30V	25V	3V	300MA	150C	1WH	1700M	3P5	30MN	150MA	UMP	MUB			2
BFQ19	NS	X90A	X90	20V	15V	3V	150MA	150C	500MWH	4400M	1P6	25MN	75MA	SMP	MUB			2
BFQ28	NS	X61B	X61	20V	15V	1V5	20MA	175C	200MWF		0R5	30MN	10MA	SLA	SID			2
BFQ31	NS	X12	L29	30V	15V	3V	100MA	150C	200MWF	600M	1P7	20MN	3MA	ULA	FEB			2
BFQ31A	NS	X12	L29	30V	15V	3V	100MA	150C	200MWF	600M	1P7	100MN	3MA	ULA	FEB			2
BFQ31R	NS	X12	L27	30V	15V	3V	100MA	150C	200MWF	600M	1P7	20MN	3MA	ULA	FEB			2
BFQ31AR	NS	X12	L27	30V	15V	3V	100MA	150C	200MWF	600M	1P7	100MN	3MA	ULA	FEB			2
BFQ32	PS	X63A	X63	20V	15V	3V	150MA	175C	500MWH	3600M	1R4	20MN	75MA	SLA	MUB			2
BFQ34	NS	X54D	X54	25V	18V	2V	150MA	200C	2.25WC	3500M	2P75	25MN	150MA	SMP	MUB			2
BFQ35	PS	T05	L04	160V	160V	5V	200MA	175C	500MWF	40M		50/400	10MA	RLE	TIB	BFT196	2N5415	2
BFQ36	PS	T05	L04	250V	250V	5V	200MA	175C	500MWF	40M		40/350	10MA	RLE	TIB	BFT196	2N5416	2
BFQ37	PS	T05	L04	300V	300V	5V	200MA	175C	500MWF	40M		30/300	10MA	RLE	TIB	BFT196	2N5416	2
BFQ38	NS	T039	L04	300V	250V	5V	1A	125C	5.7WC	10M	25P	25MN	50MA	AME	MUB	BUX54	2N3439	2
BFQ39	NS	T039	L04	300V	300V	5V	1A	125C	5.7WC	10M	25P	25MN	50MA	AME	MUB	BUX54	2N3439	2
BFQ40	NS	T039	L04	450V	350V	5V	1A	125C	5.7WC	10M	25P	25MN	50MA	AME	MUB	BUX54	2N3439	2
BFD41	NS	X28	L65	50V	25V	4V	350MA	200C	4WC	600M	6P	20/200	50MA	VHA	TFK			1
BFD42	NS	T039	L04	36V	18V	4V	1A8	200C	7.2WC	350M	16P	10/60	250MA	VMP	MUB			2
BFD43	NS	T039	L04	36V	18V	4V	3A75	200C	12WC	350M	30P	10/80	500MA	VMP	MUB			1
BFR10	NS	T039	L04	75V	40V	6V	500MA	200C	800MWF	250M	8P	60/120	150MA	RMG	ATB	BSW54	2N2219A	1
BFR11	NS	T018	L01	75V	40V	6V	500MA	200C	400MWF	250M	8P	60/120	150MA	RMG	ATB	BSW64	2N2222A	1
BFR12	NS	T018	L01		30V		300MA	200C	1WC	480M				UMP	TFK			0
BFR14A	NS	X61B	X61	20V	12V	2V5	30MA	175C	250MWF	2500M	0R65	40MN	20MA	SLA	SID			2
BFR14B	NS	X61B	X61	20V	12V	2V5	30MA	175C	250MWF	3000M	0R65	25MN	20MA	SLA	SID			2
BFR14C	NS	X61C	X61	27V	20V	1V5	35MA	175C	700MWF	2150M	0R65	30MN	15MA	SLA	SID			2
BFR15	NS	T072	L51	12V	12V	3V5	30MA	150C	260MWF	2G	1P1	25MN	5MA	SLG	SID	BFR14	2N5852	1
BFR15A	NS	T072	L51	20V	12V	2V5	30MA	150C	200MWF	2250M	0R85	25MN	20MA	SLA	SID	BFT17	2N5835	2
BFR16	NS	T018	L01	60V	60V	8V	100MA	200C	360MWF	70M	6P	150MN	1MA	ALA	SGI	BC109	2N930	0
BFR17	NS	T018	L01	60V	60V	8V	100MA	200C	360MWF	70M	6P	450MN	1MA	ALA	SGI	BC109C	2N930	0
BFR17	NS	X12	L69	15V	15V	3V	50MA	150C	200MWF	650M	1R3	20/150	2MA	ULA	MUB			2
BFR17R	NS	X12	L27	15V	15V	3V	50MA	150C	200MWF	650M	1R3	20/150	2MA	ULA	MUB			2
BFR18	NS	T018	L01	85V	55V	7V	500MA	200C	500MWF	60M	20P	60MN	150MA	AMG	SGI	BSX33	2N731	0
BFR18	NS	X12	L29	30V	20V	5V	30MA	150C	200MWF	200M	1R7	35/125	1MA	RLA	MUB			2
BFR18R	NS	X12	L27	30V	20V	5V	30MA	150C	200MWF	200M	1R7	35/125	1MA	RLA	MUB			2
BFR19	NS	T05	L04	75V	35V	7V	1A	200C	800MWF	60M	20P	30MN	500MA	AMG	SGI	BFY51	2N2297	0
BFR20	NS	T05	L04	75V	35V	7V	1A	200C	800MWF	60M	20P	90MN	150MA	AMG	SGI	BFY51	2N2297	0
BFR21	NS	T039	L04	120V	70V	7V	1A	200C	800MWF	60M	20P	40MN	150MA	AMS	SGI	BFY65	2N1990	0
BFR22	NS	T039	L04	120V	65V	7V	1A	200C	800MWF	60M	15P	40MN	150MA	AMH	ATI	BSW66	2N4001	0
BFR23	PS	T039	L04	90V	65V	7V	1A	200C	800MWF	50M	30P	40MN	150MA	AMH	ATI	BFR23	2N4036	0
BFR24	PS	T039	L04	60V	40V	7V	1A	200C	800MWF	60M	30P	50MN	150MA	AMG	OBS	BF395	2N4036	2
BFR25	NS	T018	L01	120V	120V	6V	500MA	175C	375MWF	6M	10P	20MN	20MA	AMH	ATI	BFR25	2N4390	0
BFR26	NS	T018	L01	30V	20V		120MA	200C	300MWF			15/50	50MA	AMG	LTT	BSX20	2N2369	1
BFR27	NS	T05	L04	160V			400MA		600MWF		15P	30/120	200MA	AME	LTT	BSW67	2N5682	1
BFR28	NS			30V	20V	3V	50MA	200C	200MWF	400M	0R95	30MN	5MA	SLA	SID			2
BFR34	NS	X17	L35	12V	12V	3V5	30MA	125C	200MWF	2G5	0P7	25MN	5MA	SLA	SID			1
BFR34A	NS	X12	L69	12V	12V	3V5	30MA	125C	200MWF	2G5	0R8	25MN	5MA	ULG	SID			1
BFR35	NS	X12	L29	12V	12V	3V5	30MA	125C	200MWF	3G	0P7	25MN	5MA	SLA	SID			1
BFR35A	NS	X12	L69	12V	12V	3V5	30MA	125C	200MWF	2G2	0R8	25MN	5MA	ULG	SID			1
BFR36	NS	T039	L04	40V	30V	3V	400MA	200C	800MWF	1G	2R2	60/130	70MA	UMA	ATB			1
BFR37	NS	T072	L51	30V	30V	4V	50MA	200C	250MWF	800M	0R3	80/250	10MA	ULA	ATB	BFY90	2N2857	1
BFR38	PS	T072	L51	40V	35V	3V	20MA	200C	200MWF	700M	0R5	25MN	3MA	ULA	ATB	BF497		1
BFR39	NS	T092	L21	90V	80V		2A	125C	800MWF	100M		50MN	100MA	AMH	TIB		2N5551	1
BFR39	NS	T092	L21	90V	80V	5V	1A	150C	800MWF	100M	10P	50MN	100MA	AMH	TIB	BCX49	2N5551	2
BFR39T05	NS	T092	L54	90V	80V		2A	125C	800MWF	100M		50MN	100MA	AMH	TIB	BSW66	2N4001	0
BFR40	NS	T092	L21	70V	60V		2A	125C	800MWF	100M		75MN	100MA	AMG	TIB	BCW36	2N3704	1
BFR40	NS	T092	L21	70V	60V	5V	1A	150C	800MWF	100M	10P	75MN	100MA	AMH	TIB	BCX49	2N5551	2
BFR40T05	NS	T092	L54	70V	60V		2A	125C	800MWF	100M		75MN	100MA	AMH	TIB	BSW66	2N4001	1
BFR41	NS	T092	L21	60V	50V		2A	125C	800MWF	100M		100MN	100MA	AMG	TIB	BCW36	2N3704	1
BFR41	NS	T092	L21	60V	50V	5V	1A	150C	800MWF	100M	10P	100MN	100MA	AMG	TIB	BCX49	2N5551	2
BFR41T05	NS	T092	L54	60V	50V		2A	125C	800MWF	100M		100MN	100MA	AMG	TIB	BSV64	2N4877	1