

|             |             |             |  |           |            |          |          |   |   |
|-------------|-------------|-------------|--|-----------|------------|----------|----------|---|---|
| 2 N 3709    | USA,Aeg,Tix | Si-N        | =2N3708: hFE=45...165                              | 7c        | TO-92      | BC 550   | 7a       | BC 168, BC 183, BC 238, BC 548, ++          |   |
| 2 N 3710    | USA,Aeg,Tix | Si-N        | =2N3708: hFE=90...330                              | 7c        | TO-92      | BC 550   | 7a       | BC 168, BC 183, BC 238, BC 548, ++          |   |
| 2 N 3711    | USA,Aeg,Tix | Si-N        | =2N3708: hFE=180...600                             | 7c        | TO-92      | BC 550   | 7a       | BC 168, BC 183, BC 238, BC 548, ++          |   |
| 2 N 3712(S) | USA,Mot,Tix | Si-N        | Vid, 150/150V, 0,2A, 1W, >40MHz                    | (S: TO-39 | 2a         | TO-5     | 2a       | BF 257...259, BF 657...759, 2N5058...59, ++ |   |
| 2 N 3713    | USA,Mot,Sgs | Si-N        | LFS P, 80/60V, 10/15A, 150W, >4MHz, hFE=25...90    | 23a       | TO-3       | BD 317   | 23a      | BD 545B, BD 315, 2N3772, 2N5632...34, ++    |   |
|             | Tos,Tix,++  |             | 450/350ns  | (2N3789   |            |          |          |   |   |
| 2 N 3714    |             | Si-N        | =2N3713: 100/80V                                   | (2N3790   | 23a        | TO-3     | BD 317   | 23a   | BD 545C, BD 317, 2N3772, 2N5632...34, ++    |
| 2 N 3715    |             | Si-N        | =2N3713: hFE=50...150                              | (2N3791   | 23a        | TO-3     | BD 317   | 23a   | BD 545B, BD 315, 2N3772, 2N5632...34, ++    |
| 2 N 3716    |             | Si-N        | =2N3713: 100/80V, hFE=50...150                     | (2N3792   | 23a        | TO-3     | BD 317   | 23a   | BD 545C, BD 317, 2N3772, 2N5632...34, ++    |
| 2 N 3717    | Mot         | Si-N        | HF/S, 60V, 1A, 7,5W(Tc=25°), 250MHz                | 2a        | TO-39      |          |          | 2N3553, 2SC2419                             |   |
| 2 N 3718    | Mot         | Si-N        | HF/S, 60V, 1A, 10W(Tc=25°), 250MHz                 | 49a       |            |          |          | BLY 60                                      |   |
| 2 N 3719    | USA,Mot,Tix | Si-P        | S, 40V, 3A, 1W, >60MHz, <100/400ns                 | 2a        | TO-5       |          |          | 2N3867...68, 2N6303                         |   |
| 2 N 3720    | USA,Mot,Tix | Si-P        | =2N3719: 60V                                       | 2a        | TO-5       |          |          | 2N3868, 2N6303                              |   |
| 2 N 3721    | USA,Gen,Mic | Si-N        | Uni, 18V, 0,1A, 0,36W, 120MHz                      | 7c        | TO-98      |          |          | BC 168, BC 183, BC238, BC 548, ++           |   |
| 2 N 3722    | USA,Mot     | Si-N        | S, 80V, 0,5A, 0,8W, >300MHz, <62/130ns             | 2a        | TO-5       |          |          | BSV 95, 2N3725, 2SC1069                     |   |
| 2 N 3723    | USA,Mot     | Si-N        | =2N3722: 100V, <85/160ns                           | 2a        | TO-5       |          |          | BSW 39, 2SC1069                             |   |
| 2 N 3724    | USA,Fer,Itt | Si-N        | S, 50/30V, 0,5A, 0,8W, >300MHz, 20/55ns, hFE>60    | 2a        | TO-39      |          |          | BSV 77, BSV 95, 2N3722...23, 2N5189, ++     |   |
|             | Mot,Sgs,Tix |             |  | (2N3467   |            |          |          |   |   |
| 2 N 3724 A  |             | Si-N        | =2N3724: 1,2A, 2W                                  | 2a        | TO-39      |          |          | BSS 14, 2N3734...35, 2N5262                 |   |
| 2 N 3725    | =2N3724     | Si-N        | =2N3724: 80/50V                                    | (2N3468   | 2a         | TO-39    |          | BSV 95, 2N3722...23, 2SC1069                |   |
| 2 N 3725 A  |             | Si-N        | =2N3725: 1,2A                                      | 2a        | TO-39      |          |          | BSS 14, 2N3735, 2N5262                      |   |
| 2 N 3726    | USA,Fch,Mic | Si-P        | Dual, in, 45/45V, 0,3A, 0,5W, >200MHz, <4dB(1kHz)  | TO-77     | (CBE-EBC-) |          |          | 2N4015...4016                               |   |
|             | Mot,Sgs,++  |             | hFE=135...350, ΔhFE=0,9...1, ΔUbe<5mV              |           |            |          |          |   |   |
| 2 N 3727    | =2N3727     | Si-P        | ΔUbe<2,5mV   | TO-77     | (CBE-EBC-) |          |          | 2N4015...4016                               |   |
| 2 N 3728    | Fch,Ray,Sca | Si-N        | Dual, 60/30V, 0,5A, 0,45W, >80MHz, F<7dB(1kHz)     | TO-77     | (CBE-EBC-) |          |          | BFX 70...72, 2N2060, 2N2223                 |   |
|             | Sgs         |             | hFE=80...280, ΔhFE=0,8...1, ΔUbe<5mV               |           |            |          |          |   |   |
| 2 N 3729    | =2N3728     | Si-N        | =2N3728: ΔhFE=0,9...1, ΔUbe<3mV                    | TO-77     | (CBE-EBC-) |          |          | BFX 70...72, 2N2060, 2N2223                 |   |
| 2 N 3730    | Gpd,Rca     | Ge-P        | TV-HA, 200V, 3A, 10W(Tc=55°)                       | 23a       | TO-3       |          |          | AU 107, AU 113, AU 213, 2N5324              |   |
| 2 N 3731    | Gpd,Rca     | Ge-P        | TV-HA, 320V, -/10A, 5W(Tc=55°)                     | 23a       | TO-3       |          |          | AU 106, AU 109, AU 111...112, 2N5325        |   |
| 2 N 3732    | Gpd,Rca     | Ge-P        | TV-HA, 100V, 3A, 3W(Tc=55°)                        | 23a       | TO-3       |          |          | AU 108, AU 110, AU 210                      |   |
| 2 N 3733    | USA,EUR     | Si-N        | VHF/UHF P, 65V, 3A, PQ>10W(400MHz)                 | 49a       | TO-60      |          |          | -   |   |
| 2 N 3734(S) |             | Si-N        | S,Drv, 50V, 1,5A, 1W, >250MHz, <48/60ns            | 2a        | TO-5       |          |          | BSS 14, 2N5262                              |   |
| 2 N 3735(S) | USA,EUR     | Si-N        | =2N3734: 75V                                       | 2a        | TO-5       |          |          | BSS 14, 2N5262                              |   |
| 2 N 3736    | USA,EUR     | Si-N        | =2N3734: 0,5W                                      | 2a        | TO-46      |          |          | -   |   |
| 2 N 3737    |             | Si-N        | =2N3734: 75V, 0,5W                                 | 2a        | TO-46      |          |          | -   |   |
| 2 N 3738    | USA,Mot,Tho | Si-N        | LFS P, 250/225V, 1A, 20W, >10MHz                   | (2N6424   | 22a        | TO-66    |          | BUW 40(A,B), BUX 84, 2N4296...97, ++        |   |
| 2 N 3739    | USA,Mot,Tho | Si-N        | =2N3738: 325/300V                                  | (2N6425   | 22a        | TO-66    |          | BUW 40(A,B), BUX 84, 2N4296...97, ++        |   |
| 2 N 3740(A) | USA,Fch,Mot | Si-P        | LFS P, 60/60V, 4/10A, 25W, >4MHz, hFE=30...100     | 22a       | TO-66      | BD 244 C | 17j      | BD 244A, BD 540A, BDX 14, 2N6313...14, ++   |   |
|             | Sgs,Tho,Tix |             | I<100μA(A: <0,1μA)(Umax)                           | (2N3766   |            |          |          |   |   |
| 2 N 3741(A) | =2N3740     | Si-P        | =2N3740: 80/80V                                    | (2N3767   | 22a        | TO-66    | BD 244 C | 17j   | BD 244B, BD 540B, BDX 14, 2N6314, ++        |
| 2 N 3742(S) | Mot,Nsc,Sca | Si-N        | Vid, 300/300V, 0,05A, 1W, >30MHz, hFE=20...200     | 2a        | TO-5       | MPS-U106 | 13m      | BF 259, BF 659, BFR 59, BFS 89, 2N5058      |   |
|             | Ssi,Stc     |             | 2N3742S: TO-39                                     | (2N3743   |            |          |          |   |   |
| 2 N 3743(S) | Mot,Nsc,Sca | Si-P        | Vid, 300/300V, 0,05A, 1W, >30MHz, hFE=25...250     | 2a        | TO-5       | MPS-U60  | 13m      | BFT 44, BFQ 37, 2SB622                      |   |
|             | Ssi,Stc     |             | 2N3743S: TO-39                                     | (2N3742   |            |          |          |   |   |
| 2 N 3744    | USA,Tix     | Si-N        | S P, 60V, 5A, 30W(Tc=100°), >30MHz, hFE=20...60    | 50g       | TO-111     |          |          | -   |   |
| 2 N 3745    |             | Si-N        | =2N3744: 80V                                       | 50g       | TO-111     |          |          | -   |   |
| 2 N 3746    |             | Si-N        | =2N3744: 100V                                      | 50g       | TO-111     |          |          | -   |   |
| 2 N 3747    | USA,Tix     | Si-N        | S P, 60V, 5A, 30W(Tc=100°), >40MHz, hFE=40...120   | 50g       | TO-111     |          |          | -   |   |
| 2 N 3748    |             | Si-N        | =2N3747: 80V                                       | 50g       | TO-111     |          |          | -   |   |
| 2 N 3749    |             | Si-N        | =2N3747: 100V                                      | 50g       | TO-111     |          |          | -   |   |
| 2 N 3750    | USA,Tix     | Si-N        | S P, 60V, 5A, 30W(Tc=100°), >50MHz, hFE=100...300  | 50g       | TO-111     |          |          | -   |   |
| 2 N 3751    |             | Si-N        | =2N3750: 80V                                       | 50g       | TO-111     |          |          | -   |   |
| 2 N 3752    |             | Si-N        | =2N3750: 100V                                      | 50g       | TO-111     |          |          | -   |   |
| 2 N 3762(S) | USA,Mot     | Si-P        | S,Drv, 40V, 1,5A, 1W, >180MHz, <43/115ns           | 2a        | TO-5       |          |          | BSV 82, 2SA799                              |   |
| 2 N 3763(S) |             | Si-P        | =2N3762: 60V                                       | 2a        | TO-5       |          |          | BSV 82, 2SA799                              |   |
| 2 N 3764(A) |             | Si-P        | =2N3762: 0,5W                                      | 2a        | TO-46      |          |          | -   |   |
| 2 N 3765    |             | Si-P        | =2N3762: 60V, 0,5W                                 | 2a        | TO-46      |          |          | -   |   |
| 2 N 3766    | USA,Fch,Mot | Si-N        | LFS P, 80/60V, 4/4A, 20W, >10MHz, hFE=40...160     | 22a       | TO-66      |          |          | BD 243B, BD 539B, BD 951, 2N3054, ++        |   |
|             | Sgs,Tix     |             |  | (2N3740   |            |          |          |   |   |
| 2 N 3767    |             | Si-N        | =2N3766: 100/80V                                   | (2N3741   | 22a        | TO-66    |          | BD 243C, BD 539C, BD 953, 2N3054, ++        |   |
| 2 N 3770    | Spr         | Ge-P        | HF, 10V, 0,05A, 0,05W, >100MHz                     | 2a        | TO-18      |          |          | AF 106, AF 109R, AF 306, 2N3323...25        |   |
| 2 N 3771    | USA,EUR,Tos | Si-N        | LFS P, 50/40V, 30/30A, 150W, >0,2MHz               | 23a       | TO-3       |          |          | BDX 41, BDX 29, MJ 802, 2SD630...631        |   |
| 2 N 3772    | USA,EUR,Tos | Si-N        | LFS P, 100/60V, 20/30A, 150W, >0,2MHz              | 23a       | TO-3       |          |          | BDX 40, BDX 29, MJ 802, 2SD797              |   |
| 2 N 3773    | USA,EUR,Tos | Si-N        | LFS P, 160/140V, 16/30A, 150W, >0,2MHz             | (2N6609   | 23a        | TO-3     | MJ 15015 | 23a   | BDW 32...36, BDX 50, MJ 15015, 2SC2608      |
| 2 N 3774    | USA,Tix     | Si-P        | LFS, 40/40V, 1A, 5W(Tc=100°), >1MHz, hFE=20...60   | 2a        | TO-5       |          |          | BSS 17...18, BSW 40, BSV 82, 2N5322...23    |   |
| 2 N 3775    |             | Si-P        | =2N3774: 60/60V                                    | 2a        | TO-5       |          |          | BSS 17...18, BSW 40, BSV 82, 2N5322...23    |   |
| 2 N 3776    |             | Si-P        | =2N3774: 80/80V                                    | 2a        | TO-5       |          |          | BSS 17...18, BSW 40, BSV 82, 2N5322...23    |   |
| 2 N 3777    |             | Si-P        | =2N3774: 100/100V                                  | 2a        | TO-5       |          |          | BSS 17, BSW 40, 2N5322                      |   |
| 2 N 3778    | USA,Tix     | Si-P        | =2N3774: hFE=10...40                               | 2a        | TO-5       |          |          | BSS 17...18, BSW 40, BSV 82, 2N5322...23    |   |
| 2 N 3779    |             | Si-P        | =2N3774: 60/60V, hFE=10...40                       | 2a        | TO-5       |          |          | BSS 17...18, BSW 40, BSV 82, 2N5322...23    |   |
| 2 N 3780    |             | Si-P        | =2N3774: 80/80V, hFE=10...40                       | 2a        | TO-5       |          |          | BSS 17...18, BSW 40, BSV 82, 2N5322...23    |   |
| 2 N 3781    |             | Si-P        | =2N3774: 100/100V, hFE=10...40                     | 2a        | TO-5       |          |          | BSS 17, BSW 40, 2N5322                      |   |
| 2 N 3782    | USA,Tix     | Si-P        | =2N3774: 3A, hFE=10...60                           | 2a        | TO-5       |          |          | 2N3719...20, 2N3867...68, 2N4234...36       |   |
| 2 N 3783    | Mot,Ssi     | Ge-P        | UHF, 30V, 0,02A, 0,15W, >800MHz                    | 5g        | TO-72      |          |          | AF 139, AF 239(S), 2N3279...86              |   |
| 2 N 3784    | Mot,Ssi     | Ge-P        | UHF, 30V, 0,02A, 0,15W, >700MHz                    | 5g        | TO-72      |          |          | AF 139, AF 239(S), 2N3279...86              |   |
| 2 N 3785    | Mot,Ssi     | Ge-P        | UHF, 15V, 0,02A, 0,15W, >700MHz                    | 5g        | TO-72      |          |          | AF 139, AF 239(S), 2N3279...86              |   |
| 2 N 3788    | Sol,Ssi,Stc | Si-N        | TV-HA, 400/325V, 2A, 100W                          | 23a       | TO-3       |          |          | BU 104, BU 606, BU 608                      |   |
| 2 N 3789    | USA,Mot,Sgs | Si-P        | LFS P, 60/60V, 10/15A, 150W, >4MHz, hFE=25...90    | 23a       | TO-3       | BD 318   | 23a      | BD546A, BD316, 2N6029...31, 2N6229...31, ++ |   |
|             | Tix,Tos,++  |             | 350/800ns  | (2N3713   |            |          |          |   |   |
| 2 N 3790    |             | Si-P        | =2N3789: 80/80V                                    | (2N3714   | 23a        | TO-3     | BD 318   | 23a   | BD546B, BD318, 2N6029...31, 2N6229...31, ++ |
| 2 N 3791    |             | Si-P        | =2N3789: hFE=50...150                              | (2N3715   | 23a        | TO-3     | BD 318   | 23a   | BD546A, BD316, 2N6029...31, 2N6229...31, ++ |
| 2 N 3792    |             | Si-P        | =2N3789: 80/80V, hFE=50...150                      | (2N3716   | 23a        | TO-3     | BD 318   | 23a   | BD546B, BD318, 2N6029...31, 2N6229...31, ++ |
| 2 N 3793    | USA,Mic,Phi | Si-N        | LF, 40V, 0,3A, 0,25W, 220MHz, hFE=20...150         | =40b      |            |          |          | BC 337, BC 635, BC 637, BC 639, ++          |   |
| 2 N 3794    |             | Si-N        | =2N3793: 100MHz, hFE=100...600                     | =40b      |            |          |          | BC 337, BC 635, BC 637, BC 639, ++          |   |
| 2 N 3795    | Csr,Ssi,Stc | Si-P        | LFS, 120V, 1A, 5W(Tc=25°), >0,5MHz, <5/5μs         | 2a        | TO-5       |          |          | 2N3634...37, 2N5415                         |   |
| 2 N 3796    | Mot         | MOS-N-FET-d | LF, 30V, Idss>0,5mA, Up<4V                         | 2a        | TO-18      |          |          | -   |   |
| 2 N 3797    | Mot         | MOS-N-FET-d | LF, 30V, Idss>2mA, Up<7V                           | 2a        | TO-18      |          |          | -   |   |
| 2 N 3798    | USA,Mot,Tix | Si-P        | Uni, in, 60V, 0,05A, 0,36W, >100MHz, hFE=150...450 | 2a        | TO-18      |          |          | 2SA872(A), 2SA941...942, 2SA970, ++         |   |
| 2 N 3798 A  |             | Si-P        | =2N3798: 90V                                       | 2a        | TO-18      |          |          | 2SA872(A), 2SA941...942, 2SA970, ++         |   |
| 2 N 3799    |             | Si-P        | =2N3798: hFE=300...900                             | 2a        | TO-18      |          |          | 2SA872(A), 2SA941...942, 2SA970, ++         |   |
| 2 N 3799 A  |             | Si-P        | =2N3798: 90V, hFE=300...900                        | 2a        | TO-18      |          |          | 2SA872(A), 2SA941...942, 2SA970, ++         |   |
| 2 N 3800    | Fch,Mot,Nsc | Si-P        | Dual, in, 60/60V, 0,05A, 0,36W, >100MHz, F<3dB(1k) | TO-71     | (EBC-EBC-) |          |          | -   |   |
|             | Ray         |             | hFE=150...450, ΔhFE=, ΔUbe=                        |           |            |          |          |   |   |