

2 N 1145	USA	Ge-P	=2N1144: hfe=45	1a			AC 125...126, AC 151, 2SB54, 2SB56	
2 N 1146	USA	Ge-P	L.F.S P, 40V, 15A, 90W	23a	TO-3		2N1549...60	
2 N 1146 A		Ge-P	=2N1146: 60V	23a	TO-3		2N1550...52, 2N1554...56, 2N1558...60	
2 N 1146 B		Ge-P	=2N1146: 80V	23a	TO-3		2N1551...52, 2N1555...56, 2N1559...60	
2 N 1146 C		Ge-P	=2N1146: 100V	23a	TO-3		2N1552, 2N1556, 2N1560	
2 N 1147	USA	Ge-P	L.F.S P, 40V, 15A, 90W	23a	TO-3		2N1549...60	
2 N 1147 A		Ge-P	=2N1147: 60V	23a	TO-3		2N1550...52, 2N1554...56, 2N1558...60	
2 N 1147 B		Ge-P	=2N1147: 80V	23a	TO-3		2N1551...52, 2N1555...56, 2N1559...60	
2 N 1147 C		Ge-P	=2N1147: 100V	23a	TO-3		2N1552, 2N1556, 2N1560	
2 N 1149	USA	Si-N	Uni, 45V, 0,025A, 0,15W, 12MHz	=1a	TO-22		BC 167, BC 182, BC 237, BC 547, ++	
2 N 1150	USA	Si-N	Uni, 45V, 0,025A, 0,15W, 13MHz	=1a	TO-22		BC 167, BC 182, BC 237, BC 547, ++	
2 N 1151	USA	Si-N	Uni, 45V, 0,025A, 0,15W, 14MHz	=1a	TO-22		BC 167, BC 182, BC 237, BC 547, ++	
2 N 1152	USA	Si-N	Uni, 45V, 0,025A, 0,15W, 15MHz	=1a	TO-22		BC 167, BC 182, BC 237, BC 547, ++	
2 N 1153	USA	Si-N	Uni, 45V, 0,025A, 0,15W, 16MHz	=1a	TO-22		BC 167, BC 182, BC 237, BC 547, ++	
2 N 1154	USA	Si-N	Uni, 50V, 0,06A, 0,75W, 1MHz	=1a	TO-22		BC 140...141, BC 300...302, 2N3053, ++	
2 N 1155	USA	Si-N	=2N1154: 80V, 0,05A	=1a	TO-22		BC 140...141, BC 300...301, 2N1889...90, ++	
2 N 1156	USA	Si-N	=2N1154: 120V, 0,04A	=1a	TO-22		BC 300, 2N1883(A), 2N2102, 2N2405, ++	
2 N 1157	USA	Ge-P	S P, 60V, 40A, 187W	=49m			-	
2 N 1157 A	USA	Ge-P	=2N1157: 80V	=49m			-	
2 N 1158(A)	Csr,Etc	Ge-P	HF, 20V, 0,1A, 0,06...0,075W	2a	TO-9		-	
2 N 1159	USA	Ge-P	L.F.S P, 80V, 5A, 90W	23a	TO-3		AL 102...103, AUY 22, 2N3615...18, ++	
2 N 1160	USA	Ge-P	=2N1159: 7A	23a	TO-3		AL 102...103, AUY 22, 2N3615...18, ++	
2 N 1162(A)	USA,Mot	Ge-P	L.F.S P, 50V, 25A, 106W	23a	TO-3		2N1651...53, 2N2285...87	
2 N 1163(A)	USA,Mot	Ge-P	L.F.S P, 50V, 25A, 106W	23a	TO-3		2N1651...53, 2N2285...87	
2 N 1164(A)	USA,Mot	Ge-P	L.F.S P, 80V, 25A, 106W	23a	TO-3		2N1652...53, 2N2286...87	
2 N 1165(A)	USA,Mot	Ge-P	L.F.S P, 80V, 25A, 106W	23a	TO-3		2N1652...53, 2N2286...87	
2 N 1166(A)	USA,Mot	Ge-P	L.F.S P, 100V, 25A, 106W	23a	TO-3		2N1653, 2N2287	
2 N 1167(A)	USA,Mot	Ge-P	L.F.S P, 100V, 25A, 106W	23a	TO-3		2N1653, 2N2287	
2 N 1168	USA	Ge-P	L.F.S P, 50V, 5A, 45W	23a	TO-3		AL 102...103, AUY 22, 2N1545...48, ++	
2 N 1169	Csr,Sty	Ge-N	L.F.S,Chopper, 40V, 0,4A, 0,12W	2a	TO-5		-	
2 N 1170	Csr,Sty	Ge-N	L.F.S,Chopper, 40V, 0,4A, 0,12W	2a	TO-5		-	
2 N 1171	Mot	Ge-P	L.F.S, 30V, 0,4A, 0,17W, >10MHz	2a	TO-5		AC 128, AC 152...153, ASY 26, ASY 76...77	
2 N 1172	USA	Ge-P	L.F.S, 40V, 1,5A(ss), 5W	43m	TO-37		(AD 162) <sup>4</sup>	
2 N 1173	Wes	Ge-N	L.F.S, 35V, 0,2A, 0,25W	2a	TO-29		-	
2 N 1174	Wes	Ge-P	L.F.S, 35V, 0,2A, 0,25W	2a	TO-29		-	
2 N 1175(A)	USA,Mot	Ge-P	L.F.S, 35V, 0,5A, 0,225W, 4,2MHz	2a(β-case)	TO-5		AC 128, AC 152...153, ASY 76...77	
2 N 1176	USA	Ge-P	LF, 10V, 0,3A, 0,3W	2a	TO-5		AC 128, AC 152...153, 2SB324, 2SB415	
2 N 1176 A		Ge-P	=2N1176: 40V	2a	TO-5		ASY 48, ASY 76...77, 2SB405ST	
2 N 1176 B		Ge-P	=2N1176: 60V	2a	TO-5		ASY 48, ASY 77	
2 N 1177	Can,Rca,Sgs	Ge-P	HF, 40V, 10mA, 0,08W, 140MHz	1g	TO-7		AF 106, AF 109R, AF 306	
2 N 1178	Can,Rca,Sgs	Ge-P	HF, 40V, 10mA, 0,08W, 140MHz	1g	TO-7		AF 106, AF 109R, AF 306	
2 N 1179	Can,Rca,Sgs	Ge-P	HF, 40V, 10mA, 0,08W, 140MHz	1g	TO-7		AF 106, AF 109R, AF 306	
2 N 1180	Can,Rca,Sgs	Ge-P	HF, 40V, 10mA, 0,08W, 100MHz	1g	TO-7		AF 106, AF 109R, AF 306	
2 N 1182	Can,Gpd	Ge-P	L.F.S P, -60V, 5A, 106W	23a	TO-3		2N1541...43, 2N1546...48, 2N3615...18, ++	
2 N 1183	Gpd,Stc	Ge-P	L.F.S P, 45V, 3A, 7,5W, hFE>20	2a	TO-8		AUY 18	
2 N 1183 A		Ge-P	=2N1183: 60V	2a	TO-8		AUY 18	
2 N 1183 B		Ge-P	=2N1183: 80V	2a	TO-8		AUY 18	
2 N 1184	Gpd,Stc	Ge-P	L.F.S P, 45V, 3A, 7,5W, hFE=40	2a	TO-8		AUY 18	
2 N 1184 A		Ge-P	=2N1184: 60V	2a	TO-8		AUY 18	
2 N 1184 B		Ge-P	=2N1184: 80V	2a	TO-8		AUY 18	
2 N 1185	USA,Mot	Ge-P	L.F.S, 45V, 0,5A, 0,2W, 3MHz, hfe>190	2a	TO-5		ASY 76...77	
2 N 1186	USA,Mot	Ge-P	L.F.S, 60V, 0,5A, 0,2W, 1,5MHz, hfe>30	2a	TO-5		ASY 77	
2 N 1187	USA,Mot	Ge-P	L.F.S, 60V, 0,5A, 0,2W, 2MHz, hfe>50	2a	TO-5		ASY 77	
2 N 1188	USA,Mot	Ge-P	L.F.S, 60V, 0,5A, 0,2W, 2,5MHz, hfe>100	2a	TO-5		ASY 77	
2 N 1189	USA,Mot	Ge-P	L.F.S, 45V, 0,5A, 0,2W, 3,5MHz, hfe>75	2a	TO-5		ASY 76...77, 2SB405ST	
2 N 1190	USA,Mot	Ge-P	L.F.S, 45V, 0,5A, 0,2W, 4,5MHz, hfe>125	2a	TO-5		ASY 76...77, 2SB405ST	
2 N 1191	USA,Mot	Ge-P	L.F.S, 40V, 0,2A, 0,2W, 1,5MHz, hfe>30	2a	TO-5	AC 151	2a	ASY 48, ASY 76...77, 2SB56A
2 N 1192	USA,Mot	Ge-P	L.F.S, 40V, 0,2A, 0,2W, 2MHz, hfe>50	2a	TO-5	AC 151	2a	ASY 48, ASY 76...77, 2SB56A
2 N 1193	USA,Mot	Ge-P	L.F.S, 40V, 0,2A, 0,2W, 2,5MHz, hfe>100	2a	TO-5	AC 151	2a	ASY 48, ASY 76...77, 2SB56A
2 N 1194	USA,Mot	Ge-P	L.F.S, 40V, 0,2A, 0,2W, 3MHz, hfe>190	2a	TO-5	AC 151	2a	ASY 48, ASY 76...77, 2SB56A
2 N 1195	Mot,Spe	Ge-P	UHF, 30V, 0,04A, 0,225W, >1200MHz	2a	TO-5		2N1141...43	
2 N 1196	USA	Si-P	Uni, 70V, 0,1A, 0,35	2a	TO-5		BC 212, BC 256, BC 266, BC 556, ++	
2 N 1197	USA	Si-P	Uni, 70V, 0,1A, 0,35	2a	TO-5		BC 212, BC 256, BC 266, BC 556, ++	
2 N 1198	USA	Ge-N	L.F.S, 25V, 0,075A, 0,065W, 9MHz	=1a	TO-22		ASY 28...29, ASY 73...75	
2 N 1199(A)	Etc,Phc	Si-N	HF/S, 20V, 0,1A, 0,15W, 125MHz	2a	TO-9		BSV 89...92, BSX 92...93, 2N2368...69(A), ++	
2 N 1200	Phc	Si-N	HF, 20V, 0,1A, 0,1W, 4,3MHz	2a	TO-9		BC 168, BC 183, BC 238, BC 548, ++	
2 N 1201	Phc	Si-N	=2N1200: 12MHz	2a	TO-9		BC 168, BC 183, BC 238, BC 548, ++	
2 N 1202	USA	Ge-P	S P, 80V, 3,5A, 34W	=37b			-	
2 N 1203	USA	Ge-P	=2N1202: 120V	=37b			-	
2 N 1204(A)	USA,Mot	Ge-P	S, 20V, 0,5A, 0,3W, 200MHz	2a	TO-9		2N1495, 2N2099...2100	
2 N 1205	USA	Si-N	Uni, 20V, 0,15W, >17MHz	2a	TO-5		BC 168, BC 183, BC 238, BC 548, ++	
2 N 1206	USA	Si-N	L.F.S, 60V, 0,15A, 3W(Tc=100°), >10MHz	2a	TO-5		BC 140...141, BC 300...302, 2N3053, ++	
2 N 1207	USA	Si-N	=2N1206: 125V	2a	TO-5		BC 300, 2N1893(A), 2SC959, 2SC2108, ++	
2 N 1208(I)	USA	Si-N	S P, 60V, 5A, 45...80W	49m	TO-61		2N3487...92	
2 N 1209(I)	USA	Si-N	S P, 45V, 5A, 45...80W	49m	TO-61		2N3487...92	
2 N 1210(I)	USA	Si-N	S P, 60V, 5A, 45...80W		TO-53		2N1722...23	
2 N 1211(I)	USA	Si-N	S P, 80V, 5A, 45...80W		TO-53		2N1722...23	
2 N 1212(I)	USA	Si-N	S P, 60V, 5A, 45...80W		TO-61		2N3487...92	
2 N 1217	Csr,Etc	Ge-N	L.F.S, 20V, 0,025A, 0,075W, 9MHz	=1a	TO-22		-	
2 N 1218	USA	Ge-N	L.F.S P, 45V, 3A, 20W	23a	TO-3		-	
2 N 1219	USA	Si-P	Uni, 30V, 0,1A, 0,25W, >5MHz	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1220	USA	Si-P	Uni, 30V, 0,1A, 0,25W, >2MHz	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1221	USA	Si-P	Uni, 30V, 0,1A, 0,25W	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1222	USA	Si-P	Uni, 30V, 0,1A, 0,25W, >2MHz	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1223	USA	Si-P	Uni, 40V, 0,1A, 0,25W, 2MHz	2a	TO-5		(BC 212, BC 257, BC 307, BC 557,++)	
2 N 1224	USA	Ge-P	HF, 40V, 10mA, 0,12W, 30MHz	5g	TO-33		AF 124...126, AF 200	
2 N 1225	USA	Ge-P	HF, 40V, 10mA, 0,12W, 100MHz	5g	TO-33		AF 124...125, AF 200	
2 N 1226	USA	Ge-P	HF, 60V, 10mA, 0,12W, 30MHz	5g	TO-33		AF 118	
2 N 1227	USA	Ge-P	L.F.S P, 35V, 3A, 50W	23a	TO-3		AD 149, AUY 19...20, 2N2144...46, ++	
2 N 1228	USA	Si-P	Uni, 15V, 0,1A, 0,4W, 1,2MHz, hfe>14	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1229	USA	Si-P	=2N1228: hfe>28	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1230	USA	Si-P	Uni, 35V, 0,1A, 0,4W, 1,2MHz, hfe>14	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	
2 N 1231	USA	Si-P	=2N1230: hfe>28	2a	TO-5		(BC 213, BC 258, BC 308, BC 558,++)	