

| TRANSISTOR NUMBER | PM OA LT | PACK-AGE | LEAD INFO | VCB MAX | VCE MAX | VEB MAX | I C MAX | T J MAX | P TOT | F T MIN | C OB MAX | H FE | H FE BIAS | USE MFR | EUR EQUIV | USA EQUIV | ISS | |
|-------------------|----------|----------|-----------|---------|---------|---------|---------|---------|--------|---------|----------|--------|-----------|---------|-----------|-----------|--------|---|
| BC315 | PS | X10 | L20 | 45V | 35V | 5V | 100MA | 150C | 300MWF | 200M | 10P | 100MN | 2MA | ALN | TIB | BC309 | 2N6003 | 0 |
| BC315A | PS | X10 | L20 | 45V | 35V | 5V | 100MA | 150C | 300MWF | 200M | 10P | 125MN | 2MA | ALN | TIB | BC309 | 2N6003 | 2 |
| BC315B | PS | X10 | L20 | 45V | 35V | 5V | 100MA | 150C | 300MWF | 200M | 10P | 200MN | 2MA | ALN | TIB | BC309 | 2N6003 | 2 |
| BC317 | NS | T092 | L14 | 50V | 45V | 6V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC167 | 2N5209 | 0 |
| BC317A | NS | T092 | L14 | 50V | 45V | 6V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC167 | 2N5209 | 0 |
| BC317B | NS | T092 | L14 | 50V | 45V | 6V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALG | MOU | BC167 | 2N5209 | 0 |
| BC318 | NS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC167 | 2N5209 | 0 |
| BC318A | NS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC167 | 2N5209 | 0 |
| BC318B | NS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALG | MOU | BC167 | 2N5209 | 0 |
| BC318C | NS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 400MN | 2MA | ALG | MOU | BC169 | 2N5210 | 0 |
| BC319 | NS | T092 | L14 | 30V | 20V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALN | MOU | BC169 | 2N5210 | 0 |
| BC319B | NS | T092 | L14 | 30V | 20V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALN | MOU | BC169 | 2N5210 | 0 |
| BC319C | NS | T092 | L14 | 30V | 25V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 400MN | 2MA | ALN | MOU | BC169 | 2N5210 | 0 |
| BC320 | PS | T092 | L14 | 50V | 45V | 6V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC320 | 2N5086 | 0 |
| BC320A | PS | T092 | L14 | 50V | 45V | 6V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC320 | 2N5086 | 0 |
| BC320B | PS | T092 | L14 | 50V | 45V | 6V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALG | MOU | BC320 | 2N5086 | 0 |
| BC321 | PS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC320 | 2N5086 | 0 |
| BC321A | PS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALG | MOU | BC320 | 2N5086 | 0 |
| BC321B | PS | T092 | L14 | 40V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALG | MOU | BC320 | 2N5086 | 0 |
| BC321C | PS | T092 | L14 | 45V | 30V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 400MN | 2MA | ALN | MOU | BC352B | 2N5086 | 2 |
| BC322 | PS | T092 | L14 | 30V | 20V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 110MN | 2MA | ALN | MOU | BC322 | 2N5087 | 0 |
| BC322B | PS | T092 | L14 | 30V | 20V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 200MN | 2MA | ALN | MOU | BC322 | 2N5087 | 0 |
| BC322C | PS | T092 | L14 | 30V | 20V | 5V | 150MA | 135C | 310MWF | 100M | 4P | 400MN | 2MA | ALN | MOU | BC322 | 2N5087 | 0 |
| BC323 | NS | T039 | L04 | 100V | 60V | 5V | 5A | 200C | 800MWF | 50M | 80P | 50MN | 500MA | AMG | SGI | BFY50 | 2N2297 | 0 |
| BC324 | NS | T039 | L04 | 85V | 55V | 5V | 1A | 200C | 800MWF | 50M | 40P | 20MN | 500MA | AMG | SGI | BFY50 | 2N2297 | 0 |
| BC325 | PS | T018 | L01 | 60V | 60V | 6V | 50MA | 200C | 360MWF | 100M | 9P | 40MN | 10UA | ALA | TIB | BCY71 | 2N3965 | 2 |
| BC326 | PS | T018 | L01 | 60V | 60V | 6V | 50MA | 200C | 360MWF | 100M | 9P | 100MN | 10UA | ALA | TIB | BCY71 | 2N3965 | 2 |
| BC327 | PS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 63MN | 100MA | AMG | SID | BC327 | 2N5819 | 0 |
| BC327AP | PS | T092 | L74 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 100MN | 100MA | AMG | FEB | BC32716 | 2N5819 | 2 |
| BC327BP | PS | T092 | L74 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 160MN | 100MA | AMG | FEB | BC32725 | 2N5819 | 2 |
| BC327CP | PS | T092 | L74 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 250MN | 100MA | AMG | FEB | BC32740 | 2N5819 | 2 |
| BC327/01 | PS | X09 | L10 | 45V | 45V | 6V | 500MA | 125C | 400MWF | 50M | 15P | 100MN | 100MA | AMG | OBS | BSY59 | 2N6014 | 2 |
| BC327/10 | PS | T092 | L74 | 50V | 45V | 5V | 1A | 150C | 500MWF | 50M | 24P | 67/150 | 100MA | AMG | SID | BC327 | 2N6014 | 2 |
| BC327/16 | PS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 100MN | 100MA | AMG | SID | BC327 | 2N5819 | 2 |
| BC327/25 | PS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 160MN | 100MA | AMG | SID | BC327 | 2N5819 | 2 |
| BC327/40 | PS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 250MN | 100MA | AMG | SID | BC327 | 2N5819 | 0 |
| BC328 | PS | X10 | L20 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 63MN | 100MA | AMG | SID | BC327 | 2N5819 | 0 |
| BC328AP | PS | T092 | L74 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 100MN | 100MA | AMG | FEB | BC32816 | 2N5819 | 2 |
| BC328BP | PS | T092 | L74 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 160MN | 100MA | AMG | FEB | BC32825 | 2N5819 | 2 |
| BC328CP | PS | T092 | L74 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 250MN | 100MA | AMG | FEB | BC32840 | 2N5819 | 2 |
| BC328/01 | PS | X09 | L10 | 25V | 25V | 5V | 500MA | 125C | 400MWF | 50M | 15P | 100MN | 100MA | AMG | OBS | BSY59 | 2N6014 | 2 |
| BC328/10 | PS | T092 | L74 | 30V | 25V | 5V | 1A | 150C | 500MWF | 50M | 24P | 67/150 | 100MA | AMG | SID | BC327 | 2N6014 | 2 |
| BC328/16 | PS | X10 | L20 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 100MN | 100MA | AMG | SID | BC327 | 2N5819 | 0 |
| BC328/25 | PS | X10 | L20 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 160MN | 100MA | AMG | SID | BC327 | 2N5819 | 0 |
| BC328/40 | PS | X10 | L20 | 30V | 25V | 5V | 800MA | 150C | 500MWF | 60M | 18P | 250MN | 100MA | AMG | SID | BC327 | 2N5819 | 0 |
| BC329 | NS | T092 | L74 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 6P | 240MN | 2MA | ALN | TIW | BC239 | 2N5827 | 1 |
| BC329B | NS | X10 | L20 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 6P | 220MN | 2MA | ALN | TIW | BC239 | 2N5827 | 0 |
| BC329C | NS | X10 | L20 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 220MN | 2MA | ALN | TIW | BC239 | 2N5827 | 0 |
| BC330 | NS | T092 | L74 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 6P | 220MN | 2MA | ALN | TIW | BC239 | 2N5827 | 1 |
| BC330B | NS | X10 | L20 | 45V | 45V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 220MN | 2MA | ALN | TIW | BC239 | 2N5827 | 0 |
| BC330C | NS | X10 | L20 | 45V | 45V | 6X | 30MA | 150C | 220MWF | 100M | 3P | 220FG | 2MA | ALN | TIW | BC239 | 2N5827 | 0 |
| BC331 | NS | T092 | L74 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 125MN | 2MA | ALN | TIW | BC239 | 2N5827 | 1 |
| BC331A | NS | X10 | L20 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MN | 2MA | ALG | TIW | BC237 | 2N5825 | 0 |
| BC331B | NS | X10 | L20 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MN | 2MA | ALG | TIW | BC237 | 2N5825 | 0 |
| BC331C | NS | X10 | L20 | 60V | 60V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MN | 2MA | ALG | TIW | BC237 | 2N5825 | 0 |
| BC332 | NS | T092 | L74 | 45V | 45V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MN | 2MA | ALN | TIW | BC239 | 2N5827 | 1 |
| BC332A | NS | X10 | L20 | 45V | 45V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MN | 2MA | ALG | TIW | BC237 | 2N2825 | 0 |
| BC332B | NS | X10 | L20 | 45V | 45V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MW | 2MA | ALG | TIW | BC237 | 2N2825 | 0 |
| BC332C | NS | X10 | L20 | 45V | 45V | 6V | 30MA | 150C | 250MWF | 100M | 3P | 100MN | 2MA | ALG | TIW | BC237 | 2N5825 | 0 |
| BC333 | NS | T092 | L14 | 25V | 25V | 5V | 50MA | 135C | 310MWF | 50M | 4P | 100MN | 100UA | ALG | MOB | BC320 | 2N5086 | 0 |
| BC334 | PS | T092 | L14 | 25V | 25V | 5V | 50MA | 135C | 310MWF | 50M | 4P | 100MN | 100UA | ALG | MOB | BC320 | 2N5286 | 0 |
| BC335 | NS | T092 | L14 | 25V | 25V | 5V | 50MA | 135C | 310MWF | 50M | 4P | 100MN | 100UA | ALN | MOB | BC322 | 2N5087 | 0 |
| BC336 | PS | T092 | L14 | 25V | 25V | 5V | 50MA | 135C | 310MWF | 50M | 4P | 100MN | 100UA | ALN | MOB | BC322 | 2N5087 | 0 |
| BC337 | NS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 100MN | 100MA | AMG | SID | BC337 | 2N5818 | 0 |
| BC337AP | NS | T092 | L74 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 100MN | 100MA | AMG | FEB | BC33716 | 2N6016 | 2 |
| BC337BP | NS | T092 | L74 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 160MN | 100MA | AMG | FEB | BC33725 | 2N6016 | 2 |
| BC337CP | NS | T092 | L74 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 250MN | 100MA | AMG | FEB | BC33740 | 2N6016 | 2 |
| BC337/01 | NS | X09 | L10 | 45V | 45V | 6V | 500MA | 150C | 400MWF | 50M | 20P | 100MN | 100MA | AMG | OBS | BFW87 | 2N6220 | 2 |
| BC337/10 | NS | T092 | L74 | 50V | 45V | 5V | 1A | 150C | 500MWF | 50M | 24P | 67/150 | 100MA | AMG | SID | BC487B | 2N6220 | 2 |
| BC337/16 | NS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 100MN | 100MA | AMG | SID | BC337 | 2N5818 | 0 |
| BC337/25 | NS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 160MN | 100MA | AMG | SID | BC337 | 2N5818 | 0 |
| BC337/40 | NS | X10 | L20 | 50V | 45V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 250MN | 100MA | AMG | SID | BC337 | 2N5818 | 0 |
| BC338 | NS | X10 | L20 | 30V | 20V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 100MN | 100MA | AMG | SID | BC337 | 2N5818 | 0 |
| BC338AP | NS | T092 | L74 | 30V | 20V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 100MN | 100MA | AMG | FEB | BC33740 | 2N6016 | 2 |
| BC338BP | NS | T092 | L74 | 30V | 20V | 5V | 800MA | 150C | 360MWF | 60M | 20P | 160MN | 100MA | AMG | FEB | BC33740 | 2N6016 | 2 |