

2 N 6437		Si-P	=2N6436: 120/100V	I2N6338	23a	TO-3			2N6378...79
2 N 6438		Si-P	=2N6436: 140/120V	I2N6339	23a	TO-3			2N6379
2 N 6439	Mot	Si-N	VHF/UHF P, 60/33V, PQ=60W(400MHz)		57s	SOT-119			MRF 327, 2SC2186, 2SC2796
2 N 6441	Mot,Isi	Si-N	Dual, 60/45V, 0.01A, 0.55W, >160MHz, hFE=60...240 F<4dB(1kHz), ΔhFE=0.6...1, ΔUbe<10mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6442		Si-N	=2N6441: hFE=120...600		TO-77	(CBE-EBC-)			2N3409...11
2 N 6443		Si-N	=2N6441: ΔhFE=0.8...1, ΔUbe<5mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6444		Si-N	=2N6441: hFE=120...600, ΔhFE=0.8...1, ΔUbe<5mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6445		Si-N	=2N6441: ΔhFE=0.9...1, ΔUbe<3mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6446		Si-N	=2N6441: hFE=120...600, ΔhFE=0.9...1, ΔUbe<3mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6447		Si-N	=2N6441: ΔhFE=0.95...1, ΔUbe<3mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6448		Si-N	=2N6441: hFE=120...600, ΔhFE=0.95...1, ΔUbe<3mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 6449	Tdy,Tix	N-FET	Uni, 300V, Idss>2mA, Up<15V		2b	TO-39			-
2 N 6450	Tdy,Tix	N-FET	Uni, 200V, Idss>2mA, Up<15V		2b	TO-39			-
2 N 6451	Tix	N-FET	Uni, In, 20V, Idss>5mA, Up<3.5V		5k	TO-72			BC 264, BF 410C, 2SK147, 2SK168
2 N 6452	Tix	N-FET	Uni, In, 25V, Idss>5mA, Up<3.5V		5k	TO-72			BC 264, BF 410C, 2SK147, 2SK168
2 N 6453	Tix	N-FET	Uni, In, 20V, Idss>15mA, Up<5V		5k	TO-72			BF 256B, BF 348, BFT 10A,B, 2N5397
2 N 6454	Tix	N-FET	Uni, In, 25V, Idss>15mA, Up<5V		5k	TO-72			BF 256B, BF 348, BFT 10A,B, 2N5397
2 N 6455	Ppc	Si-N	HF P, 45/25V, 7A, 60W, >75MHz		55r	SOT-120			-
2 N 6456	Ppc	Si-N	HF P, 45/25V, 12A, 75W, >60MHz		55r	SOT-120			-
2 N 6457	Ppc	Si-N	HF P, 45/25V, 20A, 140W, >50MHz		55r	SOT-147			-
2 N 6458	Ppc	Si-N	HF P, 45/25V, 7A, 75W, >75MHz		59r	SOT-121			-
2 N 6459	Ppc	Si-N	HF P, 45/25V, 12A, 120W, >60MHz		59r	SOT-121			-
2 N 6460	Ppc	Si-N	HF P, 45/25V, 20A, 140W, >50MHz		59r	SOT-121			-
2 N 6461	Ssi,Tix	Si-N	Vid, 300/300V, 0.1A, 1W, >200MHz, hFE=30...120		2a	TO-39			BF 259, BF 659, BFS 89, 3N5058
2 N 6462		Si-N	=2N6461: hFE=100...300		2a	TO-39			BF 259, BF 659, BFS 89, 3N5058
2 N 6463		Si-N	=2N6461: 250/250V		2a	TO-39			BF 258...259, BF 658...659, 2N5058...59, ++
2 N 6464		Si-N	=2N6461: 250/250V, hFE=100...300		2a	TO-39			BF 258...259, BF 658...659, 2N5058...59, ++
2 N 6465	Ker,Stc,Stc	Si-N	LFS P, 110/100V, 4A, 40W, >5MHz	I2N6467	22a	TO-66			BD 243C, BD 539D, BD 955, 2SD961, ++
2 N 6466		Si-N	=2N6465: 130/120V	I2N6468	22a	TO-66			BD 243D, 2SC2516, 2SD961
2 N 6467	Ker,Rca,Stc	Si-P	LFS P, 110/100V, 4A, 40W, >5MHz	I2N6465	22a	TO-66			BD 244C, BD 540D, BD 956, 2SB869, ++
2 N 6468		Si-P	=2N6467: 130/120V	I2N6466	22a	TO-66			BD 244D, 2SB869
2 N 6469	USA,Rca,Tix	Si-P	LFS P, 50/40V, 15A, 125W, >10MHz	I2N6470	23a	TO-3	BD 318	23a	BD 316, BD 546A, MJ 2955, 2N5879...80, ++
2 N 6470	USA,Rca,Tix	Si-N	LFS P, 50/40V, 15A, 125W, >5MHz	I2N6469	23a	TO-3	BD 317	23a	BD 315, BD 545A, 2N3055, 2N5881...82, ++
2 N 6471		Si-N	=2N6470: 70/60V	I2N6246	23a	TO-3	BD 317	23a	BD 315, BD 545B, 2N3055, 2N5881...82, ++
2 N 6472		Si-N	=2N6470: 90/80V	I2N6247	23a	TO-3	BD 317	23a	BD 317, BD 545C, 2N3055, 2N5882, ++
2 N 6473	USA,Nsc,Rca	Si-N	=2N6465:	I2N6475	17j	TO-220			*2N6465
2 N 6474	USA,Nsc,Rca	Si-N	=2N6466:	I2N6476	17j	TO-220			*2N6466
2 N 6475	USA,Nsc,Rca	Si-P	=2N6467:	I2N6473	17j	TO-220			*2N6467
2 N 6476	USA,Nsc,Rca	Si-P	=2N6468:	I2N6474	17j	TO-220			*2N6468
2 N 6477	Rca	Si-N	LFS P, 140/130V, 2.5/4A, 50W, >0.2MHz, hFE=25...150		17j	TO-220			BD 241D, BD 941, 2SC2516
2 N 6478(A)		Si-N	=2N6477: 160/150V, A: hFE=30...120		17j	TO-220			BD 241D
2 N 6479	Rca	Si-N	S P, RadH, 100/60V, 12/25A, 87W, >100MHz, -/ <1μs						-
2 N 6480	Rca	Si-N	=2N6479: RadH, 100/80V						-
2 N 6481	Rca	Si-N	=2N6479: RadH, 117W						-
2 N 6482	Rca	Si-N	=2N6479: RadH, 100/80V, 117W						-
2 N 6483	Isi,Nsc,Sol	N-FET	Dual, 50V, Idss=0.5...7.5mA, Up=0.7...4V, Ur<5nV(1kHz), ΔIdss=0.95...1, ΔUgs<5mV		TO-71	(SDG-SDG-)			-
2 N 6484		N-FET	=2N6483: ΔUgs<10mV		TO-71	(SDG-SDG-)			-
2 N 6485		N-FET	=2N6483: ΔUgs<15mV		TO-71	(SDG-SDG-)			-
2 N 6486	Fch,Mot,Nsc Rca,Sgs	Si-N	LFS P, 50/40V, 15A, 75W, >5MMHz	I2N6489	17j	TO-220			BD 743A, BD 907, BDT 81
2 N 6487		Si-N	=2N6486: 70/60V	I2N6490	17j	TO-220			BD 743B, BD 909, BDT 83
2 N 6488		Si-N	=2N6486: 90/80V	I2N6491	17j	TO-220			BD 743C, BD 911, BDT 85
2 N 6489	=2N6486	Si-P	LFS P, 50/40V, 15A, 75W, >5MHz	I2N6486	17j	TO-220			BD 744A, BD 908, BDT 82
2 N 6490		Si-P	=2N6489: 70/60V	I2N6487	17j	TO-220			BD 744B, BD 910, BDT 84
2 N 6491		Si-P	=2N6489: 90/80V	I2N6488	17j	TO-220			BD 744C, BD 912, BDT 86
2 N 6492	Mot	Si-N-Darl	LFS P, 55/45V, 15A, 100W, hFE=500...5000		23a	TO-3			BDV 67, BDW 83A, BDX 67, MJ 4033, ++
2 N 6493	Mot	Si-N-Darl	LFS P, 100/70V, 15A, 100W, hFE=500...5000		23a	TO-3			BDV 67A, BDW 83C, BDX 67B, MJ 4035, ++
2 N 6494	Mot	Si-N-Darl	LFS P, 100/80V, 15A, 100W, hFE=500...5000		23a	TO-3			BDV 67A, BDW 83C, BDX 67B, MJ 4035, ++
2 N 6495	USA,Mot,Tix	Si-N	S P, 150/80V, 10/20A, 70W, >25MHz, <350/350ns		22a	TO-66			BUS 36...37, BUV 27(A), 2SC2867
2 N 6496	Ker,Rcs,Sgs Stc,Tix,Uni	Si-N	S P, 150/110V, 15A, 140W, >60MHz, -/ <2μs		23a	TO-3			BUW 57...58, BUX 41, 2SD552, 2SD583, ++
2 N 6497	Mot,Sgs	Si-N	LFS P, 350/250V, 5/10A, 80W, >5MHz, -/ <1950ns		17j	TO-220			BUT 56(A), MJE 51T...53T, 2SC2907, ++
2 N 6498		Si-N	=2N6497: 400/300V		17j	TO-220			BUT 56(A), MJE 52T...53T, 2SC2907, ++
2 N 6499		Si-N	=2N6497: 450/350V		17j	TO-220			BUT 56(A), MJE 53T, 2SC3056, ++
2 N 6500	USA,Rca,Tix	Si-N	S P, 120/90V, 4/5A, 35W, >60MHz, <440/1500ns		22a	TO-66			BDV 10...12, BUX 77, 2SC2767, 2SD772, ++
2 N 6501	Mot	Si-N	4x NPN, 80/40V, 1A, 0.6W, >250MHz, <35/60		14-FLP	TO-86			-
2 N 6502	Mot,Sgs	Si-N	=2N6501: Dual		TO-77	(CBE-EBC-)			-
2 N 6503	Mot,Sgs	Si-N	=2N6501: Dual		10-FLP	TO-89			-
2 N 6504	Mot	50Hz-Thy	50V, 16A(Tc=25°), 25A=, Igt/Ih<40/<40mA		17e	TO-220			MCR 69-2
2 N 6505		50Hz-Thy	=2N6504: 100V		17e	TO-220			MCR 69-3
2 N 6506		50Hz-Thy	=2N6504: 200V		17e	TO-220			-
2 N 6507		50Hz-Thy	=2N6504: 400V		17e	TO-220			-
2 N 6508		50Hz-Thy	=2N6504: 600V		17e	TO-220			-
2 N 6509		50Hz-Thy	=2N6504: 800V		17e	TO-220			-
2 N 6510	USA,Rca	Si-N	S P, 250/200V, 7A, 120W, >3MHz		23a	TO-3			BUX 18(A...C), BUX 43...44, 2SC3041, ++
2 N 6511		Si-N	=2N6510: 300/250V		23a	TO-3			BUX 18(A...C), BUX 43...44, 2SC3041, ++
2 N 6512		Si-N	=2N6510: 350/300V		23a	TO-3			BUX 18A...C, BUX 43...44, 2SC3041, ++
2 N 6513		Si-N	=2N6510: 400/350V		23a	TO-3			BUX 18B...C, BUX 43...44, 2SC3041, ++
2 N 6514		Si-N	=2N6510: 350/300V		23a	TO-3			BUX 18A...C, BUX 43...44, 2SC3041, ++
2 N 6515	Mot	Si-N	LFS,Vid, 250/250V, 0.5A, 0.625W, >40MHz, <200/3500ns	I2N6518	7e	TO-92	BF 420 A	7c	BF 422A, BF 393...393, BFP 25, MPS-A42, ++
2 N 6516		Si-N	=2N6515: 300/300V	I2N6519	7e	TO-92	BF 420 A	7c	BF420A, BF 393, BFP 25, MPS-A42, 2SD1350
2 N 6517		Si-N	=2N6515: 350/350V	I2N6520	7e	TO-92			2SD1350
2 N 6518	Mot	Si-P	LFS,Vid, 250/250V, 0.5A, 0.625W, >40MHz, <200/3500ns	I2N6515	7e	TO-92	BF 421 A	7c	BF 421A, BF 492...493, BFP 26, MPS-A92, ++
2 N 6519		Si-P	=2N6518: 300/300V	I2N6516	7e	TO-92	BF 421 A	7c	BF421A, BF 493, BFP 26, MPS-A92, 2SB1074
2 N 6520		Si-P	=2N6518: 350/350V	I2N6517	7e	TO-92			BF 493S, 2SB1074
2 N 6521	Mot	Si-P-Darl	60/40V, 1A, 0.7W, >175MHz, hFE=10k...25k		5	TO-12			-
2 N 6522		Si-P-Darl	=2N6521: hFE=20k...50k		5	TO-12			-
2 N 6523	Mws	Si-N	HF P, 40V, 0.6A, 5W		62a				-
2 N 6524	Mws	Si-N	HF P, 40V, 1.2A, 10W		62a				-