

2 N 5061	50Hz-Thy	=2N5060: 60V	7n	BRX 49	7a
2 N 5062	50Hz-Thy	=2N5060: 100V	7n	BRX 49	7a
2 N 5063	50Hz-Thy	=2N5060: 150V	7n	BRX 49	7a
2 N 5064	50Hz-Thy	=2N5060: 200V	7n	BRX 49	7a
2 N 5067	Si-N	NF/S-L, 40V, 5A, 87,5W, >4MHz	23a	BD 317	23a
2 N 5068	Si-N	=2N5067: 60V	23a	BD 317	23a
2 N 5069	Si-N	=2N5057: 80V	23a	BD 317	23a
2 N 5086	Si-P	NF, ra, 50V, 0,05A, 0,625W, B>150	7e	BC 560	7a
2 N 5087	Si-P	=2N5086: B>250	7e	BC 560	7a
2 N 5088	Si-N	NF, ra, 35V, 0,05A, 0,625W, B>300	7e	BC 550	7a
2 N 5089	Si-N	=2N5088: 30V, B>400	7e	BC 550	7a
2 N 5126	Si-N	HF/ZF, re, 20V, 0,03A, 0,2W, >300MHz	8a	BF 255	7d
2 N 5127	Si-N	HF/ZF, 20V, 0,1A, 0,2W, >150MHz	8a	BF 255	7d
2 N 5172	Si-N	Uni, 25V, 0,1A, 0,36W, 200MHz	7c	BC 546	7a
2 N 5179	Si-N	VHF/UHF, ra, 20V, 0,05A, 0,2W, 1400MHz	5g	2SC2570 A	7f
2 N 5190	Si-N	NF/S-L, 40V, 4A, 40W, >2MHz	14h	BD 189	14h
2 N 5191	Si-N	=2N5190: 60V	14h	BD 189	14h
2 N 5192	Si-N	=2N5190: 80V	14h	BD 189	14h
2 N 5193	Si-P	NF/S-L, 40V, 4A, 40W, >2MHz	14h	BD 190	14h
2 N 5194	Si-P	=2N5193: 60V	14h	BD 190	14h
2 N 5195	Si-P	=2N5193: 80V	14h	BD 190	14h
2 N 5208	Si-P	FM/VHF, ra, 30V, 0,05A, 0,35W, >300MHz	7f	BF 324	7a
2 N 5245	N-FET	VHF, 30V, Idss>5mA, Up<6V	7f	BF 245	7f
2 N 5246	N-FET	VHF, 30V, Idss>1,5mA, Up<4V	7f	BF 245	7f
2 N 5247	N-FET	VHF, 30V, Idss>8mA, Up<8V	7f	BF 245	7f
2 N 5248	N-FET	VHF, 30V, Idss>4mA, Up<8V	7e	BF 245	7f
2 N 5293	Si-N	NF/S-L, 80V, 4A, 36W, >0,8MHz	17j	BD 243 C	17j
2 N 5294	Si-N	NF/S-L, 80V, 4A, 36W, >0,8MHz	17j	BD 243 C	17j
2 N 5295	Si-N	NF/S-L, 60V, 4A, 36W, >0,8MHz	17j	BD 243 C	17j
2 N 5296	Si-N	NF/S-L, 60V, 4A, 36W, >0,8MHz	17j	BD 243 C	17j
2 N 5297	Si-N	NF/S-L, 80V, 4A, 36W, >0,8MHz	17j	BD 243 C	17j
2 N 5298	Si-N	NF/S-L, 80V, 4A, 36W, >0,8MHz	17j	BD 243 C	17j
2 N 5320	Si-N	NF/S, 100V, 2A, 10W(Tc=25°), <80/800ns	2a	(2SC4135)	30j 4
2 N 5321	Si-N	=2N5320: 75V	2a	(2SC4135)	30j 4
2 N 5322	Si-P	NF/S, 100V, 2A, 10W(Tc=25°), <100/1000ns	2a	(2SA1593)	30j 4
2 N 5323	Si-P	=2N5322: 75V	2a	(2SA1593)	30j 4
2 N 5415(S)	Si-P	S/Vid, 200V, 1A, 10W(Tc=25°), >15MHz	2a	(MPSU 60)	13m 6
2 N 5416	Si-P	S/Vid, 350V, 1A, 10W(Tc=25°), >50MHz	2a	(MPSU 60)	13m 6
2 N 5447	Si-P	Uni, 40V, 0,2A, 0,3W, >100MHz	7a	BC 327	7a
2 N 5448	Si-P	Uni, 50V, 0,2A, 0,3W, >100MHz	7a	BC 327	7a
2 N 5449	Si-N	Uni, 50V, 0,8A, 0,36W, >100MHz	7a	BC 337	7a
2 N 5450	Si-N	Uni, 50V, 0,8A, 0,36W, >100MHz	7a	BC 337	7a
2 N 5451	Si-N	Uni, 40V, 0,8A, 0,36W, >100MHz	7a	BC 337	7a
2 N 5457	N-FET	Uni, sym, 25V, Idss>1mA, Up<6V	7d	BF 245	7f
2 N 5458	N-FET	Uni, sym, 25V, Idss>2mA, Up<7V	7d	BF 245	7f
2 N 5459	N-FET	Uni, sym, 25V, Idss>4mA, Up<8V	7d	BF 245	7f
2 N 5460	P-FET	Uni, ra, 40V, Idss>1mA, Up<6V	7c	-	-
2 N 5461	P-FET	Uni, ra, 40V, Idss>2mA, Up<7,5V	7c	-	-
2 N 5462	P-FET	Uni, ra, 40V, Idss>4mA, Up<9	7c	-	-
2 N 5463	P-FET	=2N5460: 60V	7c	-	-
2 N 5464	P-FET	=2N5461: 60V	7c	-	-
2 N 5465	P-FET	=2N5462: 60V	7c	-	-
2 N 5490	Si-N	NF/S-L, 60V, 7A, 50W, >0,8MHz	17j	BD 243 C	17j
2 N 5491	Si-N	=2N5490	17j	BD 243 C	17j
2 N 5492	Si-N	NF/S-L, 75V, 7A, 50W, >0,8MHz	17j	BD 243 C	17j
2 N 5493	Si-N	=2N5492	17j	BD 243 C	17j