

TRANSISTOR NUMBER	PM OA LT	PACK-AGE	LEAD INFO	VCB MAX	VCE MAX	VEB MAX	I C MAX	T J MAX	P TOT	F T MIN	C OB MAX	H FE	H FE BIAS	USE	MFR	EUR EQUIV	USA EQUIV	ISS
25C204	NS	T018	L01	20V		3V	200MA	175C	350MWF	175M	8P	60TP	1MA	RLG	FUJ	BSW64	2N2222A	0
25C205	NS	T018	L01	80V		5V	200MA	175C	350MWF	175M	8P	60TP	1MA	RLG	FUJ	BSW64	2N2222A	0
25C206	NS	T072	L06	20V		2V	25MA	185C	200MWF	100M	3P	35TP	2MA	VLA	FUJ	BFX73	2N918	0
25C207	NS	T072	L06	20V		3V	25MA	175C	200MWF	400M		40MN	2MA	VLA	FUJ	BFX73	2N918	1
25C208	NS	T072	L06	20V		3V	25MA	175C	200MWF	275M		30MN	2MA	VLA	FUJ	BFX73	2N918	1
25C209	NS	T072	L06	20V		3V	25MA	175C	200MWF	225M		20MN	2MA	VLA	FUJ	BFX73	2N918	1
25C210	NS	T05	L04	50V		5V	500MA	175C	650MWF	75M	30P	50TP	20MA	AMG	FUJ	BFY50	2N2297	0
25C211	NS	T05	L04	25V		5V	500MA	175C	650MWF	75M	30P	50TP	20MA	AMG	FUJ	BFY50	2N2297	0
25C212	NS	T05	L04	80V		5V	500MA	175C	650MWF	75M	30P	50TP	20MA	AMH	FUJ	BSW66	2N1893	0
25C213	NS	T08	L12	50V		5V	600MA	175C	1500MWF	75M	30P	20MN	10MA	VHG	FUJ		2N2782	0
25C214	NS	T08	L12	25V		5V	600MA	175C	1500MWF	75M	30P	20MN	10MA	VHG	FUJ		2N2782	0
25C215	NS	T08	L12	80V		5V	600MA	175C	1500MWF	75M	30P	20MN	10MA	VHH	FUJ		2N2782	0
25C216	NS	T05	L04	50V	25V	5V	300MA	175C	650MWF	100M		50TP	50MA	AMG	FUJ	BFY50	2N2297	0
25C217	NS	T05	L04	25V	18V	5V	300MA	175C	650MWF	100M		50TP	50MA	AMG	FUJ	BFY50	2N2297	0
25C218	NS	T05	L04	80V	40V	5V	300MA	175C	650MWF	100M		50TP	50MA	AMH	FUJ	BSW66	2N1893	0
25C219	NS	T072	L06	20V		5V	25MA	175C	200MWF	300M		30MN	3MA	ULA	OBS	BFX73	2N918	1
25C220	NS	T05	L04	50V		5V	700MA	175C	650MWF	75M	30P	50TP	20MA	AMG	FUJ	BFY50	2N2297	0
25C221	NS	T05	L04	25V		5V	700MA	175C	650MWF	75M	30P	50TP	20MA	AMG	FUJ	BFY50	2N2297	0
25C222	NS	T05	L04	80V		5V	700MA	175C	650MWF	75M	30P	50TP	20MA	AMH	FUJ	BSW66	2N1893	0
25C223	NS	T08	L12	50V		5V	1A	175C	1500MWF	75M	30P	20MN	10MA	VHG	FUJ		2N2782	0
25C224	NS	T08	L12	25V		5V	1A	175C	1500MWF	75M	30P	20MN	10MA	VHG	FUJ		2N2782	0
25C225	NS	T08	L12	80V		5V	1A	175C	1500MWF	75M	30P	20MN	10MA	VHH	FUJ		2N2782	0
25C226	NS	T05	L04	50V	40V	5V	700MA	175C	650MWF	100M		50TP	100MA	AMG	FUJ	BFY50	2N2297	0
25C227	NS	T05	L04	25V	20V	5V	700MA	175C	650MWF	100M		50TP	100MA	AMG	FUJ	BFY50	2N2297	0
25C228	NS	T05	L04	80V	50V	5V	700MA	175C	650MWF	100M		50TP	100MA	AMH	FUJ	BSW66	2N1893	0
25C229	NS	T08	L12	80V	60V	5V	1A	175C	1500MWF	75M	30P	30TP	100MA	VHG	FUJ		2N2782	0
25C230	NS	T018	L01	80V		3V	200MA	175C	350MWF	175M	8P	60TP	1MA	ALG	FUJ	BC107	A157	0
25C231	NS	T05	L04	50V	40V	5V	700MA	175C	650MWF	100M		40TP	150MA	AMG	FUJ	BFY50	2N2297	0
25C232	NS	T05	L04	25V	20V	5V	700MA	175C	650MWF	100M		40TP	150MA	AMG	FUJ	BFY50	2N2297	0
25C233	NS	T05	L04	80V	60V	5V	700MA	175C	650MWF	100M		40TP	150MA	AMH	FUJ	BSW66	2N1893	0
25C234	NS	T08	L12	100V	60V		1500MA	175C	1800MWF	70M		20TP	150MA	VHG	FUJ		2N2782	0
25C235	NS	T08	L12	100V	60V		1500MA	175C	1800MWF	60M		20TP	150MA	VHG	FUJ		2N2782	0
25C236	NS	T08	L12	90V	50V		500MA	175C	1800MWF	50M		17TP	20MA	VHG	FUJ		2N2782	0
25C237	NS	T018	L01	25V	18V	5V	300MA	175C	350MWF	225M	9P	80TP	1MA	AMG	FUJ	BSW64	2N2222A	0
25C238	NS	T05	L04	30V		3V5	100MA	150C	500MWF	150M	9P	80TP	1MA	ALG	FUJ	BSW54	2N2219A	0
25C239	NS	T018	L01	30V	20V	5V	300MA	175C	350MWF	225M	9P	80TP	1MA	AMG	FUJ	BSW64	2N2222A	0
25C240	NS	T03	L05	100V	65V	5V	5A	175C	75WC	18M		15/35	1A	AHG	NIP	BU123		0
25C241	NS	T03	L05	60V	40V	5V	5A	175C	75WC	18M		15/35	1A	AHG	NIP	BU123		0
25C242	NS	T03	L05	100V	65V	5V	5A	175C	75WC	18M		15/35	1A	AHG	NIP	BU123		0
25C243	NS	T03	L05	140V	80V	5V	5A	175C	75WC	18M		15/35	1A	AHH	NIP	BU123		0
25C244	NS	T03	L05	60V	40V	5V	6A	175C	75WC	18M		15/35	1A	AHG	OBS	BU123		0
25C245	NS	T03	L05	120V	60V	5V	6A	175C	75WC	18M		15/35	1A	AHH	OBS	BU123		0
25C246	NS	T03	L05	180V	90V	5V	6A	175C	75WC	18M		15/35	1A	AHH	OBS	BU123		0
25C247	NS	T05	L04	100V		3V	100MA	175C	600MWF	75M	6P	60TP	2MA	ALH	FUJ	BFY65	2N1990	0
25C248	NS	T018	L01	70V	40V	5V	50MA	175C	300MWF	85M	5P	60TP	2MA	ALG	FUJ	BC107	A157	0
25C249	NS	T05	L04	70V	45V	5V	70MA	175C	500MWF	85M	7P	60TP	2MA	ALG	FUJ	BFY50	2N2297	0
25C250	NS	T044	L36	20V		2V	25MA	175C	60MWF	85M	4P	45TP	2MA	VLA	FUJ	BFX73	2N918	0
25C251	NS	T072	L06	30V	15V	3V	30MA	150C	200MWF	450M	2P	50TP	5MA	VLA	NIP	BFX73	2N918	0
25C251A	NS	T072	L06	30V	15V	3V	30MA	150C	200MWF	450M	2P	50TP	5MA	VLA	NIP	BFX73	2N918	0
25C252	NS	T072	L06	30V	15V	3V	30MA	150C	200MWF	450M	2P	50TP	5MA	VLA	NIP	BFX73	2N918	0
25C253	NS	T072	L06	30V	15V	3V	30MA	150C	200MWF	450M	2P	50TP	5MA	VLA	NIP	BFX73	2N918	0
25C254	NS	T05	L04	50V	30V	5V	800MA	175C	650MWF	100M		30MN	150MA	RMG	OBS	BFY50	2N2297	1
25C255	NS	T05	L04	80V	50V	5V	800MA	175C	650MWF	100M		20MN	150MA	RMG	OBS	BSW66	2N4001	1
25C256	NS	T05	L04	90V	70V	5V	800MA	175C	650MWF	100M		20MN	150MA	RMG	OBS	BFY50	2N2297	1
25C257	NS	OBS	OBS	50V	30V	5V	800MA	175C	800MWF	100M		30MN	150MA	RMG	OBS	BFY50	2N2297	1
25C258	NS	OBS	OBS	80V	50V	5V	800MA	175C	800MWF	100M		20MN	150MA	RMG	OBS	BSW66	2N4001	1
25C259	NS	T05	L04	90V	70V	5V	800MA	175C	800MWF	100M		20MN	150MA	RMH	OBS	BSW66	2N4001	1
25C260	NS	T08	L12	30V		5V	1A	175C	1.6WF	140M		30MN	150MA	RMP	OBS			1
25C261	NS	T08	L12	60V		5V	1A	175C	1.6WF	140M		30MN	150MA	RMP	OBS			1
25C262	NS	T08	L12	80V		5V	1A	175C	1.6WF	140M		30MN	150MA	RMH	OBS			1
25C263	NS	OBS	OBS	15V		5V	120MA	100C	100MWF	200M		30MN	10MA	RLG	OBS	BSX20	2N2369	1
25C264	NS	OBS	OBS	30V		5V	120MA	100C	100MWF	200M		30MN	10MA	RLS	OBS	BSX20	2N2369	1
25C265	NS	OBS	OBS	40V		5V	120MA	100C	100MWF	200M		30MN	10MA	RLH	OBS	BSW64	2N2222	1
25C266	NS	X37		30V	20V	5V	30MA	150C	100MWF	125M		2930	500UA	ALN	NIP	BC109	2N930	1
25C267	NS	X37		35V	20V	5V	200MA	150C	150MWF	45M		30MN	20MA	ALG	NIP	BSW64	2N2222	1
25C268	NS	X37		60V	30V	5V	30MA	150C	150MWF	75M		20MN	1MA	ALE	NIP	BC107	2N1990R	1
25C269	NS	X37		25V	20V	5V	200MA	150C	150MWF	100M		40MN	1MA	RLS	NIP	BSW64	2N2222	1
25C270	NS	T03	L05	270V	75V	6V	5A	175C	50WC	10M		24/92	2A	AHE	OBS	BU122		1
25C271	NS	X37		25V	12V	3V	20MA	150C	36MWF	550M		30MN	2MA	ULA	NIP	BFX73	2N918	1
25C272	NS	X37		25V	12V	3V	20MA	150C	36MWF	600M		30MN	2MA	ULA	NIP	BFX73	2N918	1
25C273	NS	T018	L01	120V	120V	5V	1A	150C	500MWF	100M	5P	50TP	3MA	AMH	NIP	BSW66	2N1893	0
25C281	NS	T01	L02	30V	20V	5V	100MA	175C	200MWF	80M	10P	170TP	10MA	ALG	HIJ	BC107	A157	0
25C281H	NS	T01	L02	30V	20V	5V	100MA	175C	200MWF	90M	10P	170TP	10MA	ALG	HIJ	BC107	A157	0
25C282	NS	T01	L02	30V	20V	5V	100MA	175C	350MWF	90M	15P	60MN	10MA	ALG	HIJ	BC107	A157	0
25C282H	NS	T01	L02	30V	20V		100MA	175C	350MWF	100M	10P	60MN	10MA	RLS	HIJ	BC108	2N2222	2