

2 N 4915		Si-N	=2N4913: 80/80V	{2N4906	22a	TO-66			BD 245B, BDV 93, BDX 93, 2N5874, ++
2 N 4916	Fch,Nsc,Sgs	Si-P	Uni, 30/30V, 0,1A, 0,2W, >400MHz, <55/180ns		8a	TO-106	(BC 556)	7a	BSW 24, BSX 36, 2N2906...07(A), 2N4125, ++
2 N 4917		Si-P	=2N4916: >450MHz		8a	TO-106	(BC 556)	7a	BSW 24, BSX 36, 2N2906...07(A), 2N4125, ++
2 N 4918	Mot,Nsc,Sgs	Si-P	L.F.S P, 40/40V, 1/3A, 30W, >3MHz, sat<0,6V(1A) hFE=20...100	{2N4921	14h	TO-126	BD 238	14h	BD 136, BD 166, BD 176, BD 234, ++
2 N 4919		Si-P	=2N4918: 60/60V	{2N4922	14h	TO-126	BD 238	14h	BD 138, BD 168, BD 178, BD 236, ++
2 N 4920		Si-P	=2N4918: 80/80V	{2N4923	14h	TO-126	BD 238	14h	BD 140, BD 170, BD 180, BD 238, ++
2 N 4921	Mot,Nsc,Sgs	Si-N	L.F.S P, 40/40V, 1/3A, 30W, >3MHz, sat<0,6V(1A) hFE=20...100	{2N4918	14h	TO-126	BD 237	14h	BD 135, BD 165, BD 175, BD 233, ++
2 N 4922		Si-N	=2N4921: 60/60V	{2N4919	14h	TO-126	BD 237	14h	BD 137, BD 167, BD 177, BD 235, ++
2 N 4923		Si-N	=2N4921: 80/80V	{2N4920	14h	TO-126	BD 237	14h	BD 139, BD 169, BD 179, BD 237, ++
2 N 4924(S)	USA,Mot,Nsc	Si-N	Uni, 100/100V, 0,2A, 1W, >100MHz	{S: TO-39	2a	TO-5			BC 141, BC 300, 2N1889...90, 2N1893, ++
2 N 4925(S)		Si-N	=2N4924: 150/150V		2a	TO-5			BSS 48...49, 2N3439...40, 2N5010
2 N 4926	USA,Mot,Sgs	Si-N	Vid, 200/200V, 0,05A, 1W, >30MHz		2a	TO-39	BF 259	2a	BF 258...259, BF 658...659, 2N5058...59, ++
2 N 4927		Si-N	=2N4926: 250/250V		2a	TO-39	BF 259	2a	BF 258...259, BF 658...659, 2N5058...59, ++
2 N 4928(S)	USA,Mot	Si-P	Uni, 100/100V, 0,1A, 0,6W, >100MHz		2a	TO-5			BFT 44...45, 2N3634...35, 2SB606
2 N 4929(S)	USA,Mot	Si-P	Uni, 150/150V, 0,5A, 1W, >100MHz		2a	TO-5			BFT 44...45, 2N3636...37, 2SB606
2 N 4930(S)	USA,Mot	Si-P	Uni, 200/200V, 0,5A, 1W, >20MHz		2a	TO-5			BFT 44...45, 2N5415...16, 2SB606
2 N 4931(S)	USA,Mot	Si-P	Uni, 250/250V, 0,5A, 1W, >20MHz		2a	TO-5			BFT 44...45, MJ 5415...16, 2N5416, 2SB606
2 N 4932	Rca,Ssi,Tix	Si-N	FM/VHF P, 50/25V, 3,3A, PQ>12W(88MHz)		49a	TO-60			BLW 36
2 N 4933	Rca,Ssi,Tix	Si-N	FM/VHF P, 70/35V, 3,3A, PQ>20W(88MHz)		49a	TO-60			2SC1037
2 N 4934	Mic,Nsc,Sca	Si-N	VHF/UHF, 50V, 0,2W, >700MHz		5g	TO-104			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 4935	Mic,Nsc,Sca	Si-N	VHF/UHF, 50V, 0,2W, >700MHz		5g	TO-104			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 4936	Mic,Nsc,Sca	Si-N	VHF/UHF, 50V, 0,2W, >700MHz		5g	TO-104			BF 377...378, BF 689, BF 763, 2N2857, ++
2 N 4937	Mot,Ray	Si-P	Dual, In, 50/40V, 0,05A, 0,6W, 400MHz, F<4dB(1kHz) hFE=50...250, ΔhFE=0,9...1, ΔUbe<3mV		TO-77	(CBE-EBC-)			2N3726...27, 2N4015...16
2 N 4938		Si-P	=2N4937: ΔhFE=0,8...1, ΔUbe<5mV		TO-77	(CBE-EBC-)			2N3726...27, 2N4015...16
2 N 4939		Si-P	=2N4937: ΔhFE=0,7...1, ΔUbe=5mV		TO-77	(CBE-EBC-)			2N3726...27, 2N4015...16
2 N 4940		Si-P	=2N4937: 0,35W		10-FLP	TO-89			-
2 N 4941		Si-P	=2N4938: 0,35W		10-FLP	TO-89			-
2 N 4942		Si-P	=2N4938: 0,35W		10-FLP	TO-89			-
2 N 4943	USA,Mic,Nsc	Si-N	L.F.S, 120/80V, 1A, 0,8W, >150MHz		2a	TO-5			BSS 42...43, BSW 67...68, BSX 47, 2N2102, ++
2 N 4944	USA,Nsc,Sgs	Si-N	Uni, 80/40V, 0,5A, 0,22W, >60MHz, hFE=40...120		8a	TO-106			BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 4945		Si-N	=2N4944: 80/60V		8a	TO-106			BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 4946		Si-N	=2N4944: hFE=100...300		8a	TO-106			BC 639, BCX 24, 2N3700...01, 2SD667, ++
2 N 4947	Mot,Tix	UJT-P	35/30V, 50mA, iEM=1A, 0,36W, Ip<2μA, Iv>2mA, η=0,51...0,69, Rbb=4...12kΩ		2e	TO-72			2N4851, 2N4948, 2N4893
2 N 4948		UJT-P	=2N4947: η=0,55...0,82		2e	TO-72			2N4851, 2N4947, 2N4893
2 N 4949		UJT-P	=2N4947: Ip<1μA, η=0,74...0,86		2e	TO-72			2N4894
2 N 4950	USA	Si-N	S P, 80/60V, 70A, 200W, >0,1MHz, <10/20μs		49m	TO-114			2N6309...11
2 N 4951	USA,Nsc,Tho	Si-N	Uni, 60/30V, 0,5A, 0,36W, 250MHz, hFE=60...200		7c	TO-98			BC 337A, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4952		Si-N	=2N4951: hFE=100...300		7c	TO-98			BC 337A, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4953		Si-N	=2N4951: hFE=200...600		7c	TO-98			BC 337A, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4954		Si-N	=2N4951: 40/30V		7c	TO-98			BC 337, BC 635, BSV 59, 2N2221...22(A), ++
2 N 4955(/78)	Isi,Fch,Sca Sgs	Si-N	Dual, 30/25V, 0,03A, 0,45W, >60MHz, F<4,5dB(1kHz) hFE>150, ΔhFE=, ΔUbe=		TO-77	(CBE-EBC-)			2N3409...11
2 N 4956(/78)		Si-N	=2N4955: ΔhFE=0,8...1, ΔUbe<5mV		TO-77	(CBE-EBC-)			2N3409...11
2 N 4957	Mot,Sca,Tho	Si-P	UHF, In, 30V, 0,03A, 0,2W, 1600MHz		5g	TO-72			BF 439, BF 516, BF 606, BFR 38, BFR 99, ++
2 N 4958	Mot,Sca,Tho	Si-P	UHF, In, 30V, 0,03A, 0,2W, 1500MHz		5g	TO-72			BF 439, BF 516, BF 606, BFR 38, BFR 99, ++
2 N 4959	Mot,Sca,Tho	Si-P	UHF, In, 30V, 0,03A, 0,2W, 1500MHz		5g	TO-72			BF 439, BF 516, BF 606, BFR 38, BFR 99, ++
2 N 4960	Fch,Sca,Ssi	Si-N	Uni, 60/60V, 1A, 0,8W, >250MHz, <175/1050ns		2a	TO-39			BC 140...141, BSW 65...68, BSX 45...47, ++
2 N 4961		Si-N	=2N4960: 80/80V		2a	TO-39			BC 140...141, BSW 65...68, BSX 45...47, ++
2 N 4962		Si-N	=2N4960: 0,5W		2a	TO-18			BC 637, BSS 40...41, BSX 33, 2SD774, ++
2 N 4963		Si-N	=2N4960: 80/80V, 0,5W		2a	TO-18			BC 639, BSS 59, BSX 33, 2SD774, ++
2 N 4964	Fch,Mic,Nsc	Si-P	Uni, 50/40V, 0,1A, 0,2W, >60MHz, hFE=30...120		8a	TO-106			BC 212, BC 257, BC 307, BC 557, ++
2 N 4965		Si-P	=2N4964: hFE=80...400		8a	TO-106			BC 212, BC 257, BC 307, BC 557, ++
2 N 4966	Fch,Mic,Nsc	Si-N	Uni, 50/40V, 0,03A, 0,2W, >40MHz, hFE=40...200		8a	TO-106			BC 167, BC 182, BC 237, BC 547, ++
2 N 4967		Si-N	=2N4966: hFE=100...600		8a	TO-106			BC 167, BC 182, BC 237, BC 547, ++
2 N 4968		Si-N	=2N4966: 30/25V		8a	TO-106			BC 168, BC 183, BC 238, BC 548, ++
2 N 4969	Fch,Mic,Nsc	Si-N	Uni, 50/30V, 0,5A, 0,2W, >200MHz, hFE=40...120		8a	TO-106			BC 337, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4970		Si-N	=2N4969: hFE=100...350		8a	TO-106			BC 337, BC 637, BSV 59, 2N2221...22(A), ++
2 N 4971	Fch,Mic,Nsc	Si-P	Uni, 50/40V, 0,5A, 0,2W, >200MHz, hFE=40...120		8a	TO-106			BC 327, BC 638, BSW 24, 2N2906...07(A), ++
2 N 4972		Si-P	=2N4971: hFE=100...300		8a	TO-106			BC 327, BC 638, BSW 24, 2N2906...07(A), ++
2 N 4973	Ray	Si-P	VHF/UHF, 20V, 0,03A, 0,2W, >800MHz		8a	TO-106			BF 316, BF 439, BF 516, BF 606, BFR 38, ++
2 N 4974	Mot,Ray	Si-P-Darl	Uni, 40/30V, 1A, 0,8W, hFE>25000		5	TO-12			-
2 N 4975		Si-P-Darl	=2N4974: hFE>15000		5	TO-12			-
2 N 4976	Trw	Si-N	UHF P, 55/30V, 0,4A, 5W, >1GHz		55v				(BLW 90, MRF 5174) ⁵
2 N 4977	USA,Tho,Tix	N-FET	S, Chopper, 30V, Idss>50mA, Up<10V		2b	TO-18			BFS 74, BFS 77, BSV 78, 2N3970, 2N4391, ++
2 N 4978	USA,Tho,Tix	N-FET	S, Chopper, 30V, Idss>15mA, Up<8V		2b	TO-18			BFS 75, BFS 78, BSV 79, 2N4857, 2N4092, ++
2 N 4979	USA,Tho,Tix	N-FET	S, Chopper, 30V, Idss>7,5mA, Up<5V		2b	TO-18			BFS 76, BFS 79, BSV 80, 2N4858, 2N4093, ++
2 N 4980	Tdy	Si-P	Chopper, 30/30/30V, 0,1A, 0,4W		2a	TO-46			2N2946
2 N 4981	Tdy	Si-P	Chopper, 50/50/50V, 0,1A, 0,4W		2a	TO-46			-
2 N 4982	Tdy	Si-P	Chopper, 70/70/70V, 0,1A, 0,4W		2a	TO-46			-
2 N 4983	Gen	SUS	-30V, 0,175A, Itsm=5A, 0,3W, Ub=6...10V, Is<0,5mA		2d(AKG)	TO-18			-
2 N 4984	Gen	SUS	-30V, 0,2A, Itsm=5A, 0,35W, Ub=7,5...9V, Is<0,15mA		2d(AKG)	TO-18			-
2 N 4985	Gen	SUS	-30V, 0,2A, Itsm=5A, 0,35W, Ub=7,5...8,2V, Is<0,3mA		2d(AKG)	TO-18			-
2 N 4986	Gen	SUS	-30V, 0,175A, Itsm=5A, 0,3W, Ub=7...9V, Is<0,2mA		2d(AKG)	TO-18			-
2 N 4987	Gen	SUS	=2N4983:		7a(KGA)	TO-98			-
2 N 4988	Gen	SUS	=2N4984:		7a(KGA)	TO-98			-
2 N 4989	Gen	SUS	=2N4985:		7a(KGA)	TO-98			-
2 N 4990	Gen	SUS	=2N4986:		7a(KGA)	TO-98			-
2 N 4991	Gen	SBS	0,175A, Itsm=5A, 0,3W, Ub=6...10V, Is<0,5mA		7m(AGA)	TO-98			-
2 N 4992	Gen	SBS	0,2A, Itsm=5A, 0,35W, Ub=7,5...9V, Is<0,12mA		7m(AGA)	TO-98			BS 08A, N313
2 N 4993	Gen	SBS	0,2A, Itsm=5A, 0,35W, Ub=6...10V, Is<0,5mA		7m(AGA)	TO-98			-
2 N 4994	Gen,Mic,Tix	Si-N	H.F.I.F, 60V, 0,3A, 0,36W, 300MHz, hFE=40...160		7a	SOT-30			BF 240...241, BF 254...255, BF 594...595, ++
2 N 4995		Si-N	=2N4994: hFE=100...400		7a	SOT-30			BF 240...241, BF 254...255, BF 594...595, ++
2 N 4996	Mic,Sca,Tix	Si-N	VHF, 30V, 0,05A, 0,25W, >600MHz, hFE>50		7a	SOT-30			BF 314, BF 502, BF 505, BF 507, BF 562, ++
2 N 4997		Si-N	=2N4996: hFE=30...150		7a	SOT-30			BF 314, BF 502, BF 505, BF 507, BF 562, ++
2 N 4998	USA,Tix	Si-N	S P, 100/80V, 2/5A, 30W(Tc=50°), >50MHz, 100/1100ns hFE=30...90	{2N4999	49a	TO-59			2N5002, 2N5004, 2N5284...85
2 N 4999	USA,Tix	Si-P	S P, 100/80V, 2/5A, 30W(Tc=50°), >50MHz, 100/1100ns hFE=30...90	{2N4998	49a	TO-59			2N5003, 2N5005, 2N5286...87
2 N 5000		Si-N	=2N4998: >60MHz, hFE=70...200	{2N5001	49a	TO-59			2N5002, 2N5004, 2N5284...85